



ROHDE & SCHWARZ

Test and Measurement
Division

Release Notes

1xEV-DO Mobile Station Test

Application Firmware R&S FS-K85

Release 4.60SP1

for R&S FSP, FSU, FSQ, FSG, FSMR, FSUP
Analyzer Firmware 4.6x

Release Note Revision: 1

Printed in the Federal
Republic of Germany

Contents

| | |
|---|---|
| History | 2 |
| General Topics..... | 3 |
| Compatibility of R&S FS-K85 1xEV-DO MS Application Firmware..... | 3 |
| Firmware Update of R&S FS-K85 1xEV-DO MS Application Firmware | 4 |
| Enabling the Application Firmware via License Key Code Entry | 4 |
| New Functions in version 4.60SP1 | 4 |
| Improvements | 4 |
| Known Issues | 4 |
| Modified Functions..... | 5 |
| Modifications to the Operating Manual and Supplements..... | 6 |
| Modified Chapters | 6 |
| Customer Support | 6 |
| Technical support – where and when you need it | 6 |
| Up-to-date information and upgrades..... | 6 |

History

| Date | Rel Note Rev | Changes |
|------------------|--------------|---|
| 22 November 2012 | 1 | First revision for R&S FS-K85 Firmware 4.60SP1. |

General Topics

Compatibility of R&S FS-K85 1xEV-DO MS Application Firmware

The following table shows the compatible version of the basic spectrum firmware version and the 1xEV-DO MS application firmware:

Table of compatible versions:

| R&S FS-K85 Application Firmware | R&S FSP Basic Firmware | R&S FSU Basic Firmware | R&S FSQ Basic Firmware | R&S FSMR Basic Firmware | R&S FSUP Basic Firmware | R&S FMU Basic Firmware | R&S FSG Basic Firmware |
|---------------------------------------|------------------------------|------------------------------|------------------------------|-------------------------------|--|------------------------------|------------------------------|
| 4.60SP1 | - | - | - | - | Please refer to the FSUP release notes | - | - |
| 4.60 | - | 4.61 | 4.65 | - | | - | 4.69 |
| 4.50 | 4.50 | 4.51 | 4.55 | - | | - | 4.59 |
| 4.40 SP1 | - | - | - | - | | - | - |
| 4.40 | 4.40 | 4.41 | 4.45 | - | | - | 4.49 |
| 4.30 | 4.30 | 4.31 | 4.35 | 4.36 | | 4.38 | 4.39 |
| 4.21 | 4.20 | 4.21 | 4.25 | 4.26 | | - | 4.29 SP1 |
| 4.20 | - | - | - | - | | - | 4.29 |
| 4.10 | 4.10 | 4.11 | 4.15 | 4.16 | | - | - |
| 4.00 | 4.00 | 4.01 | 4.05 | 4.06 | | - | - |
| 3.90 | 3.90 | 3.91 | 3.95 | 3.96 | | - | - |
| 3.80 | 3.80 | 3.81 | 3.85 | 3.86 | | - | - |
| 3.70 | 3.70 | 3.71 | 3.75 | - | | - | - |
| 3.60 | 3.60 | 3.61 | 3.65 | 3.66 SP1 | | - | - |
| 3.50 | 3.50 | 3.51 | 3.55 | - | | - | - |
| 3.40 | 3.40 | 3.41 | 3.45 | - | | - | - |
| 3.30 | 3.30 | 3.31 | 3.35 | - | | - | - |
| 2.80 | 2.80 | 2.81 | - | - | | - | - |
| 2.60 | 2.60 | 2.61 | - | - | | - | - |
| 2.40 | 2.40 | 2.41 | 2.45 | - | | - | - |
| 2.30 | 2.30 | 2.31 | 2.35 | - | | - | - |

Application firmware versions 3.xx are running on R&S FSPs with order # 1164.4391.xx or R&S FSU with order # 1166.1660.xx or R&S FSQ with operating system XP.

Application firmware version 2.xx are running on R&S FSPs with order # 1093.4495.xx or R&S FSU with order # 1129.9003.xx or R&S FSQ with operating system NT.

Firmware Update of R&S FS-K85 1xEV-DO MS Application Firmware

Since basic firmware version 4.2x a ZIP file with the update sets of the basic system firmware and all available applications is provided. This ZIP file is available in the instruments FIRMWARE section, e.g. R&S FSU of the Service Board on GLORIS.

Please follow the steps described in the instrument's basic firmware release note to perform a complete firmware update.

Enabling the Application Firmware via License Key Code Entry

This section can be skipped if the option key was entered once.

After installing the application firmware package a license key for validation must be entered. The license key is printed either on a label on the rear panel of the analyzer or delivered as a part of the R&S FS-K85 1xEV-DO MS application firmware package.

The key sequence for entering the license key is:

SETUP - GENERAL SETUP – OPTIONS - INSTALL OPTION

Use the numeric keypad to input the license key number and press ENTER.

- On successful validation the message 'option key valid' will appear.
- If the validation failed, the application firmware will not be installed.
The most likely reason will be that the instrument is not equipped with the correct basic firmware version. In this case a message box will appear asking for installation of the correct basic firmware version.
If the application firmware package was not installed prior to entering the license key code, a message will appear asking for installation of the application firmware package.
In any case please make sure that the correct basic firmware version and the application firmware package is installed prior to entering the license key code.

New Functions in version 4.60SP1

None.

Improvements

None.

Known Issues

None.

Modified Functions

The version numbers in brackets indicate the version in which the function was modified

- 1) [V2.40/3.40] **Sign change for frequency offset, phase offset and q-inversion for symbol constellation and bitstream.**
Due to a correction of the cdma2000 specific -q definition, the mention values had been changed
- 2) [V3.50] **Remote command : [SENSe:]CDPower:ORDER? Delivers now short form HAD or BITR as result.**
- 3) [V3.50] **CDP measurement over 3648 consecutive half slots for R&S FSQ possible (over 3 seconds of IQ data).**
- 4) [V3.60/V2.60] **External trigger level adjustable from 0.5 to 3.5V.**
- 5) [V3.60/V2.60] **Carrier frequency step size softkey available.**
- 6) [V2.60/3.60] **Changed SCPI commands.**
In order to limit to 12 chars the commands
:CALCulate2:FEED 'XTIME:CDPower:SYMBOL:CONStellation' and
:CALCulate2:FEED 'XTIME:CDPower:COMPOSITE:CONStellation'
are changed to
:CALCulate2:FEED 'XTIME:CDPower:SYMBOL:CONSt' and
:CALCulate2:FEED 'XTIME:CDPower:COMPOSITE:CONSt'.
- 7) [V3.70/V2.80] **ACP: number of adjacent channels increased to 12.**
- 8) [V3.70/V2.80] **ACP: power mode to max holds the power results.**
- 9) [V3.80/V2.80] **Trace view available within code domain analyzer.**
- 10) [V4.00] **Spectrum emission mask: List evaluation in lower screen now supported.**
- 11) [V4.20] **Support for instrument R&S FSG.**
- 12) [V4.20] **Softkey REF VALUE Y AXIS available for CDP measurements.**
- 13) [V4.21] **Band Classes 14 and 15 supported.**
- 14) [V4.30] **Softkey AC / DC Coupling available.**
- 15) [V4.30] **New Ref Value Y Axis / Reference Level coupling simplifies grid scaling configuration for Code Domain measurements.**
Since version 4.20 the Reference Level and the grid scaling (REF VALUE Y AXIS) with unit dBm can be independently set for Code Domain measurements. In previous versions changing the Reference Level and changing the Ref Value Y Axis were independent. If the Reference Level value is changed the Ref Value Y Axis is now automatically adjusted to keep the difference between Reference Level and Ref Value Y axis constant.
Example:
Ref Level set to 0 dBm
Ref Value Y axis set to -10 dBm (at Y Axis Position 100%)
► The upper Y limit of the grid scaling is now at 10 dB below reference level.
Change Reference Level to -10dBm
The Ref Value Y Axis is now adjusted to -20 dB
► The upper Y limit of the grid scaling is at 10 dB below reference level as before.
Note: The internal reference level change with function ADJUST REF LEVEL is treated in the same way.

Modifications to the Operating Manual and Supplements

For the R&S FS-K85 1xEV-DO MS Application Firmware manuals please refer to the following order numbers:

- 1007.9800.44-04 (English)
- 1007.9800.42-04 (German)

They can be downloaded from R&S internet – search: FS-K85:

<http://www.rohde-schwarz.com>

Modified Chapters

None.

Customer Support

Technical support – where and when you need it

For quick, expert help with any Rohde & Schwarz equipment, contact one of our Customer Support Centers. A team of highly qualified engineers provides telephone support and will work with you to find a solution to your query on any aspect of the operation, programming or applications of Rohde & Schwarz equipment.

Up-to-date information and upgrades

To keep your instrument up-to-date and to be informed about new application notes related to your instrument, please send an e-mail to the Customer Support Center stating your instrument and your wish. We will take care that you will get the right information.

Europe, Africa, Middle East

Phone +49 89 4129 12345
customersupport@rohde-schwarz.com

North America

Phone 1-888-TEST-RSA (1-888-837-8772)
customer.support@rsa.rohde-schwarz.com

Latin America

Phone +1-410-910-7988
customersupport.la@rohde-schwarz.com

Asia/Pacific

Phone +65 65 13 04 88
customersupport.asia@rohde-schwarz.com