

R&S[®]SMCVB-KS13

ATSC & Mobile DTV Streams

User Manual



1179267702
Version 02

ROHDE & SCHWARZ
Make ideas real



This document describes the following software options:

- R&S®SMCVB-KS13 ATSC & Mobile DTV Streams (1434.5011.xx)

© 2022 Rohde & Schwarz GmbH & Co. KG
Muehldorfstr. 15, 81671 Muenchen, Germany
Phone: +49 89 41 29 - 0

Email: info@rohde-schwarz.com

Internet: www.rohde-schwarz.com

Subject to change – data without tolerance limits is not binding.

R&S® is a registered trademark of Rohde & Schwarz GmbH & Co. KG.

Trade names are trademarks of the owners.

1179.2677.02 | Version 02 | R&S®SMCVB-KS13

The following abbreviations are used throughout this manual: R&S®SMCV100B is abbreviated as R&S SMCV100B.

Contents

1	Welcome to the R&S SMCVB-KS13 option.....	5
1.1	Key features.....	5
1.2	Installation.....	5
1.3	What's new.....	5
1.4	Documentation overview.....	5
1.4.1	Getting started manual.....	6
1.4.2	User manuals and help.....	6
1.4.3	Service manual.....	6
1.4.4	Instrument security procedures.....	6
1.4.5	Printed safety instructions.....	6
1.4.6	Data sheets and brochures.....	7
1.4.7	Release notes and open source acknowledgment (OSA).....	7
1.4.8	Application notes, application cards, white papers, etc.....	7
2	Available DTV stream files.....	8
2.1	Transport stream files list, ordered by disk number.....	8
2.2	3ServESG_RS24_HHQQ_5Slots.ATSC_C.....	10
2.3	1Serv_RS24_HHQQ_5Slots.ATSC_C.....	11
2.4	1Serv_RS48_QHHQ_5Slots.ATSC_C.....	11
2.5	1Serv_RS48_HHHH_5Slots.ATSC_C.....	12
2.6	3Ens_RS48.ATSC_C.....	12
2.7	3Ens_RS48_RS36_RS24.ATSC_C.....	13
2.8	1Ens_Separated_RS24_RS48.ATSC_C.....	14
2.9	3Ens_AutoFEC_All.ATSC_C.....	14
2.10	3Ens_AutoFEC_RS.ATSC_C.....	15
2.11	3Ens_AutoFEC_SCCC.ATSC_C.....	16
2.12	3Ens_AutoFEC_SCCC_BlockMode.ATSC_C.....	17
2.13	Referencestream.atsc_c.....	18
2.14	BCAST_1.0_DIST_INT_103.ATSC_C.....	18
2.15	BCAST_1.0_DIST_INT_107.ATSC_C.....	19
2.16	BCAST_1.0_DIST_INT_111.ATSC_C.....	20
2.17	CEA_CON_103_Stream1.ATSC_C.....	20

2.18	CEA_CON_103_Stream3.ATSC_C.....	21
2.19	CEA_CON_104.ATSC_C.....	22
2.20	CEA_IOP_100_101_109.ATSC_C.....	22
2.21	CEA_IOP_103.ATSC_C.....	23
2.22	CEA_IOP_104.ATSC_C.....	24
2.23	CEA_IOP_105.ATSC_C.....	24
2.24	CEA_IOP_106.ATSC_C.....	25
2.25	CEA_IOP_106a.ATSC_C.....	26
2.26	CEA_IOP_106b.ATSC_C.....	26
	Index.....	28

1 Welcome to the R&S SMCVB-KS13 option

The R&S SMCVB-KS13 is a stream library that provides stream files in accordance with the ATSC digital standard.

This user manual contains a reference description of the functionality that the stream library provides. All functions not discussed in this manual are described in the R&S SMCV100B user manual. The latest version is available at:

www.rohde-schwarz.com/manual/SMCV100B

1.1 Key features

The R&S SMCVB-KS13 features:

- Numerous stream files in accordance with ATSC digital standard
- Streaming of high-quality video contents
- Streaming of high-quality audio contents
- Efficient use with dedicated streams

1.2 Installation

You can find detailed installation instructions in the supplement document of the R&S SMCV100B user manual and in the R&S SMCV100B user manual describing firmware versions FW 4.90.002.xx and later of the R&S SMCV100B.

1.3 What's new

Compared to the previous version there are editorial changes only.

1.4 Documentation overview

This section provides an overview of the R&S SMCV100B user documentation. Unless specified otherwise, you find the documents on the R&S SMCV100B product page at:

www.rohde-schwarz.com/manual/smcv100b

1.4.1 Getting started manual

Introduces the R&S SMCV100B and describes how to set up and start working with the product. Includes basic operations, typical measurement examples, and general information, e.g. safety instructions, etc. A printed version is delivered with the instrument.

1.4.2 User manuals and help

Separate manuals for the base unit and the software options are provided for download:

- **Base unit manual**
Contains the description of all instrument modes and functions. It also provides an introduction to remote control, a complete description of the remote control commands with programming examples, and information on maintenance, instrument interfaces and error messages. Includes the contents of the getting started manual.
- **Software option manual**
Contains the description of the specific functions of an option. Basic information on operating the R&S SMCV100B is not included.

The contents of the user manuals are available as help in the R&S SMCV100B. The help offers quick, context-sensitive access to the complete information for the base unit and the software options.

All user manuals are also available for download or for immediate display on the Internet.

1.4.3 Service manual

Describes the performance test for checking compliance with rated specifications, firmware update, troubleshooting, adjustments, installing options and maintenance.

The service manual is available for registered users on the global Rohde & Schwarz information system (GLORIS):

<https://gloris.rohde-schwarz.com>

1.4.4 Instrument security procedures

Deals with security issues when working with the R&S SMCV100B in secure areas. It is available for download on the Internet.

1.4.5 Printed safety instructions

Provides safety information in many languages. The printed document is delivered with the product.

1.4.6 Data sheets and brochures

The data sheet contains the technical specifications of the R&S SMCV100B. It also lists the options and their order numbers and optional accessories.

The brochure provides an overview of the instrument and deals with the specific characteristics.

See www.rohde-schwarz.com/brochure-datasheet/smcv100b

1.4.7 Release notes and open source acknowledgment (OSA)

The release notes list new features, improvements and known issues of the current firmware version, and describe the firmware installation.

The open-source acknowledgment document provides verbatim license texts of the used open source software.

See www.rohde-schwarz.com/firmware/smcv100b

1.4.8 Application notes, application cards, white papers, etc.

These documents deal with special applications or background information on particular topics.

See www.rohde-schwarz.com/application/smcv100b

2 Available DTV stream files

The ATSC A/153 standard has a logical separation between the preprocessor and postprocessor.

The preprocessor calculates an M/H-specific expanded Reed Solomon code and a serial concatenated convolutional code (SCCC), and creates the frame groups and packet formats. In the packet multiplexer, the M/H data is derived. Then, it is combined with the conventional ATSC data (the main service multiplex) into a single data stream. At the end, it is stuffed into the required data rate of 19.392658 Mbit/s. The postprocessor synchronizes with this data stream and calculates the rest of the FEC components. The postprocessor is implemented exclusively in the R&S SFE and R&S SFU systems.

The ATSC / ATSC & mobile DTV streams option is therefore an external code replacement for the main and M/H service, the preprocessor and finally the multiplexer. Different files are available for the different preprocessor settings.

All streams include one legacy ATSC SD/HD program as main service multiplex and mobile content with at least one M/H service. Some of the streams allow SFN transmitter synchronization by carrying synchronization data over the dummy data bytes channel and also over the OMP transmission control packet (TCP) (ATSC A/110:2011).

The PID of the mobile content can vary depending on the selected file. Therefore every stream is associated with a script file (*.scpi) that passes a correct MHE PID setting to the TX application when the stream is opened in the player.

The streams described in the chapters [Chapter 2.9, "3Ens_AutoFEC_All.ATSC_C"](#), on page 14 to [Chapter 2.26, "CEA_IOP_106b.ATSC_C"](#), on page 26 (ReferenceTest.ATSC_C, BCAST*.ATSC_C, CEA_CON_*.ATSC_C, CEA_IOP_*.ATSC_C) have been designed for conformance and interoperability testing at the CEA SIG PlugFest (March 1st to 4th, 2010). Note that these streams exhibit an issue with the fast information channel (FIC). The "current_next_indicator" flag of the FIC chunk header is set to "0", whereas the correct setting would be "1".

The configurations and content details of the M/H multiplex service are described in the following tables.

2.1 Transport stream files list, ordered by disk number

Transport stream file	Described on page	File size [MB]	Disk no.
3Ser-vESG_RS24_HHQQ_5S lots.ATSC_C	Chapter 2.2, "3Ser-vESG_RS24_HHQQ_5S lots.ATSC_C" , on page 10	700.1	1
1Serv_RS24_HHQQ_5S lots.ATSC_C	Chapter 2.3, "1Serv_RS24_HHQQ_5 Slots.ATSC_C" , on page 11	501.2	1

Transport stream files list, ordered by disk number

1Serv_RS48_QHHQ_5Slots.ATSC_C	Chapter 2.4, "1Serv_RS48_QHHQ_5Slots.ATSC_C", on page 11	501.2	1
1Serv_RS48_HHHH_5Slots.ATSC_C	Chapter 2.5, "1Serv_RS48_HHHH_5Slots.ATSC_C", on page 12	501.2	1
3Ens_RS48.ATSC_C	Chapter 2.6, "3Ens_RS48.ATSC_C", on page 12	501.2	1
3Ens_RS48_RS36_RS24.ATSC_C	Chapter 2.7, "3Ens_RS48_RS36_RS24.ATSC_C", on page 13	501.2	1
1Ens_Separated_RS24_RS48.ATSC_C	Chapter 2.8, "1Ens_Separated_RS24_RS48.ATSC_C", on page 14	501.2	1
3Ens_Auto-FEC_All.ATSC_C	Chapter 2.9, "3Ens_Auto-FEC_All.ATSC_C", on page 14	501.2	1
3Ens_Auto-FEC_RS.ATSC_C	Chapter 2.10, "3Ens_Auto-FEC_RS.ATSC_C", on page 15	501.2	1
3Ens_Auto-FEC_SCCC.ATSC_C	Chapter 2.11, "3Ens_Auto-FEC_SCCC.ATSC_C", on page 16	501.2	1
3Ens_Auto-FEC_SCCC_Block-Mode.ATSC_C	Chapter 2.12, "3Ens_Auto-FEC_SCCC_Block-Mode.ATSC_C", on page 17	501.2	1
Reference-Stream.ATSC_C	Chapter 2.13, "Referencestream.atsc_c", on page 18	501.2	2
BCAST_1.0_DIST_INT_103.ATSC_C	Chapter 2.14, "BCAST_1.0_DIST_INT_103.ATSC_C", on page 18	416.9	2
BCAST_1.0_DIST_INT_107.ATSC_C	Chapter 2.15, "BCAST_1.0_DIST_INT_107.ATSC_C", on page 19	501.2	2
BCAST_1.0_DIST_INT_111.ATSC_C	Chapter 2.16, "BCAST_1.0_DIST_INT_111.ATSC_C", on page 20	417.9	2

CEA_CON_103_Stream 1.ATSC_C	Chapter 2.17, "CEA_CON_103_Strea m1.ATSC_C", on page 20	501.2	2
CEA_CON_103_Stream 3.ATSC_C	Chapter 2.18, "CEA_CON_103_Strea m3.ATSC_C", on page 21	501.2	2
CEA_CON_104.ATSC_ C	Chapter 2.19, "CEA_CON_104.ATSC_ C", on page 22	501.2	2
CEA_IOP_100_101_109 .ATSC_C	Chapter 2.20, "CEA_IOP_100_101_10 9.ATSC_C", on page 22	501.2	2
CEA_IOP_103.ATSC_C	Chapter 2.21, "CEA_IOP_103.ATSC_C ", on page 23	501.2	2
CEA_IOP_104.ATSC_C	Chapter 2.22, "CEA_IOP_104.ATSC_C ", on page 24	501.2	2
CEA_IOP_105.ATSC_C	Chapter 2.23, "CEA_IOP_105.ATSC_C ", on page 24	501.2	2
CEA_IOP_106.ATSC_C	Chapter 2.24, "CEA_IOP_106.ATSC_C ", on page 25	501.2	2
CEA_IOP_106a.ATSC_ C	Chapter 2.25, "CEA_IOP_106a.ATSC_ C", on page 26	501.2	2
CEA_IOP_106b.ATSC_ C	Chapter 2.26, "CEA_IOP_106b.ATSC_ C", on page 26	501.2	2

2.2 3ServESG_RS24_HHQQ_5Slots.ATSC_C

MHE PID

0x1FF4

Parades

ID	Number of groups	RS prim	RS sec	SCCC mode	SCCC rate a	SCCC rate b	SCCC rate c	SCCC rate d
1	5	24	None	Separa- ted	1/2	1/2	1/4	1/4

Ensembles

Ensemble ID	Service ID	Service name	Destination IP	Service content
1	7681 (30-01)	RS_Serv_1	224.1.1.1	Grouper
1	7682 (30-02)	RS_Serv_2	224.1.1.2	Diver
1	7683 (30-03)	GMIT_Barker	224.1.1.20	Traffic
1	7690 (30-10)	ESG	225.0.23.1	ESG

Description

Single ensemble containing three basic TV services and a service guide.

2.3 1Serv_RS24_HHQQ_5Slots.ATSC_C**MHE PID**

0x1FFE

Parades

ID	Number of groups	RS prim	RS sec	SCCC mode	SCCC rate a	SCCC rate b	SCCC rate c	SCCC rate d
1	5	24	None	Separated	½	½	¼	¼

Ensembles

Ensemble ID	Service ID	Service name	Destination IP	Service content
1	513 (02-01)	RS24 HHQQ	224.1.1.100	R&S promotional

Description

Single ensemble containing one basic TV service. Carries the OMP transmission control packet for the SFN synchronization.

2.4 1Serv_RS48_QHHQ_5Slots.ATSC_C**MHe PID**

0x1FFE

Parades

ID	Number of groups	RS prim	RS sec	SCCC mode	SCCC rate a	SCCC rate b	SCCC rate c	SCCC rate d
1	5	48	None	Separated	1/4	1/2	1/2	1/4

Ensembles

Ensemble ID	Service ID	Service name	Destination IP	Service content
1	513 (02-01)	RS48 QHHQ	224.1.1.100	R&S promotional

Description

Single ensemble containing one basic TV service. Uses the OMP transmission control packet for the SFN synchronization.

2.5 1Serv_RS48_HHHH_5Slots.ATSC_C

MHE PID

0x1FF4

Parades

ID	Number of groups	RS prim	RS sec	SCCC mode	SCCC rate a	SCCC rate b	SCCC rate c	SCCC rate d
1	5	48	None	Combined	1/2	1/2	1/2	1/2

Ensembles

Ensemble ID	Service ID	Service name	Destination IP	Service content
1	513 (02-01)	RS24 HHQQ	224.1.1.100	R&S promotional

Description

Single ensemble containing one basic TV service. Uses the OMP transmission control packet for the SFN synchronization.

2.6 3Ens_RS48.ATSC_C

MHE PID

0x1FF9

Parades

ID	Number of groups	RS prim	RS sec	SCCC mode	SCCC rate a	SCCC rate b	SCCC rate c	SCCC rate d
1	4	48	None	Com-bined	¼	¼	¼	¼
2	2	48	None	Com-bined	½	½	½	½
3	3	48	None	Separa-ted	½	¼	¼	¼

Ensembles

Ensemble ID	Service ID	Service name	Destination IP	Service content
1	7937 (31-01)	RSTEST_1	224.1.1.1	Codec169
2	7938 (31-02)	RSTEST_2	224.1.1.2	Flowers
3	7939 (31-03)	RSTEST_3	224.1.1.3	Park

Description

Three ensembles, each with a different SCCC rate. Every ensemble carries one basic TV service. Uses the OMP transmission control packet for the SFN synchronization.

2.7 3Ens_RS48_RS36_RS24.ATSC_C**MHE PID**

0x1FF9

Parades

ID	Number of groups	RS prim	RS sec	SCCC mode	SCCC rate a	SCCC rate b	SCCC rate c	SCCC rate d
1	4	24	None	Com-bined	¼	¼	¼	¼
2	2	36	None	Com-bined	½	½	½	½
3	3	48	None	Separa-ted	½	¼	¼	¼

Ensembles

Ensemble ID	Service ID	Service name	Destination IP	Service content
1	7937 (31-01)	RSTEST_1	224.1.1.1	Codec169
2	7938 (31-02)	RSTEST_2	224.1.1.2	Flowers
3	7939 (31-03)	RSTEST_3	224.1.1.3	Park

Description

Three ensembles, each with different RS primary code rate. Every ensemble carries one basic TV service. Uses the OMP transmission control packet for the SFN synchronization.

2.8 1Ens_Separated_RS24_RS48.ATSC_C**MHE PID**

0x1FF9

Parades

ID	Number of groups	RS prim	RS sec	SCCC mode	SCCC rate a	SCCC rate b	SCCC rate c	SCCC rate d
1	4	24	48	Separated	1/4	1/4	1/2	1/2

Ensembles

Ensemble ID	Service ID	Service name	Destination IP	Service content
1 (primary RS-Frame)	7937 (31-01)	RSTEST_1	224.1.1.1	Codec169
1 (secondary RS-Frame)	7938 (31-02)	RSTEST_2	224.1.1.2	Flowers

Description

One ensemble with both primary and secondary RS frames. Each RS frame carries one basic TV service. Uses the OMP transmission control packet for the SFN synchronization.

2.9 3Ens_AutoFEC_All.ATSC_C**MHE PID**

0x1FF9

Parades

ID	Number of groups	RS prim	RS sec	SCCC mode	SCCC rate a	SCCC rate b	SCCC rate c	SCCC rate d
1	4	48	None	Com-bined	¼	¼	¼	¼
2	2	48	None	Com-bined	½	½	½	½
3	2	Variable	None	Variable	Variable	Variable	Variable	Variable

Ensembles

Ensemble ID	Service ID	Service name	Destination IP	Service content
1	7937 (31-01)	RSTEST_1	224.1.1.1	Codec169
2	7938 (31-02)	RSTEST_2	224.1.1.2	Flowers
3	7939 (31-03)	RSTEST_3	224.1.1.3	Park-ABR

Description

Three ensembles, two with constant FEC settings, one using the auto FEC mode. The FEC of the third ensemble is automatically adjusted to utilize the variable data rate of the mobile content (ABR encoded video). This stream file includes changes of:

- RS code
- SCCC block mode
- SCCC code rate

The OMP transmission control packet is activated.

2.10 3Ens_AutoFEC_RS.ATSC_C

MHE PID

0x1FF9

Parades

ID	Number of groups	RS prim	RS sec	SCCC mode	SCCC rate a	SCCC rate b	SCCC rate c	SCCC rate d
1	4	48	None	Com-bined	¼	¼	¼	¼

2	2	48	None	Com- bined	½	½	½	½
3	2	Variable	None	Separa- ted	½	¼	½	¼

Ensembles

Ensemble ID	Service ID	Service name	Destination IP	Service content
1	7937 (31-01)	RSTEST_1	224.1.1.1	Codec169
2	7938 (31-02)	RSTEST_2	224.1.1.2	Flowers
3	7939 (31-03)	RSTEST_3	224.1.1.3	Park-ABR

Description

Three ensembles, two with constant FEC settings, one using the auto FEC mode. The FEC of the third ensemble is automatically adjusted to utilize the variable data rate of the mobile content (ABR encoded video). This stream file includes changes of:

- RS code

The OMP transmission control packet is activated.

2.11 3Ens_AutoFEC_SCCC.ATSC_C

MHE PID

0x1FF9

Parades

ID	Number of groups	RS prim	RS sec	SCCC mode	SCCC rate a	SCCC rate b	SCCC rate c	SCCC rate d
1	4	48	None	Com- bined	¼	¼	¼	¼
2	2	48	None	Com- bined	½	½	½	½
3	2	48	None	Separa- ted	Variable	Variable	Variable	Variable

Ensembles

Ensemble ID	Service ID	Service name	Destination IP	Service content
1	7937 (31-01)	RSTEST_1	224.1.1.1	Codec169
2	7938 (31-02)	RSTEST_2	224.1.1.2	Flowers
3	7939 (31-03)	RSTEST_3	224.1.1.3	Park-ABR

Description

Three ensembles, two with constant FEC settings, one using the auto FEC mode. The FEC of the third ensemble is automatically adjusted to utilize the variable data rate of the mobile content (ABR encoded video). This stream file includes changes of:

- SCCC code rate

The OMP transmission control packet is activated.

2.12 3Ens_AutoFEC_SCCC_BlockMode.ATSC_C**MHE PID**

0x1FF9

Parades

ID	Number of groups	RS prim	RS sec	SCCC mode	SCCC rate a	SCCC rate b	SCCC rate c	SCCC rate d
1	4	48	None	Com-bined	¼	¼	¼	¼
2	2	48	None	Com-bined	½	½	½	½
3	2	48	None	Variable	Variable	Variable	Variable	Variable

Ensembles

Ensemble ID	Service ID	Service name	Destination IP	Service content
1	7937 (31-01)	RSTEST_1	224.1.1.1	Codec169
2	7938 (31-02)	RSTEST_2	224.1.1.2	Flowers
3	7939 (31-03)	RSTEST_3	224.1.1.3	Park-ABR

Description

Three ensembles, two with constant FEC settings, one using the auto FEC mode. The FEC of the third ensemble is automatically adjusted to utilize the variable data rate of the mobile content (ABR encoded video). This stream file includes changes of:

- SCCC block mode
- SCCC code rate

The OMP transmission control packet is activated.

2.13 Referencestream.atsc_c

MHE PID

0x1FF4

Parades

ID	Number of groups	RS prim	RS sec	SCCC mode	SCCC rate a	SCCC rate b	SCCC rate c	SCCC rate d
1	8	48	None	Separated	1/2	1/4	1/4	1/4

Ensembles

Ensemble ID	Service ID	Service name	Destination IP	Service content
1	5121 (20-01)	R&S_Service1	224.1.1.1	Codec169
1	5122 (20-02)	R&S_Service2	224.1.1.2	Jump
1	5123 (20-03)	R&S_Service3	227.1.1.20	Counter
1	5130 (20-10)	ESG	225.0.23.1	ESG

Description

Three basic TV components and a service guide in a single ensemble. This stream serves as a reference for the following test streams.

Known issue: The "current_next_indicator" flag of the FIC chunk header is set to "0".

2.14 BCAST_1.0_DIST_INT_103.ATSC_C

MHE PID

0x1FF4

Parades

ID	Number of groups	RS prim	RS sec	SCCC mode	SCCC rate a	SCCC rate b	SCCC rate c	SCCC rate d
1	8	48	None	Separated	1/2	1/4	1/4	1/4

Ensembles

Ensemble ID	Service ID	Service name	Destination IP	Service content
1	5121 (20-01)	R&S_Service1	224.1.1.1	Codec169
1	5122 (20-02)	R&S_Service2	224.1.1.2	Jump
1	5130 (20-10)	ESG	225.0.23.1	ESG
1	17921 (70-01)	R&S_Service3	227.1.1.20	Counter

Description

One ensemble containing three basic TV services (two local and one regional) and a service guide. A change in content name occurs in the service guide for service 20-01 at time 01:00 and 02:00 (mm:ss).

Known issue: The "current_next_indicator" flag of the FIC chunk header is set to "0".

2.15 BCAST_1.0_DIST_INT_107.ATSC_C**MHE PID**

0x1FF4

Parades

ID	Number of groups	RS prim	RS sec	SCCC mode	SCCC rate a	SCCC rate b	SCCC rate c	SCCC rate d
1	8	48	None	Separated	½	¼	¼	¼

Ensembles

Ensemble ID	Service ID	Service name	Destination IP	Service content
1	5121 (20-01)	R&S_Service1	224.1.1.1	Codec169
1	5122 (20-02)	R&S_Service2	224.1.1.2	Jump
1	5130 (20-10)	ESG	225.0.23.1	ESG
1	17921 (70-01)	R&S_Service3	227.1.1.20	Counter

Description

One ensemble containing three basic TV services (two local and one regional) and a service guide. The service guide is not GZIP-compressed.

Known issue: The "current_next_indicator" flag of the FIC chunk header is set to "0".

2.16 BCAST_1.0_DIST_INT_111.ATSC_C

MHE PID

0x1FF4

Parades

ID	Number of groups	RS prim	RS sec	SCCC mode	SCCC rate a	SCCC rate b	SCCC rate c	SCCC rate d
1	8	48	None	Separated	1/2	1/4	1/4	1/4

Ensembles

Ensemble ID	Service ID	Service name	Destination IP	Service content
1	5121 (20-01)	R&S_Service1	224.1.1.1	Codec169
1	5122 (20-02)	R&S_Service2	224.1.1.2	Jump
1	5130 (20-10)	ESG	225.0.23.1	ESG
1	17921 (70-01)	R&S_Service3	227.1.1.20	Counter

Description

One ensemble containing three basic TV services (two local and one regional) and a service guide. Service 20-01 contains two audio components which are described in the service guide as different language-specific content.

Known issue: The "current_next_indicator" flag of the FIC chunk header is set to "0".

2.17 CEA_CON_103_Stream1.ATSC_C

MHE PID

0x1FF4

Parades

ID	Number of groups	RS prim	RS sec	SCCC mode	SCCC rate a	SCCC rate b	SCCC rate c	SCCC rate d
1	8	48	None	Auto	Auto	Auto	Auto	Auto

Ensembles

Ensemble ID	Service ID	Service name	Destination IP	Service content
1	5121 (20-01)	R&S_Service1	224.1.1.1	Codec169
1	5122 (20-02)	R&S_Service2	224.1.1.2	Jump
1	5123 (20-03)	R&S_Service3	227.1.1.20	Counter
1	5130 (20-10)	ESG	225.0.23.1	ESG

Description

Three basic TV components and a service guide in a single ensemble. The FEC parameters SCCC Mode and SCCC Rate change frequently.

Known issue: The "current_next_indicator" flag of the FIC chunk header is set to "0".

2.18 CEA_CON_103_Stream3.ATSC_C**MHE PID**

0x1FF4

Parades

ID	Number of groups	RS prim	RS sec	SCCC mode	SCCC rate a	SCCC rate b	SCCC rate c	SCCC rate d
1	8	24 / 48	None	Separated	¼ / ½	¼	¼	¼

Ensembles

Ensemble ID	Service ID	Service name	Destination IP	Service content
1	5121 (20-01)	R&S_Service1	224.1.1.1	Codec169
1	5122 (20-02)	R&S_Service2	224.1.1.2	Jump
1	5123 (20-03)	R&S_Service3	227.1.1.20	Counter
1	5130 (20-10)	ESG	225.0.23.1	ESG

Description

Three basic TV components and a service guide in a single ensemble. The FEC parameters Primary RS Code Mode and SCCC Rate A change every minute.

Known issue: The "current_next_indicator" flag of the FIC chunk header is set to "0".

2.19 CEA_CON_104.ATSC_C

MHE PID

0x1FF4

Parades

ID	Number of groups	RS prim	RS sec	SCCC mode	SCCC rate a	SCCC rate b	SCCC rate c	SCCC rate d
1	8	48	None	Separated	½	¼	¼	¼

Ensembles

Ensemble ID	Service ID	Service name	Destination IP	Service content
1	5121 (20-01)	R&S_Service1	224.1.1.1	Codec169
1	5122 (20-02)	R&S_Service2	224.1.1.2	Jump
1	5123 (20-03)	R&S_Service3	227.1.1.20	Counter
1	5130 (20-10)	ESG	225.0.23.1	ESG

Description

Three basic TV components and a service guide in a single ensemble. The service 20-03 disappears and reappears every minute.

Known issue: The "current_next_indicator" flag of the FIC chunk header is set to "0".

2.20 CEA_IOP_100_101_109.ATSC_C

MHE PID

0x1FF4

Parades

ID	Number of groups	RS prim	RS sec	SCCC mode	SCCC rate a	SCCC rate b	SCCC rate c	SCCC rate d
1	7	48	None	Separated	½	¼	¼	¼
2	2	48	None	Separated	½	¼	¼	¼

Ensembles

Ensemble ID	Service ID	Service name	Destination IP	Service content
1	5121 (20-01)	R&S_Service1	224.1.1.1	Codec169
1	5122 (20-02)	R&S_Service2	224.1.1.2	Jump
1	5130 (20-10)	ESG	225.0.23.1	ESG
2	17921 (70-01)	R&S_Service3	227.1.1.20	Counter

Description

Two ensembles, the first one with two regional (ID 20-01 and 20-02) basic TV services and a service guide. The second ensemble contains a single local (ID 70-01) basic TV service.

Known issue: The "current_next_indicator" flag of the FIC chunk header is set to "0".

2.21 CEA_IOP_103.ATSC_C

MHE PID

0x1FF4

Parades

ID	Number of groups	RS prim	RS sec	SCCC mode	SCCC rate a	SCCC rate b	SCCC rate c	SCCC rate d
1	7	48	None	Separated	1/2	1/4	1/4	1/4
2	2	48	None	Separated	1/2	1/4	1/4	1/4

Ensembles

Ensemble ID	Service ID	Service name	Destination IP	Service content
1	5121 (20-01)	R&S_Service1	224.1.1.1	Codec169
1	5122 (20-02)	R&S_Service2	224.1.1.2	Jump
1	5130 (20-10)	ESG	225.0.23.1	ESG
2	17921 (70-01)	R&S_Service3	227.1.1.20	Counter

Description

Two ensembles, the first one with two regional (ID 20-01 and 20-02) basic TV services and a service guide. The second ensemble contains a single local (ID 70-01) basic TV service. The status of broadcasted services is listed in the following table.

Service ID	Service Status
5121 (20-01)	active, visible
5122 (20-02)	inactive, visible
5130 (20-10)	active, visible
5123 (70-01)	active, hidden

Known issue: The "current_next_indicator" flag of the FIC chunk header is set to "0".

2.22 CEA_IOP_104.ATSC_C

MHE PID

0x1FF4

Parades

ID	Number of groups	RS prim	RS sec	SCCC mode	SCCC rate a	SCCC rate b	SCCC rate c	SCCC rate d
1	8	48	None	Separated	½	¼	¼	¼

Ensembles

Ensemble ID	Service ID	Service name	Destination IP	Service content
1	5121 (20-01)	R&S_Service1	224.1.1.1	Codec169
1	5122 (20-02)	R&S_Service2	224.1.1.2	Jump
1	5123 (20-03)	R&S_Service3	227.1.1.20	Counter
1	5130 (20-10)	ESG	225.0.23.1	ESG

Description

A single ensemble containing two basic TV services (20-01 and 20-02), one basic radio service carrying only an audio component (20-03) and a service guide. Known issue: The "current_next_indicator" flag of the FIC chunk header is set to "0".

2.23 CEA_IOP_105.ATSC_C

MHE PID

0x1FF4

Parades

ID	Number of groups	RS prim	RS sec	SCCC mode	SCCC rate a	SCCC rate b	SCCC rate c	SCCC rate d
1	8	48	None	Separated	1/2	1/4	1/4	1/4

Ensembles

Ensemble ID	Service ID	Service name	Destination IP	Service content
1	5121 (20-01)	R&S_Service1	224.1.1.1	Codec169
1	5122 (20-02)	R&S_Service2	224.1.1.2	Jump
1	5123 (20-03)	R&S_Service3	227.1.1.20	Counter
1	5130 (20-10)	ESG	225.0.23.1	ESG

Description

Three basic TV components and a service guide in a single ensemble. The service label information delivered by the service guide is inconsistent with the SMT/SLT label carried by the service-signaling channel.

Known issue: The "current_next_indicator" flag of the FIC chunk header is set to "0".

2.24 CEA_IOP_106.ATSC_C

MHE PID

0x1FF4

Parades

ID	Number of groups	RS prim	RS sec	SCCC mode	SCCC rate a	SCCC rate b	SCCC rate c	SCCC rate d
1	8	48	None	Separated	1/2	1/4	1/4	1/4

Ensembles

Ensemble ID	Service ID	Service name	Destination IP	Service content
1	5121 (20-01)	R&S_Service1	224.1.1.1	Codec169
1	5122 (20-02)	R&S_Service2	224.1.1.2	Jump
1	5123 (20-03)	R&S_Service3	227.1.1.20	Counter

Description

Three basic TV components carried by a single ensemble. No service guide is in the broadcast.

Known issue: The "current_next_indicator" flag of the FIC chunk header is set to "0".

2.25 CEA_IOP_106a.ATSC_C

MHE PID

0x1FF4

Parades

ID	Number of groups	RS prim	RS sec	SCCC mode	SCCC rate a	SCCC rate b	SCCC rate c	SCCC rate d
1	6	48	None	Separated	½	¼	¼	¼
2	3	48	None	Separated	½	¼	¼	¼

Ensembles

Ensemble ID	Service ID	Service name	Destination IP	Service content
1	5121 (20-01)	R&S_Service1	224.1.1.1	Codec169
1	5122 (20-02)	R&S_Service2	224.1.1.2	Jump
1	5130 (20-10)	ESG_Ensemble1	225.0.23.1	ESG
2	5123 (20-03)	R&S_Service3	227.1.1.20	Counter
2	5131 (20-11)	ESG_Ensemble2	225.0.23.2	ESG

Description

There are two M/H ensembles in this stream. The first one contains two basic TV services and a service guide. The other one carries one basic TV service and a second service guide.

Known issue: The "current_next_indicator" flag of the FIC chunk header is set to "0".

2.26 CEA_IOP_106b.ATSC_C

MHE PID

0x1FF4

Parades

ID	Number of groups	RS prim	RS sec	SCCC mode	SCCC rate a	SCCC rate b	SCCC rate c	SCCC rate d
1	6	48	None	Separated	1/2	1/4	1/4	1/4

Ensembles

Ensemble ID	Service ID	Service name	Destination IP	Service content
1	5121 (20-01)	R&S_Service1	224.1.1.1	Codec169
1	5122 (20-02)	R&S_Service2	224.1.1.2	Jump
1	5123 (20-03)	R&S_Service3	227.1.1.20	Counter

Description

Three basic TV components carried by a single ensemble. This broadcast contains no service guide, but there is an entry in the Guide Access Table referencing a service guide in another broadcast (referenced TSID: 0x040F, referenced stream ID: 0x1064).

Known issue: The "current_next_indicator" flag of the FIC chunk header is set to "0".

Index

A

Application cards	7
Application notes	7

B

Brochures	7
-----------------	---

D

Data sheets	7
Documentation overview	5
DTV stream files	8

G

Getting started	6
-----------------------	---

H

Help	6
------------	---

I

Installation	5
Instrument help	6
Instrument security procedures	6

K

Key features	5
--------------------	---

O

Open source acknowledgment (OSA)	7
----------------------------------------	---

R

Release notes	7
---------------------	---

S

Safety instructions	6
Security procedures	6
Service manual	6

U

User manual	6
-------------------	---

W

Welcome	5
What's new	5
White papers	7