

R&S® TSMA6B

Autonomous Mobile Network Scanner User Manual



4901402602
Version 06

ROHDE & SCHWARZ
Make ideas real



This manual describes the following R&S®TSMA6B models and options:

- R&S®TSMA6B (4900.8005K20)
- R&S®TSMA6-K10 Block I/Q data (4901.0989.02)
- R&S®TSMA6-K19 P25 scanning (4901.5820.02)
- R&S®TSMA6-K21 WCDMA scanning (4901.0789.02)
- R&S®TSMA6-K22 CDMA2000 scanning (4901.0766.02)
- R&S®TSMA6-K23 GSM scanning (4901.0795.02)
- R&S®TSMA6-K24 1xEV-DO scanning (4901.0750.02)
- R&S®TSMA6-K25 CW scanning (4901.0814.02)
- R&S®TSMA6-K26 TETRA scanning (4901.0743.02)
- R&S®TSMA6-K27 RF power scan (4901.0720.02)
- R&S®TSMA6-K28 WiMAX™ scanning (4901.0737.02)
- R&S®TSMA6-K29 LTE scanning (4901.0772.02)
- R&S®TSMA6-K30 LTE-MIMO scanning (4901.0714.02)
- R&S®TSMA6-K32 LTE eMBMS scanning (4901.0643.02)
- R&S®TSMA6-K34 NB-IoT/Cat NB1 scanning (4901.0808.02)
- R&S®TSMA6-K 35 LTE-M scanning (4901.0208.02)
- R&S®TSMA6-K36 C-V2X LTE scanning (4901.0272.02)
- R&S®TSMA6-K40 Automatic channel detection (R&S®ViCom only, not for ROMES) (4901.0614.02)
- R&S®TSMA6-K50 5G NR scanning (4901.0966.02)
- R&S®TSMA6-K51 5G NR scanning add-ons (4901.0250.02)
- R&S®TSMA6-K52 5G RedCap scanning (4901.0295.02)
- R&S®TSMA6-K61 MNT software installation (QualiPoc support) (4901.0820.02)
- R&S®TSMA6-K62 R&S®NESTOR software installation (4901.0266.02)

© 2024 Rohde & Schwarz

Muehldorfstr. 15, 81671 Muenchen, Germany

Phone: +49 89 41 29 - 0

Email: info@rohde-schwarz.com

Internet: www.rohde-schwarz.com

Subject to change – data without tolerance limits is not binding.

R&S® is a registered trademark of Rohde & Schwarz GmbH & Co. KG.

The Bluetooth® word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. and any use of such marks by Rohde & Schwarz is under license.

CDMA2000® is a registered trademark of the Telecommunications Industry Association (TIA-USA).

The terms HDMI, HDMI High-Definition Multimedia Interface, HDMI trade dress and the HDMI Logos are trademarks or registered trademarks of HDMI Licensing Administrator, Inc.

"WiMAX", "Mobile WiMAX", "Fixed WiMAX", "WiMAX Forum", "WiMAX Certified", "WiMAX Forum Certified", "WiGRID", the WiMAX Forum logo, the WiMAX Forum Certified logo and the WiGRID logo are trademarks or registered trademarks of the WiMAX Forum. All other trademarks are the properties of their respective owners.

4901.4026.02 | Version 06 | R&S®TSMA6B

Throughout this document, R&S® is indicated as R&S.

Contents

1	Safety and regulatory information.....	11
1.1	Safety instructions.....	11
1.2	Labels on the product.....	14
1.3	WLAN/Bluetooth adapter.....	14
1.4	Warning messages in the documentation.....	16
1.5	Korea certification class A.....	16
2	Welcome.....	17
2.1	Documentation overview.....	17
2.1.1	Getting started manual.....	17
2.1.2	User manuals and help.....	17
2.1.3	Videos.....	17
2.1.4	Printed safety instructions.....	17
2.1.5	Specifications and product brochures.....	18
2.1.6	Release notes and open source acknowledgment (OSA).....	18
2.1.7	Application notes, application cards, white papers, etc.....	18
2.2	Key features.....	18
3	Getting started.....	20
3.1	Preparing for use.....	20
3.1.1	Unpacking and checking.....	20
3.1.2	Preparing for walk test.....	20
3.1.3	Setting up indoors.....	20
3.1.3.1	Placing the product on a bench top.....	20
3.1.3.2	Mounting the product in a rack.....	21
3.1.4	Considerations for test setup.....	21
3.1.5	Connecting antennas.....	22
3.1.6	Selecting operation mode (normal/scanner).....	22
3.1.7	Connecting devices for local operation (mouse, keyboard, monitor) (optional).....	23
3.1.8	Using external SSD R&S TSM6B-BEB (optional).....	24
3.1.9	Connecting LAN.....	25
3.1.10	Connecting USB to LAN adapter (optional).....	25
3.1.11	Connecting test mobile phones (optional).....	26

3.1.12	Connecting to power.....	26
3.1.12.1	Connecting to a vehicle DC power supply via a cigarette lighter.....	26
3.1.12.2	Connecting to the vehicle power supply via a terminal.....	26
3.1.12.3	Connecting to an AC power supply.....	27
3.1.12.4	Connecting to a battery pack.....	28
3.1.13	Switching on or off R&S TSMA6B.....	31
3.1.14	Calibrating GPS for dead reckoning.....	32
3.2	Instrument tour.....	33
3.2.1	Front panel tour.....	33
3.2.2	Rear panel tour.....	33
3.2.3	Built-in GPS receiver.....	38
3.2.4	Built-in WLAN / Bluetooth adapter.....	38
4	Option concept.....	39
4.1	Scanner options.....	39
4.1.1	Technology options.....	40
4.1.2	Band options.....	40
4.2	Software options.....	41
4.2.1	R&S NESTOR options.....	41
5	General workflows.....	42
5.1	R&S NESTOR-based workflow.....	43
5.2	R&S SmartONE-based workflow.....	43
6	Configuring the R&S TSMA6B.....	45
6.1	Accessing the R&S TSMA6B.....	45
6.1.1	Using the R&S TSMA6B web GUI.....	45
6.1.1.1	Using the web GUI locally.....	45
6.1.1.2	Using WLAN from a remote PC or smartphone.....	46
6.1.2	Using a remote desktop connection.....	46
6.2	Connecting to LAN/WAN from a remote PC.....	48
6.3	Changing IP addresses.....	49
6.4	Connecting with R&S TSMA6B WLAN access point.....	49
6.5	Changing WLAN settings.....	52
6.6	Selecting measurement mode.....	53

6.6.1	Measurement modes.....	54
6.6.1.1	PC mode.....	54
6.6.1.2	R&S Remote ViCom server mode.....	54
6.6.1.3	QualiPoc mode.....	55
6.6.1.4	R&S NESTOR and R&S NESTOR probe mode.....	58
6.6.1.5	R&S SmartONE mode.....	60
6.7	Importing workspace files (R&S NESTOR, R&S SmartONE Expert).....	62
6.8	Pairing Bluetooth devices.....	63
6.9	Changing language and keyboard language.....	64
6.10	Verify virtual memory settings.....	66
7	Measurement setup.....	71
7.1	Connecting R&S TSM6/6B with other devices.....	71
7.1.1	Cascading R&S TSM6/6B and R&S TSME6.....	71
7.1.2	Connecting R&S TSM6/6B-BP with R&S TSME6 and R&S TSMExxDC/TSMS53DC	72
7.1.3	Disconnecting the R&S TSM6B from R&S TSM6/6B-BP and other R&S TSMx devices.....	74
7.2	Use cases.....	75
7.2.1	R&S TSM6B with R&S TSME6 and R&S TSM6B-BP.....	75
7.2.2	R&S TSM6B with R&S TSMExxDC and R&S TSM6B-BP.....	77
7.2.3	R&S TSM6B with R&S TSMExxDC, R&S TSME6 and R&S TSM6B-BP.....	78
8	Installing firmware and software updates.....	80
8.1	Downloading setup file.....	80
8.2	Prerequisites.....	80
8.3	Updating firmware/software/tools - general instructions.....	82
8.3.1	Local execution of the setup file.....	82
8.3.2	Remote installation of the setup file.....	86
8.3.3	Installation using a USB flash drive.....	90
8.3.4	Calling R&S TSM6B web GUI.....	93
8.3.5	Subsequent steps after firmware update.....	94
8.4	R&S TSME tools update.....	94
8.4.1	Preparation.....	95
8.4.2	R&S TSME tools local installation.....	95

8.4.3	R&S TSME tools remote installation.....	96
8.4.4	R&S TSME tools installation using a USB flash drive.....	96
8.5	Microsoft EDGE browser update.....	97
8.5.1	Preparation.....	98
8.5.2	Microsoft EDGE browser local installation.....	98
8.5.3	Microsoft EDGE browser remote installation.....	98
8.5.4	Microsoft EDGE browser installation using a USB flash drive.....	99
8.6	Software update - details.....	100
8.6.1	R&S Remote ViCom software.....	100
8.6.1.1	Preparation.....	101
8.6.1.2	R&S Remote ViCom server local installation.....	101
8.6.1.3	R&S Remote ViCom server remote installation.....	102
8.6.1.4	R&S Remote ViCom server installation using a USB flash drive.....	103
8.6.2	R&S NESTOR software.....	104
8.6.2.1	Preparation.....	104
8.6.2.2	R&S NESTOR local installation.....	105
8.6.2.3	R&S NESTOR remote installation.....	105
8.6.2.4	R&S NESTOR installation using a USB flash drive.....	106
8.6.3	R&S SmartONE setup (R&S SmartBenchmark, ROMES, QualiPoc).....	107
8.6.3.1	Preparation.....	108
8.6.3.2	R&S SmartONE local installation.....	108
8.6.3.3	R&S SmartONE remote installation.....	108
8.6.3.4	R&S SmartONE installation using a USB flash drive.....	109
8.6.3.5	Initial software start / measurement mode selection.....	110
9	Installing software options (scanner, R&S NESTOR).....	114
9.1	Installing scanner options.....	114
9.2	Installing R&S NESTOR options.....	114
10	User backup and restore.....	115
10.1	Creating a user backup.....	115
10.2	Restoring a backup.....	115
10.3	Restoring with Debian installation.....	116
10.4	Restoring the factory backup.....	117

10.5	Capturing and applying R&S TSMA6B images.....	118
10.5.1	Preparing a backup for R&S TSMA6B image stick.....	118
10.5.2	Creating an R&S TSMA6B image stick.....	119
10.5.3	Booting from the R&S TSMA6B image stick.....	120
10.5.4	Capturing an image from R&S TSMA6B.....	120
10.5.5	Applying an image to R&S TSMA6B.....	122
11	Troubleshooting.....	125
11.1	LED indicated errors.....	125
11.2	Evaluate self-test file.....	126
11.3	Access the firmware log file.....	126
11.4	Write battery info into the firmware log file.....	126
11.5	Verify scanner link / recall device info using the R&S TSME device manager...	127
11.5.1	Obtaining device information - "Device Info".....	127
11.5.2	Device analysis output.....	129
11.5.3	Verify installed license keys.....	130
11.6	R&S TSMA6B automatically switches off after power on.....	131
11.7	Scanner is not found from software (ROMES, R&S NESTOR).....	132
11.8	Verify LAN settings (internal scanner connection).....	135
11.9	No remote access via LAN port.....	136
11.10	WLAN access point not detected by an external PC, mobile or tablet.....	140
11.11	Web GUI not accessible via WLAN connection.....	142
11.12	Web GUI not locally accessible.....	143
11.13	Slow/Instable WLAN connection.....	145
11.14	Bluetooth device not detected by R&S TSMA6B.....	145
11.15	No RF / GPS data.....	147
11.16	Contacting customer support.....	148
12	Transporting.....	150
13	Maintenance, storage and disposal.....	151
13.1	Cleaning.....	151
13.2	Storage.....	151
13.3	Disposal.....	151
	Annex.....	153

A	Web GUI reference	153
A.1	Home	153
A.1.1	Overview	153
A.1.2	IP settings	155
A.1.3	HW info	156
A.2	Configuration	158
A.2.1	System	158
A.2.1.1	Mode	159
A.2.1.2	Power	159
A.2.1.3	RF band	160
A.2.1.4	Password	160
A.2.1.5	Watchdog	161
A.2.2	Connectivity	161
A.2.2.1	Bluetooth	161
A.2.2.2	WLAN	162
A.2.2.3	WLAN AP	163
A.2.2.4	LAN	164
A.2.2.5	LAN SCAN	165
A.2.2.6	LAN EXT2 / EXT3 / EXT5 / EXT6	165
A.3	File transfer	166
A.4	Options	167
A.4.1	Available	167
A.4.2	Install	168
A.5	Update	168
A.6	Backup	169
A.7	Restart	170
A.8	Help	170
B	Introduction to remote ViCom sample app	171
B.1	Overview	171
B.2	Requirements	171
B.2.1	General requirements	171
B.2.2	Preparation	171
B.3	Usage	172

B.3.1	Connection establishment.....	172
B.3.1.1	Connection type selection.....	172
B.3.1.2	Server discovery.....	172
B.3.2	GSM RSSI scan.....	174
B.3.2.1	GSM preferences.....	174
B.3.2.2	GSM scan results.....	175
B.3.3	WCDMA Top-N pilot scan.....	176
B.3.3.1	WCDMA Top-N pilot preferences.....	176
B.3.3.2	WCDMA Top-N pilot scan results.....	176
B.3.4	LTE top signal scan.....	177
B.3.4.1	LTE top signal preferences.....	177
B.3.4.2	LTE top signal scan results.....	178
B.3.5	Throughput test case.....	179
B.3.5.1	Throughput preferences.....	179
B.3.5.2	Throughput results.....	179
B.3.6	RF power scan.....	180
B.3.6.1	RF power scan references.....	180
B.3.6.2	RF power scan results.....	181
C	Managing scanner device with R&S TSME Device Manager.....	183
C.1	Installing and managing software license keys - "Options".....	183
C.2	Configuring measurement bands - "Band Configuration".....	185
C.3	Obtaining firmware and correction data updates - "Updates".....	187
C.4	Aligning R&S TSMA6B manually - "Self Alignment".....	188
C.5	Configuring downconverter R&S TSME30DC/TSME44DC - "Downconverter Configuration".....	189
	Index.....	191

1 Safety and regulatory information

The product documentation helps you use the product safely and efficiently. Follow the instructions provided here and in the following sections.

Intended use

The R&S TSMA6B is intended as an integrated solution for efficient drive and walk testing. It offers maximum performance, autonomy and connectivity with an integrated high-performance PC and a mobile network scanner to comply with the latest requirements for state-of-the-art mobile network testing. Together with optional equipment (battery pack, transport bag) it is the ideal companion for remote or unattended operation during drive and walk test campaigns.

The R&S TSMA6B is intended to enhance the R&S TSMx scanner family via a vibration-proof mechanical connection to allow mobile operation. It contains two easily accessible, rechargeable and hot-swappable batteries.

Observe the operating conditions and performance limits stated in the specifications document.

Where do I find safety information?

Safety information is part of the product documentation. It warns you of potential dangers and gives instructions on how to prevent personal injury or damage caused by dangerous situations. Safety information is provided as follows:

- In [Chapter 1.1, "Safety instructions"](#), on page 11. The same information is provided in many languages in printed format. The printed "Safety Instructions" for "DC-Powered Products for Mobile Use" (document number 1171.2049.99) are delivered with the product.
- Throughout the documentation, safety instructions are provided when you need to take care during setup or operation.

1.1 Safety instructions

Products from the Rohde & Schwarz group of companies are manufactured according to the highest technical standards. To use the products safely, follow the instructions provided here and in the product documentation. Keep the product documentation nearby and offer it to other users.

Use the product only for its intended use and within its performance limits. Intended use and limits are described in the product documentation such as the specifications document, manuals and the printed "Safety Instructions" document. If you are unsure about the appropriate use, contact Rohde & Schwarz customer support.

Using the product requires specialists or specially trained personnel. These users also need sound knowledge of at least one of the languages in which the user interfaces and the product documentation are available.

Reconfigure or adjust the product only as described in the product documentation or the specifications document. Any other modifications can affect safety and are not permitted.

Never open the casing of the product. Only service personnel authorized by Rohde & Schwarz are allowed to repair the product. If any part of the product is damaged or broken, stop using the product. Contact Rohde & Schwarz customer support at <https://www.rohde-schwarz.com/support>.

Connecting the product

Before connecting the interfaces and measuring inputs of the product to other products or electrical circuits, make sure that the other products or electrical circuits provide special protection against electric shock. This protection principle is referred to as SELV (safety extra-low voltage) and is based on a low voltage level and increased insulation. Exceptions are indicated by a measurement category on the product and given in the specifications document.

Operating the product

The product is intended for mobile use. The maximum weight of the product is provided in the specifications document. If the product casing is not waterproof, use an adequate weather protection to carry the product outdoors with you.

When operating the product on a mobile platform, such as a vehicle, aircraft or drone, make sure that the product is properly secured. Refer to the instructions provided by the manufacturer of the mobile platform. If stacking is possible, secure the whole stack of products so that they cannot fall over and cause injury.

Observe the ambient conditions such as altitude, operating temperature and climatic loads; see the specifications document.

Due to their exposed location, mobile communications systems are at risk of damage from lightning. This also poses a risk to persons nearby. When the risk of lightning is present, remove antennas from exposed locations, e.g. vehicle roofs. Do not operate the product until the lightning risk has passed.

Connecting to power

The product runs on DC voltage. For the specifications of the supply voltage for the product, refer to the specifications document. Only connect the product to a power source that provides a protection against electric shock.

Take the following measures for your safety:

- If you connect the product to an external power supply, use one recommended in the product documentation.
- If you connect the product to a battery, observe the safety information delivered with the battery.
- Before switching on the product, ensure that the voltage and polarity indicated on the product matches the available power source.
- Only use intact cables and route them carefully so that they cannot be damaged. Also ensure that nobody can trip over loose cables.

Handling batteries safely

The product contains exchangeable or built-in lithium polymer or lithium ion cells or batteries. The use of the word battery in the following always means all types. Only the battery contents are potentially hazardous. As long as a battery is undamaged and the seals remain intact, there is no danger.

Impact, shock or heat can cause damage such as dents, punctures and other deformations. A damaged battery poses a risk of personal injury. Handle a damaged or leaking battery with extreme care. Immediately ventilate the area since the battery releases harmful gases. If you come into contact with the battery fluid, immediately remove all contaminated clothing. Irritation can occur if the battery fluid comes in contact with your skin or eyes. Immediately and thoroughly rinse your skin or eyes with water and seek medical aid.

For safe handling, follow these rules:


- Do not short-circuit the battery.
- Do not mechanically damage the battery. Do not open or disassemble the battery.
- Do not expose the battery to high temperatures such as open flames, hot surfaces and sunlight.
- Only use the battery with the designated Rohde & Schwarz product.
- Only use the appropriate Rohde & Schwarz charger to charge the batteries. If the batteries are improperly charged, there is a risk of explosion. For charging and discharging temperature ranges, see the product documentation.
- Replace exchangeable batteries only with the same battery type.
- Store the battery in the product or use the product packaging.
- Dispose of exchangeable batteries separately from normal household waste as specified by the local waste disposal agency.


If you disregard these rules, you risk serious personal injury or even death due to explosion, fire or hazardous chemical substances. The product documentation provides further details.

If exchangeable batteries or products with built-in batteries are defective, contact the Rohde & Schwarz customer service. Rohde & Schwarz classifies the severity of the defect. When returning batteries or Rohde & Schwarz products containing batteries, use a carrier qualified to transport dangerous goods and notify the carrier of this classification. Follow the carrier's transport stipulations in line with IATA-DGR, IMDG-Code, ADR or RID.

Meaning of safety labels

Safety labels on the product warn against potential hazards.

	Potential hazard Read the product documentation to avoid personal injury or product damage.
---	--


	<p>DC - direct current</p> <p>Connect to a DC power supply of the specified voltage range.</p>
---	--


1.2 Labels on the product

Labels on the casing inform about:

- Personal safety, see "[Meaning of safety labels](#)" on page 13
- Product and environment safety, see "[Labels regarding product and environment safety](#)" on page 14.
- Identification of the product, see bottom label of the R&S TSMA6B.

Labels regarding product and environment safety

	<p>Labeling in line with EN 50419 for disposal of electrical and electronic equipment after the product has come to the end of its life.</p>
---	--

	<p>Labeling in line with directive 2006/66/EC for disposal of batteries after they have come to the end of their life.</p>
---	--

1.3 WLAN/Bluetooth adapter

The R&S TSMA6B has built-in WLAN/Bluetooth module.

This wireless adapter complies with Part 15 of the FCC Rules and with Industry Canada license-exempt RSS standards. Operation of the device is subject to the following two conditions:

- This device may not cause harmful interference.
Cet appareil ne peut pas causer d'interférences.
- This device must accept any interference that may cause undesired operation.
Cet appareil doit accepter des interférences, y compris des interférences qui peuvent causer des opérations non désirées de l'appareil.

Radio frequency interference requirements

This wireless adapter is restricted to indoor use due to its operation in the 5.15 GHz to 5.25 GHz frequency range. The wireless adapter requires to be used indoors for the frequency range 5.15 GHz to 5.25 GHz to reduce the potential for harmful interference to co-channel Mobile Satellite systems. High power radars are allocated as primary users of the 5.25 GHz to 5.35 GHz and 5.65 GHz to 5.85 GHz bands. These radar stations can cause interference with and /or damage this device.

Canada-specific enhancement

When using IEEE 802.11a wireless LAN, this product is restricted to indoor use due to its operation in the 5.15 GHz to 5.25 GHz frequency range. Industry Canada requires this product to be used indoors for the frequency range of 5.15 GHz to 5.25 GHz to reduce the potential for harmful interference to co-channel mobile satellite systems. High power radar is allocated as the primary user of the 5.25 GHz to 5.35 GHz and 5.65 GHz to 5.85 GHz bands. These radar stations can cause interference with and/or damage to this device.

L'utilisation d'un réseau sans fil IEEE802.11a est restreinte à une utilisation en intérieur à cause du fonctionnement dans la bande de fréquence 5.15 GHz to 5.25 GHz. Industry Canada requiert que ce produit soit utilisé à l'intérieur des bâtiments pour la bande de fréquence 5.15 GHz - 5.25 GHz afin de réduire les possibilités d'interférences nuisibles aux canaux co-existants des systèmes de transmission satellites. Les radars de puissances ont fait l'objet d'une allocation primaire de fréquences dans les bandes 5.25 GHz-5.35 GHz et 5.65 GHz to 5.85 GHz. Ces stations radar peuvent créer des interférences avec ce produit et/ou lui être nuisible.

Usage in specific environments

- The use of wireless adapters in hazardous locations is limited by the constraints posed by the safety directors of such environments.
- The use of wireless adapters in hospitals is restricted to the limits set forth by each hospital.

Usage on aircraft

Regulations of the FCC, FAA and individual airlines prohibit airborne operation of some radio-frequency wireless devices (wireless adapters) because their signals could interfere with critical aircraft instruments.

Local restrictions on 802.11a, 802.11b, 802.11g, 802.11n, and 802.16e radio usage

Due to the fact that the frequencies used by 802.11a, 802.11b, 802.11g, 802.11n, and 802.16e wireless LAN devices may not yet be harmonized in all countries, 802.11a, 802.11b, 802.11g, 802.11n, and 802.16e products are designed for use only in specific countries, and are not allowed to be operated in countries other than those of designated use.

As a user of these products, you are responsible for ensuring that the products are used only in the countries for which they were intended and for verifying that they are configured with the correct selection of frequency and channel for the country of use. The device transmit power control (TPC) interface is part of the Intel® PROSet/Wireless Wi-Fi Connection Utility Software. Operational restrictions for Equivalent Isotropic Radiated Power (EIRP) are provided by the system manufacturer.

Any deviation from the permissible power and frequency settings for the country of use is an infringement of national law and may be punished as such.

1.4 Warning messages in the documentation

A warning message points out a risk or danger that you need to be aware of. The signal word indicates the severity of the safety hazard and how likely it will occur if you do not follow the safety precautions.

NOTICE

Potential risks of damage. Could result in damage to the supported product or to other property.

1.5 Korea certification class A



이 기기는 업무용(A급) 전자파 적합기기로서 판매자 또는 사용자는 이 점을 주의하시기 바라며, 가정외의 지역에서 사용하는 것을 목적으로 합니다.

2 Welcome

2.1 Documentation overview

This section provides an overview of the R&S TSMA6B user documentation. Unless specified otherwise, you find the documents at:

www.rohde-schwarz.com/manual/tsmx

2.1.1 Getting started manual

Introduces the R&S TSMA6B and describes how to set up and start working with the product. It includes basic operations, typical measurement examples, and general information, e.g. safety instructions, etc. A printed version is delivered with the product.

2.1.2 User manuals and help

The user manual contains the description of all instrument modes and functions. It also describes information on maintenance, instrument interfaces and error messages. It includes the contents of the getting started manual.

The user manual also describes the usage of options and extras (downconverter R&S TSMExxDC and battery pack R&S TSMA6B-BP).

The contents of the user manual are available as help in the R&S TSMA6B. The help offers quick, context-sensitive access to the complete information for the instrument and its firmware.

The user manual is also available for download or for immediate display on the Internet.

2.1.3 Videos

Find various videos on Rohde & Schwarz products and test and measurement topics on YouTube: <https://www.youtube.com/@RohdeundSchwarz>

2.1.4 Printed safety instructions

Provides safety information in many languages. The printed document is delivered with the product.

2.1.5 Specifications and product brochures

The specifications document, also known as the data sheet, contains the technical specifications of the R&S TSMA6B. It also lists the firmware applications and their order numbers, and optional accessories.

The brochure provides an overview of the instrument and deals with the specific characteristics.

See www.rohde-schwarz.com/brochure-datasheet/tsmx.

2.1.6 Release notes and open source acknowledgment (OSA)

The release notes list new features, improvements and known issues of the current software version, and describe the software installation.

The software uses several valuable open source software packages. An open source acknowledgment document provides verbatim license texts of the used open source software.

See www.rohde-schwarz.com/firmware/tsmx.

2.1.7 Application notes, application cards, white papers, etc.

These documents deal with special applications or background information on particular topics.

See www.rohde-schwarz.com/application/tsmx.

2.2 Key features

As in-building traffic in cellular networks grows, there is an increased need for indoor measurements. While traditional drive test systems consist of a laptop with test mobile phones and scanners, there are also walk test solutions that use tablets and smartphones.

The R&S TSMA6B enhances such solutions, providing the user with accurate insight into the RF environment.

The R&S TSMA6B combines the technology of the R&S TSME6 ultra-compact drive test scanner with a high-performance Intel processor. The scanner can run PC-based drive test software, and smartphones can be connected via USB.

With its ultra-broadband frontend, the integrated scanner measures all supported technologies 350 MHz to 6000 MHz simultaneously. The future-ready architecture and the in-field upgradeability for both hardware and software, allow up to 4x4 MIMO measurements and pave the way for the upcoming 5G technology.

Outstanding key features are:

- No limitation in 3GPP (LTE, WCDMA, GSM, NB-IoT...) frequency bands up to 6 GHz incl. a Multi-GNSS receiver for uninterrupted location tracking
- More than 10 technologies simultaneously in one system
- Future-ready for upcoming 5G related measurements
- Compact and lightweight design with customized mechanical concept for cascading multiple scanner hardware
- Maximum connectivity supporting additional scanner hardware, Windows-based PCs, Android-based UEs or tablets using wireless and wired connections
- Integrated 8th generation Intel quad-core processing unit

3 Getting started

3.1 Preparing for use

Here, you can find basic information about setting up the product for the first time.

3.1.1 Unpacking and checking

1. Unpack the product carefully.
2. Retain the original packing material. Use it when transporting or shipping the product later.
3. Using the delivery notes, check the equipment for completeness.
4. Check the equipment for damage.

If the delivery is incomplete or equipment is damaged, contact Rohde & Schwarz.

3.1.2 Preparing for walk test

If you want to perform a walk test, the R&S TSMA6B needs weather protection. The R&S TSMA6-ZCB2 transport bag is especially designed for this purpose. See also "[Operating the product](#)" on page 12.

3.1.3 Setting up indoors

3.1.3.1 Placing the product on a bench top

If you want to set up the R&S TSMA6B on a benchtop or prepare the R&S TSMA6B for mobile use, proceed as follows.

To place the product on a bench top

1. Place the R&S TSMA6B on a stable, flat and level surface.
2. If you want to stack R&S TSMx products, proceed as described in [Chapter 7.1, "Connecting R&S TSMA6/6B with other devices"](#), on page 71.
3. If you want to stack the R&S TSMA6B together with other products:
 - a) Follow the instructions given for the other products.
 - b) Place the R&S TSMA6B on top.

3.1.3.2 Mounting the product in a rack

To mount the product in a rack

1. Use an adapter kit to prepare the product for rack mounting.
 - a) Order the rack adapter kit designed for the product. For the order number, see specifications document.
 - b) Mount the adapter kit. Follow the assembly instructions provided with the adapter kit.
2. Lift the product to shelf height. If the rack is high, use a safe climbing aid when placing on upper shelves.
3. Grip the product by the handles. Slide the product onto the shelf until the rack brackets fit closely to the rack.
4. Tighten all screws on the rack brackets with a tightening torque of 1.2 Nm to secure the product in the rack.

3.1.4 Considerations for test setup

Electromagnetic interference (EMI) can affect the measurement results.

To suppress electromagnetic radiation during operation:

- Use high-quality shielded cables, for example, double-shielded RF and LAN cables.
- Always terminate open cable ends.
- Ensure that connected external devices comply with EMC regulations.

Signal input and output levels

Information on signal levels is provided in the specifications document. Keep the signal levels within the specified ranges to avoid damage to the product and connected devices.

Electromagnetic compatibility classes

The electromagnetic compatibility (EMC) class indicates where you can operate the product. The EMC class of the product is given in the specifications document.

- Class B equipment is suitable for use in:
 - Residential environments
 - Environments that are directly connected to a low-voltage supply network that supplies residential buildings
- Class A equipment is intended for use in industrial environments. It can cause radio disturbances in residential environments due to possible conducted and radiated disturbances. It is therefore not suitable for class B environments. If class A equipment causes radio disturbances, take appropriate measures to eliminate them.

3.1.5 Connecting antennas



The SMA connector is sensitive to mechanical stress. Use the following handling precautions.

- Always use a torque wrench and mount the cable end with 60 Ncm.
- Do not stack adapters directly at the SMA connector. If you need to use adapters (e.g: SMA to N), then always use a specific adapter cable (Rohde & Schwarz order no. 4900.1700.00).

To connect RF and GPS antenna


1. Connect the RF antenna to the RF IN connector (see [Figure 3-11 - 10](#)).
2. Connect the GPS antenna to the GPS ANT port (see [Figure 3-11 - 12](#)).

3.1.6 Selecting operation mode (normal/scanner)

To use the R&S TSM6B in normal mode

The scanner and the CPU are active. The scanner is connected to the CPU via an internal LAN interface.

1. Switch off the R&S TSM6B. For details, see [Chapter 3.1.13, "Switching on or off R&S TSM6B"](#), on page 31.
2. Use a pointed object to push the CPU switch (1) to position I (left).



1 = CPU switch, position I (left)

3. Switch on the R&S TSM6B (see [Chapter 3.1.13, "Switching on or off R&S TSM6B"](#), on page 31).

To use the R&S TSM6B in scanner mode

Only the scanner is active. The internal CPU is not powered. You can use the R&S TSM6B like an R&D TSME6 and access via the "SCAN" port, which serves as the LAN interface to connect with the PC.

The scanner is accessible via the LAN port marked with SCAN (2).

1. Switch off the R&S TSM6B. For details, see [Chapter 3.1.13, "Switching on or off R&S TSM6B"](#), on page 31.
2. Use a pointed object to push the CPU switch (1) to position 0 (right).




Figure 3-1: Switch to scanner mode

1 = CPU switch, position 0 (right)

2 = SCAN port (see ["SCAN port - GBit LAN interface - external R&S TSME4/6 \(RJ-45 connector\)"](#) on page 35)

3. Switch on the R&S TSM6B (see [Chapter 3.1.13, "Switching on or off R&S TSM6B"](#), on page 31).



In scanner mode, the "Mode" LED is blinking blue.

3.1.7 Connecting devices for local operation (mouse, keyboard, monitor) (optional)

To connect devices

- ▶ Connect a mouse and a keyboard to a free USB port (see [Figure 3-11 - 4, 16](#)) and a monitor to the appropriate monitor port (HDMI, USB-C), (see [Figure 3-11 - 14, 17](#)).

3.1.8 Using external SSD R&S TSM6B-BEB (optional)

Correct connection between R&S TSM6B and SSD

The option is pre-assembled and can only be ordered from the factory. With this option, the system disk (SSD) is mounted in an external SSD enclosure and connected via the USB3.1 port of the R&S TSM6B (see [Figure 3-2](#)). There is no internal disk assembled / fitted when ordered with this hardware option.



There is only one USB port which is allowed to connect the TSM6B-BEB option (see [Figure 3-2](#)).




Figure 3-2: R&S TSM6B - removable disk option

1 = USB connection between R&S TSM6B and SSD
2 = External enclosure with SSD

To remove the SSD enclosure

1. Push the tab (1) backwards.
2. Hold this position.
3. Remove the SSD enclosure from the mount in the direction of the arrow see [Figure 3-3](#).




Figure 3-3: Remove SSD enclosure

1 = Tab

2 = Direction to remove external disk

3.1.9 Connecting LAN

The R&S TSM6B provides two different LAN interfaces.

- SCAN port:
It is a GBit LAN interface with a fixed IP address as the default setting. It used to connect a second scanner.
- LAN port:
It is a GBit LAN interface with auto IP address as the default setting. It is used to connect the R&S TSM6B to a LAN and allows the remote control of the R&S TSM6B.

For configuration details, see [Chapter 6.2, "Connecting to LAN/WAN from a remote PC"](#), on page 48.

3.1.10 Connecting USB to LAN adapter (optional)

To extend the available number of Gbit LAN ports, various optional USB to LAN adapters are available:

- R&S TSPC-U2L (Single Gbit LAN port adapter)
- R&S TSPC-U2L2 (Dual Gbit LAN port adapter)
- R&S TSPC-U2L4 (USB-C to 4-port Ethernet)

For R&S TSPC-U2L4, no driver needs to be loaded. The firmware automatically configures the port (see [Chapter A.2.2.6, "LAN EXT2 / EXT3 / EXT5 / EXT6"](#), on page 165).

For R&S TSPC-U2L and R&S TSPCU2L2, check if driver updates are required.

For information how to connect an additional adapter, see <https://www.rohde-schwarz.com/driver/tsma6/>.

3.1.11 Connecting test mobile phones (optional)

When you connect a test mobile phone to a USB port for the first time, the installation of the appropriate drivers is mandatory.

Currently the following driver is available.

- Samsung USB driver

For information on how to connect Qualcomm-based mobiles and required driver updates, see <https://www.rohde-schwarz.com/driver/tsma6/>.

To connect test mobile phones

- ▶ Connect test mobile phones to USB 3.0 / USB-C ports (see [Figure 3-11](#) - 4, 17).

For information on how to connect other test mobile phones and install appropriate drivers, refer to related manuals (e.g. R&S SmartONE user manual).

3.1.12 Connecting to power

This section describes how to connect the R&S TSM6B to a power supply unit.

3.1.12.1 Connecting to a vehicle DC power supply via a cigarette lighter

The R&S TSM6B is delivered with a 12 V DC power supply cable with a cigarette lighter connector.

1. Check the rating of the vehicle DC power supply.
2. Connect the 7-pin connector to DC IN.
3. Connect the cigarette lighter adapter to the 12 V outlet of the vehicle.

3.1.12.2 Connecting to the vehicle power supply via a terminal

1. Ensure that the rating of the DC power supply network matches the requirements printed on the casing next to the DC input (see (6) in [Figure 3-11](#)).
2. Demount the cigarette lighter adapter from the cable.
3. Connect the open ends of the cable to the DC power supply.
Ensure that the polarity is correct (see [Figure 3-4](#)).




Figure 3-4: Supplied power cable with cigarette lighter adapter

+12 V DC = green/yellow cabling
 GND = brown/white cabling

3.1.12.3 Connecting to an AC power supply

If you operate the product with an external power supply, you can use it indoors only in pollution degree 2 environments where nonconductive contamination can occur. Suitable AC power supplies are listed in the specifications document. They differ in the output power:

- R&S TSM6B-Z1 has an output power of 105 W and is suitable for multiple R&S TSMx products.
1. Ensure that the required ratings listed in the specifications document are matched.
 2. Connect the round connector to DC IN.

Note:

If you connect the R&S TSM6B with an R&S TSM6B-BP, connect the DC power to the R&S TSM6B-BP (1).

Do not connect the DC power to the R&S TSM6B (2).



Figure 3-5: DC IN connectors

- 1 = DC IN connector R&S TSMA6B-BP
 2 = DC IN connector R&S TSMA6B

3. Insert the AC power plug into a power outlet with ground contact.

3.1.12.4 Connecting to a battery pack

You can use the R&S TSMA6B-BP battery pack as a power supply.




If you use an R&S TSMA6B together with an R&S TSMAX-BP, connect the DC power to the DC IN connector of the R&S TSMAX-BP (see [Figure 3-5](#)).



If the R&S TSMA6B is not used for more than one day, remove the batteries from R&S TSMA6B-BP to prevent discharge. For details, see the manual of the R&S TSMA6B-BP battery pack.

To connect a battery pack

1. Remove the cover cap from the docking connector of the R&S TSMA6/6B.



2. Screw the collar screws (standard accessory of R&S TSMA6B-BP) on the top of the R&S TSMA6B with a Torx 8 screw driver.
 - Torque: $0.66 \text{ Nm} \pm 0.05 \text{ Nm}$




Figure 3-6: Collar screws

1 = Collar screws

3. Align the collar screws with the snap-in holes on the bottom of an R&S TSMA6/6B.




Figure 3-7: Aligning R&S TSM6B-BP and R&S TSM6/6B

1 = R&S TSM6B-BP

2 = Collar screws

3 = R&S TSM6/6B

4 = Snap in holes on the bottom pane of R&S TSM6/6B

4. Press the device down.
5. Move the R&S TSM6/6B to the rear side (2) until you hear a click when locking in the collar screws.



Figure 3-8: Connected R&S TSM6/6B and R&S TSM6B-BP

- 1 = Attach R&S TSM6B to R&S TSM6B-BP
- 2 = Move R&S TSM6/6B to the rear side
- 3 = Power connection established (snapped in docking connector)

3.1.13 Switching on or off R&S TSM6B

The behavior depends on the configured "Startup Settings" (see ["Startup Settings"](#) on page 159).

- "Auto Power ON"
The R&S TSM6B starts automatically.
- "Remember Last State"
If you have powered down the R&S TSM6B in the previous measurement session, you have to switch on the device next time manually.

To switch on the device

The device is off but connected to power.

- ▶ Press the power on/off button.
The Pwr LED starts green blinking. After booting, the color changes to green resp. blue continuous depending on the state of the WLAN access point (see [Table 3-1](#)).

To shut down the device

- ▶ Press the power on/off button.
The Pwr LED starts blinking green. The operating system shuts down and the Pwr LED is switched off.



Figure 3-9: Power button

For the power state LEDs, see [Table 3-1](#).

For a cold start, hold the power on/off button at least 5 s.

3.1.14 Calibrating GPS for dead reckoning

The following steps are necessary to enable untethered dead reckoning with the integrated receiver (see ["GPS Ant. connector \(SMA\) - GPS antenna input"](#) on page 36) of the R&S TSMA6B.

1. Mount the R&S TSMA6B device fixed to the frame of a car.
2. Power on the R&S TSMA6B device.
3. Activate "Dead Reckoning" in the used software.
For details, refer to R&S ROMES, R&S NESTOR or R&S ViCom documentation.
4. Wait until the used software reports a "3D fix" (time can vary depending on the configured GNSS).
5. To calibrate the instrument, perform the following driving procedures in a safe environment.
 - a) 720 degrees right turn
 - b) 720 degrees left turn
 - c) Drive in a straight line with a velocity exceeding 40 km/h.

After finishing the calibration, the used software should report a fix state "GPS+DR" or "3D+DR", in case satellite reception is lost the fix state will change to "DR only".



If using "DR only", the accuracy of the reported position will decrease over time. If it falls below a certain threshold, the receiver reports the state "No Fix".



The GPS calibration is saved in the module. Whenever the device is switched off, the calibration procedure must be repeated for the next usage of dead reckoning.

3.2 Instrument tour

The meanings of the labels on the product are described in [Chapter 1.2, "Labels on the product"](#), on page 14.

3.2.1 Front panel tour

The front panel of the R&S T SMA6B does not provide any connectors or control elements for operation. The black caps on the left and right contain the WLAN antennas. For details, see [Chapter 3.2.4, "Built-in WLAN / Bluetooth adapter"](#), on page 38.




Figure 3-10: R&S T SMA6B - Front Panel

3.2.2 Rear panel tour

The following figure provides an overview of the control elements and the connectors on the rear panel of the instrument.




Figure 3-11: R&S T SMA6B - Rear Panel

- 1 = "Power on/off" on page 34
- 2 = "Status LEDs - Mode, Meas" on page 34
- 3 = "Restore button" on page 35
- 4 = "USB 3.0 (2x 1.5 A, 2x 0.9 A, Type A)" on page 35
- 5 = "Docking connector" on page 35
- 6 = "DC IN connector" on page 35
- 7 = "Switch Normal mode - Scan mode" on page 35
- 8 = "SCAN port - GBit LAN interface - external R&S TSME4/6 (RJ-45 connector)" on page 35
- 9 = "WLAN/Bluetooth on/off" on page 36
- 10 = "RF IN connector (SMA)" on page 36

- 11 = "AUX connector (SMA) - synchronization R&S TSME4/6 / R&S TSMExxDC" on page 36
- 12 = "GPS Ant. connector (SMA) - GPS antenna input" on page 36
- 13 = "Status LEDs - Scanner Pwr / State" on page 36
- 14 = "HDMI connector (2x)" on page 37
- 15 = "LAN port - remote control (RJ-45 connector)" on page 37
- 16 = "USB 2.0/USB 3.0 (2x, Type A)" on page 37
- 17 = "USB-C (multiport for Thunderbolt, display and standard USB-C 3.1)" on page 37

Power on/off

See (1) in [Figure 3-11](#).

Turns the device on and off.

For details, see [Chapter 3.1.13, "Switching on or off R&S TSM6B"](#), on page 31.

Status LEDs - Mode, Meas

See (2) in [Figure 3-11](#).

The status LEDs Mode and Meas indicate different states of the R&S TSM6B.

Table 3-1: Power states

Device	
Mode LED	State
---	Power off
Green (BLINKING, 1/s)	Power on / power down (in progress)
Green (CONT.)	Power on (finished) / WLAN access point off
Blue (CONT.)	Power on (finished) / WLAN access point on
Blue (BLINKING, 1/s)	Restore/Backup/FW, SW installation (in progress)
Green (BLINKING, 1/5s)	Delayed start activated
Blue (BLINKING, 1/2s)	Scanner mode
Blue (BLINKING rapidly)	Self-test failed/scanner interface not accessible

Table 3-2: Measurement states (R&S SmartONE only)

Device	
Meas LED	State
Yellow (CONT.)	SW loading
Green (CONT.)	SW ready
Green (BLINKING, 1/2s)	SW measuring
Green (BLINKING rapidly)	SW recording
Yellow (BLINKING, 2/s)	SW warning
Red (BLINKING rapidly)	SW error

Restore button

See (3) in [Figure 3-11](#).

System recovery to factory or user default.

Use a slim, dull object for pressing the button.

Min button hold time for detection: 20 sec

USB 3.0 (2x 1.5 A, 2x 0.9 A, Type A)

See (4) in [Figure 3-11](#).

Connecting external storage devices, data sticks and test mobile phones.

- 2x USB 3.0 with a power limit of 1.5 A/port



- 2x USB 3.0 with a power limit of 0.9 A/ port



Overall USB current (USB-C, USB 3.0 and USB 2.0 combined): max. 3 A

Docking connector

See (5) in [Figure 3-11](#).

Connector for the battery pack unit R&S TSM6/B-BP.

DC IN connector

See (6) in [Figure 3-11](#).

Connecting external DC power supply.

Ensure that the voltage and current indicated on the R&S TSM6B match the available power source.

Input voltage range: 11 V to 18 V

Input current: max. 8.5 A

For connecting to power, see [Chapter 3.1.12, "Connecting to power"](#), on page 26.

Switch Normal mode - Scan mode

See (7) in [Figure 3-11](#).

Switches between scanner mode (scanner only) and normal mode (CPU and scanner).

For details, see [Chapter 3.1.6, "Selecting operation mode \(normal/scanner\)"](#), on page 22.

SCAN port - GBit LAN interface - external R&S TSME4/6 (RJ-45 connector)

See (8) in [Figure 3-11](#).

The SCAN port provides a high-speed 1 Gbit Ethernet interface with an RJ-45 connector. It is used to connect the R&S TSMA6B to a separate R&S TSME6 as a second scanner used for MIMO scenarios and for increasing bandwidth and measurement rate.

WLAN/Bluetooth on/off

See (9) in [Figure 3-11](#).

Switches WLAN and Bluetooth on and off.

RF IN connector (SMA)

See (10) in [Figure 3-11](#).

RF input of the device.

The maximum input power is +20 dBm/10 V DC.

Do not overload the maximum-allowed input of +20 dBm.

Non-compliance destroys the input mixer.

AUX connector (SMA) - synchronization R&S TSME4/6 / R&S TSMExxDC

See (11) in [Figure 3-11](#).

The AUX connector has two functions.

- Input/output: Synchronization with up to 4 connected R&S TSME6 resp. R&S TSMExxDC (requires sync cable R&S TSME6-ZC2, order no. 4900.1800.02 or R&S TSME6-ZC4, order no. 4900.1817.02)
- Input: Synchronization of R&S TSMA6B with an external 10 MHz reference (requires a dedicated sync cable)

GPS Ant. connector (SMA) - GPS antenna input

See (12) in [Figure 3-11](#).

Active GPS antenna port (output voltage 3V, max 25 mA).

Status LEDs - Scanner Pwr / State

See (13) in [Figure 3-11](#).

The status LEDs Scanner State and Scanner Pwr indicate different states of the R&S TSMA6B.

Scanner		
Pwr LED	State LED	State
Green (BLINKING rapidly => ON)	Red (Off-On < 5s => Off)	Scanner configuration ongoing
Green	Green	Connected
Green	Green (BLINKING rapidly)	Measuring

Scanner		
Pwr LED	State LED	State
Green	Red (BLINKING, 2/s)	Temperature warning
Green	Red	Temperature error
n.a.	Red (BLINKING, 2/s)	Scanner error Temperature warning
n.a.	Red	Scanner error Temperature error

HDMI connector (2x)

See (14) in [Figure 3-11](#).

Connecting an external monitor (max. resolution: 2560 x 1600 pixel).

LAN port - remote control (RJ-45 connector)



See (15) in [Figure 3-11](#).

High-speed 1 Gbit Ethernet interface with an RJ-45 connector. Use it to connect the R&S TSM6B to a LAN/WAN.

The LAN interface can be used for the following scenarios.

- Remote Control via web-GUI
- Remote Control via Remote Desktop Connection
- LAN interface in R&S NESTOR Probe Mode

Table 3-3: LAN port LEDs

Status	LED
Link status	 Yellow
Activity status	 Green

USB 2.0/USB 3.0 (2x, Type A)

See (16) in [Figure 3-11](#).

Connecting external devices, e.g. keyboard, mouse or software dongle.

- 1x USB 2.0 with a power limit of 0.5 A/port
- 1x USB 3.0 with a power limit of 0.9 A/ port



Overall USB current (USB-C, USB 3.0 and USB 2.0): max. 3 A

USB-C (multiport for Thunderbolt, display and standard USB-C 3.1)

See (17) in [Figure 3-11](#).

Connecting external storage devices, tablets and test mobile phones.

Total power (USB-C): max. 3 A

Overall USB current (USB-C, USB 3.0 and USB 2.0): max. 3 A

3.2.3 Built-in GPS receiver

The integrated multi-GNSS (GPS / BeiDou / Galileo / GLONASS) receiver enables the use of three satellite systems in parallel. It offers an accuracy improvement of 30 % to 50 % by using a second constellation of satellites.

The following combinations are allowed:

- GPS only
- GPS / GLONASS / Galileo
- GPS / BeiDou

The R&S TSMA6B can perform dead reckoning in tunnels to provide position information even if no satellites are available. The dead reckoning is performed by the device with its built-in electronic gyroscopes.

For enabling untethered dead reckoning, see [Chapter 3.1.14, "Calibrating GPS for dead reckoning"](#), on page 32.



Depending on the intended use, the respective valid regulations regarding lightning protection of the antennas and regarding vehicle installation must be observed during installation.

3.2.4 Built-in WLAN / Bluetooth adapter

The R&S TSMA6B has a built-in WLAN/Bluetooth module (Intel® AX200).

The R&S TSMA6B WLAN / Bluetooth adapter allows the following modes.

- Client connection to a distant WLAN network
- Serving as a WLAN access point

Per default, the R&S TSMA6B WLAN access point is switched on. The login credentials are found on the bottom label of the device. The WLAN / Bluetooth can be switched off (flight mode) via a rear panel switch.

Configure the WLAN and Bluetooth settings via web-GUI.

- [Chapter A.2.2.1, "Bluetooth"](#), on page 161
- [Chapter A.2.2.2, "WLAN"](#), on page 162
- [Chapter A.2.2.3, "WLAN AP"](#), on page 163

For regulatory information, see [Chapter 1.3, "WLAN/Bluetooth adapter"](#), on page 14.

4 Option concept

The option concept is designed as follows.

- Optional accessories
 - R&S TSMA6-ZCB2 (transport bag)
 - R&S TSMA6-Z1 (AC adapter)
 - R&S TSMA6-Z2 (19" rack adapter)
 - R&S TSMA6-Z5 (Carrying box)
 - R&S TSMA6B-Z62 (R&S NESTOR dongle lock)
- Hardware options
 - R&S TSMA6B-BEP (extern. SSD)
 - R&S TSMA6B-BST Memory - 16 GB DDR4 / 256 GB SSD
 - R&S TSMA6B-B1T Memory Extension - 32 GB DDR4 / 1 TB SSD
 - R&S TSMA6B-BN1 Processor Intel Core i7-8665U, quad core, 4.4 GHz turbo, 8 Mbyte cache
 - R&S TSMA6B-BN2 Processor Intel Core i5-8365U, quad core, 4.1 GHz turbo, 6 Mbyte cache
- Scanner options
- Software options

4.1 Scanner options

The scanner options are available with registered licenses, unregistered licenses and time-based licenses.

- Registered licenses (variant .02)
Registered licenses are permanent licenses which are fixed to a serial device number.
- Unregistered licenses (variant .03)
Unregistered licenses are permanent licenses without serial number fixation.
- Timed licenses
Timed licenses are registered or unregistered licenses limited to a define time period.
 - Registered, 3 months (variant.23)
 - Registered, 6 months (variant.36)
 - Unregistered, 3 months (variant .16)

4.1.1 Technology options

Technology options allow the R&S TSMA6B to scan the input based on a specific technology, for example, LTE. All technology options can be installed on the same instrument; the R&S TSMA6B can measure various technologies simultaneously.

The following technology options are available:

Table 4-1: Available R&S TSMA6B technology options

Option	Order Number	Description
R&S TSMA6-K10	4901.0989.02	Block I/Q data
R&S TSMA6-K19	4901.5820.02	P25 scanning
R&S TSMA6-K21	4901.0789.02	WCDMA scanning
R&S TSMA6-K22	4901.0766.02	CDMA2000 scanning
R&S TSMA6-K23	4901.0795.02	GSM scanning
R&S TSMA6-K24	4901.0750.02	1xEV-DO scanning
R&S TSMA6-K25	4901.0814.02	CW scanning
R&S TSMA6-K26	4901.0743.02	TETRA scanning
R&S TSMA6-K27	4901.0720.02	RF power scan
R&S TSMA6-K28	4901.0737.02	WiMAX scanning
R&S TSMA6-K29	4901.0772.02	LTE scanning
R&S TSMA6-K30	4901.0714.02	LTE-MIMO scanning
R&S TSMA6-K32	4901.0643.02	LTE eMBMS scanning
R&S TSMA6-K34	4901.0808.02	NB-IoT/Cat NB1 scanning
R&S TSMA6-K35	4901.0208.02	LTE-M scanning
R&S TSMA6-K36	4901.0272.02	C-V2X LTE scanning
R&S TSMA6-K40	4901.0614.02	Automatic channel detection (R&S ViCom only, not for ROMES)
R&S TSMA6-K50	4901.0966.02	5G NR scanning
R&S TSMA6-K51	4901.0250.02	5G NR scanning add-ons
R&S TSMA6-K52	4901.0295.02	5G RedCap scanning
R&S TSMA6-K61	4901.0820.02	MNT software installation (QualiPoc support)
R&S TSMA6-K62	4901.0266.02	R&S NESTOR software installation

4.1.2 Band options

The R&S TSMA6B hardware measures in all wireless communications bands from 350 MHz to 6 GHz simultaneously. Using band licenses, more cost-efficient configurations are available for applications where only a limited number of bands need to be mea-

sured simultaneously. These configurations limit the number of bands that can be measured in parallel. You can reconfigure the bands for each measurement as desired.

Upgrade options are available to increase the bandwidth of the R&S TSMA6B from a limited number of bands to full bandwidth.

The following band options are available:

Table 4-2: Available R&S TSMA6B band options

Option	Order Number	Description
R&S TSMA6-KAB	4901.0708.02	Measuring all bands simultaneously
R&S TSMA6-K1B	4901.0695.02	1 band measured simultaneously
R&S TSMA6-K2B	4901.0689.02	2 bands measured simultaneously
R&S TSMA6-K3B	4901.0672.02	3 bands measured simultaneously
R&S TSMA6-K4B	4901.0666.02	4 bands measured simultaneously
R&S TSMA6-K5B	4901.0650.02	5 bands measured simultaneously
R&S TSMA6-KUB	4901.0950.02	Upgrade: 1 additional band measured simultaneously

4.2 Software options

4.2.1 R&S NESTOR options

The R&S TSMA6B has no device-internal license dongle. To use R&S NESTOR software, an external R&S NESTOR nano-USB card dongle must be connected. The usage of the license hardlock dongle is described in the supplement "R&S TSMA6B-Z62 NESTOR Dongle Lock".

5 General workflows

Prerequisites

- Antennas connected (RF, GPS)
- Software license available. With WiBu, the following solutions are possible.
 - Wibu dongle
 - Wibu software license - requires no dongle
- Power supply connected (DC/AC/Battery Pack) and TSMA6B switched on
- LAN/WLAN connection to host PC established
 - LAN

Connect the R&S TSMA6B LAN socket with an RJ-45 cable to the LAN. By default the R&S TSMA6B is configured to use DHCP and no static IP address is set. The R&S TSMA6B shows the IP address in the local web-GUI. Start a browser on the remote device and enter the following URL:
http://TSMA6B-<xxxxxx>.local (xxxxxx is the serial number of this specific R&S TSMA6B) or use the IP displayed from the local web-GUI.
 - WLAN (see [Chapter 6.4, "Connecting with R&S TSMA6B WLAN access point"](#), on page 49)


Default WLAN-Access point
SSID: *TSMA6B-xxxxxx* (xxxxxx is the serial number of this specific R&S TSMA6B)
Default key: *instrument*
- License Keys installed
 - Scanner
 - Software
 - QualiPoc mobile
- Select Measurement Mode via CPU slider (see [Chapter 3.1.6, "Selecting operation mode \(normal/scanner\)"](#), on page 22).
 - 1: Standard Mode
 - 0: Scanner Mode

Reboot necessary when changed.
- Optional: mouse, keyboard and monitor for local control
- Optional: Additional cabling for R&S TSME6 and R&S TSMExxDC connection
 - LAN cable: R&S TSME6 "LAN" connector <-> TSMA6B "SCAN" connector
 - AUX cable: R&S TSME6 "AUX" connector <-> TSMA6B "AUX" connector
 - Power cable: R&S TSME6 "DC IN" connector <-> Power Supply

See [Chapter 7.2, "Use cases"](#), on page 75.
- Optional: USB2LAN converter (TSPC-U2Lx)
Connect TSPC-USL2 / TSPC-U2L to blue USB3.0 port


5.1 R&S NESTOR-based workflow

* For details about the prerequisites, see "Prerequisites" on page 42.



5.2 R&S SmartONE-based workflow

* For details about the prerequisites, see "Prerequisites" on page 42.



6 Configuring the R&S TSMA6B

6.1 Accessing the R&S TSMA6B

There are different ways to control measurements on the R&S TSMA6B.

- Local operation
To use the R&S TSMA6B as an ordinary PC, an external monitor, mouse and keyboard have to be connected to the R&S TSMA6B.
- Remote access
The remote access to the R&S TSMA6B can be realized via the following options.
 - Using the web GUI of the R&S TSMA6B (see [Chapter 6.1.1, "Using the R&S TSMA6B web GUI"](#), on page 45).
 - Establishing a remote desktop connection (via LAN/WLAN) (see [Chapter 6.1.2, "Using a remote desktop connection"](#), on page 46).

6.1.1 Using the R&S TSMA6B web GUI



The Microsoft EDGE browser replaces the formerly used Internet Explorer for the TSMAx web-GUI and is used as default browser.

The R&S TSMA6B web GUI gives the user the full access to control and measure with the R&S TSMA6B. The following tasks can be done:

- Recalling of system information / hardware software versions / IP settings
- Configuring measurement mode / power-up/down behavior / band selection
- Configuring LAN / WLAN & Bluetooth settings / IP configuration
- File transfer (upload / download)
- Showing and installing SW licenses
- Updating firmware and software
- Creating a user backup
- Restarting device / scanner part
- Accessing online help

To access the R&S TSMA6B web GUI, use one of the following options.

6.1.1.1 Using the web GUI locally

1. Connect a mouse, a keyboard and a monitor to the R&S TSMA6B.
2. Press the Microsoft EDGE browser icon in the Windows taskbar.

The R&S TSMA6B web GUI opens automatically. If not, type the following URL:
http://localhost

6.1.1.2 Using WLAN from a remote PC or smartphone

1. On the remote device, search for the R&S TSMA6B WLAN network. The WLAN access point on the R&S TSMA6B starts automatically by factory default.
NOTE: WLAN AP startup configuration (see [Chapter A.2.2.3, "WLAN AP"](#), on page 163).
2. Connect to the access point using the login credentials found at the bottom label of the R&S TSMA6B.
Default SSID: *TSMA6B-xxxxxx* (xxxxxx is the serial number of this specific R&S TSMA6B)
Default key: *instrument*
Note:
The SSID and the key are configurable via the web GUI (see [Chapter A.2.2.3, "WLAN AP"](#), on page 163).
3. Open the browser on the remote device.
4. Enter the IP address of the TSMA6B web GUI.
http://192.168.137.1/
The TSMA6B web-GUI is displayed on the browser.

6.1.2 Using a remote desktop connection


To establish a remote desktop connection with a Windows PC (Win 10 is recommended), the following steps have to be performed.

1. Establish a WLAN/LAN connection between the R&S TSMA6B and the remote PC (see [Chapter 6.1.1, "Using the R&S TSMA6B web GUI"](#), on page 45).
2. On the keyboard, press [Win-Logo] + [R].
The command window opens.
3. Enter *mstsc.exe*.
The "Remote Desktop Connection" window opens.
4. In the "Remote Desktop Connection" window, click "Show Options".
5. In the "General" tab, enter the following parameters:
 - Computer: The input depends on the selected connection type and is as follows.
 - WLAN: *192.168.137.1*
 - LAN: IP address of the R&S TSMA6B


NOTE:

If you connect the R&S TSM6B LAN interface with a PC via LAN cable, the IP addresses are negotiated automatically by default. You can read the IP address of the R&S TSM6B from the local web GUI (see [Chapter 6.1.1, "Using the R&S TSM6B web GUI"](#), on page 45).

- User name: *instrument*



6. Click "Connect".
7. Enter the password (default: *894129*) and click "OK".



The remote desktop connection is available and the R&S TSM6B can be controlled from the remote PC.

6.2 Connecting to LAN/WAN from a remote PC

Network environment

Before connecting the product to a local area network (LAN), consider the following:

- Install the latest firmware and patches for the Windows operating system to reduce security risks.
- For internet or remote access, use secured connections if applicable.
- Ensure that the network settings comply with the security policies of your company. Contact your local system administrator or IT department before connecting your product to your company LAN.
- When connected to the LAN, the product may potentially be accessed from the internet, which may be a security risk. For example, attackers might misuse or damage the product.

1. Connect the R&S TSM6B LAN connector with an RJ-45 cable to the local area network.



2. Configure the LAN port IP address settings in the R&S TSM6B web-GUI (see [Chapter A.2.2.4, "LAN"](#), on page 164) in accordance with your administrator guidelines:
 - a) Local configuration, see [Chapter 6.1.1.1, "Using the web GUI locally"](#), on page 45.

- b) Remote configuration, see [Chapter 6.1.1.2, "Using WLAN from a remote PC or smartphone"](#), on page 46
3. Alternatively, use the assigned IP address for remote access (see [Chapter A.1.2, "IP settings"](#), on page 155).

The default IP setting is "DHCP" (configure IP address automatically). The assigned IP address for remote access when using DHCP is displayed in the web-GUI (see [Chapter A.1.2, "IP settings"](#), on page 155).

6.3 Changing IP addresses

To change the IP addresses, refer to the following.

- [Chapter A.2.2.4, "LAN"](#), on page 164
- [Chapter A.2.2.5, "LAN SCAN"](#), on page 165

6.4 Connecting with R&S TSM6B WLAN access point

The R&S TSM6B has a built-in WLAN access point.




The usage of WLAN is restricted to indoor use.


1. On the host PC, click the Network symbol in the taskbar.




2. Select the correct WLAN (in this example: "TSM6-101084").




3. Select "Connect automatically".
4. Click "Connect".



5. Select "Connect using a security key instead".



6. Enter the network security key.
7. Click "Next".
Default security key: *instrument*



The connection to the WLAN access point is established when it is reported as "Connected".

6.5 Changing WLAN settings

To change the WLAN settings (WLAN mode and preferred band), proceed as follows.

To change WLAN mode and preferred band.

1. Start the web-GUI of the R&S TSM6B.
2. Navigate to "Configuration" > "Connectivity" > "WLAN".
3. Select the following settings according to your needs or back to the default settings.
 - "Wireless Mode"
 - "Preferred band"
 - "Wireless Mode Ext"

See also "[WLAN Settings](#)" on page 163.


6.6 Selecting measurement mode



The CPU switch must be in normal mode (see [Chapter 3.1.6, "Selecting operation mode \(normal/scanner\)"](#), on page 22).

Select the measurement mode with the following steps.

1. Start the R&S TSM6B web GUI (see [Chapter 6.1.1, "Using the R&S TSM6B web GUI"](#), on page 45).
2. You can configure the measurement modes via the radio button from the web GUI under "Configuration" > "System" > "Mode".



Measurement modes are only selectable if the appropriate SW applications are installed (see [Chapter 8.6, "Software update - details"](#), on page 100). The "PC Mode" is always selectable.

6.6.1 Measurement modes

6.6.1.1 PC mode

In this mode, none of the following measurement modes are active and the device is in an idle state.

It is the preferred mode for updating R&S TSM6B firmware and software.

6.6.1.2 R&S Remote ViCom server mode



The "rViCom Server" mode is only selectable if the R&S Remote ViCom server software is installed (see [Chapter 8.6.1, "R&S Remote ViCom software"](#), on page 100).

This mode starts the R&S Remote ViCom server on the R&S TSMA6B. Measurement configuration and data collection are done from a remotely connected handheld device (smartphone or tablet). Users can develop their own Remote ViCom client applications. For details, see R&S ViCom manual.

The connection between the R&S Remote ViCom server on the R&S TSMA6B and the client application (R&S Remote ViCom client) on the handheld device can be realized via Bluetooth or WLAN.

The selection of which wireless interface to use depends on the expected data throughput and measurement task.



The WLAN connection allows a data throughput, which is about 10 times higher compared to Bluetooth.

The Bluetooth connection is less influenced by radio interference.

- Using the Bluetooth interface:
See [Chapter 6.8, "Pairing Bluetooth devices"](#), on page 63.
- Using the WLAN connection:
Connect the tablet/smartphone with the R&S TSMA6B WLAN AP. See [Chapter 6.4, "Connecting with R&S TSMA6B WLAN access point"](#), on page 49.

6.6.1.3 QualiPoc mode



The QualiPoc mode selector is only displayed if the R&S SmartONE software is installed (see [Chapter 8.6.3, "R&S SmartONE setup \(R&S SmartBenchmark, ROMES, QualiPoc\)"](#), on page 107).

Prerequisites

- Install the appropriate scanner license on the QualiPoc handheld device. If you do not have the correct license, contact the R&S service.
- On the R&S TSMA6B, Bluetooth must be activated and visible (see [Figure 6-6](#)).

To use the R&S TSMA6B with QualiPoc, the following steps must be performed.

1. Turn on the R&S TSMA6B scanner.
2. In the web-GUI, set the "Mode of Operation" to "QualiPoc" (1) and press "Submit" (2).

Mode of Operation ?

NESTOR

Monitoring

Cellular Network Analysis

NESTOR Probe

SmartONE Standard

SmartONE Expert Autostart

Recording

IP Controlled

1 QualiPoc

Smart Monitor


rVicom Server

2 PC Mode

Current Measurement ?

State

Info

3. On the handheld device, start the QualiPoc application.
4. Touch the main menu .
5. Touch "Device manager".
6. Touch the plus sign (+) at the top of the screen.
7. Touch "NCM".




Figure 6-1: Add NCM

QualiPoc displays "NCM" under "Devices".

Note: The NCM provides the Bluetooth connection to the scanner.

8. Touch "Scan" at the top of the screen.




Figure 6-2: Scan for NCM

9. Wait until the scanning process stops.
10. Touch "[Disconnected]".
11. Touch the TSM6B scanner in the list, for example "TSM6B-900012".
12. Touch "OK" to accept the pairing request.




Figure 6-3: Pair NCM




Figure 6-4: Bluetooth pairing request

13. The scanner appears in the "Devices" list upon successful detection.




Figure 6-5: Scanner ready

For more details about the QualiPoc configuration and usage, refer to the user documentation of QualiPoc.

6.6.1.4 R&S NESTOR and R&S NESTOR probe mode



The R&S NESTOR mode is only displayed if the R&S NESTOR software is installed (see [Chapter 8.6.2, "R&S NESTOR software"](#), on page 104).

General

- **R&S NESTOR mode**
The R&S NESTOR UI engine and the R&S NESTOR measurement engine are hosted on the R&S TSM6B.
- **R&S NESTOR probe mode**
The R&S TSM6B hosts only the R&S NESTOR measurement engine. The R&S NESTOR UI engine is hosted on a remote PC connected via LAN/WLAN with the R&S TSM6B. This primary PC is required to control the measurement.

Prerequisites

- For R&S NESTOR mode only:
 - R&S NESTOR workspace file imported (see ["Import R&S NESTOR workspace file"](#) on page 62)

- R&S NESTOR license dongle connected to a USB port
- For R&S NESTOR probe mode only:
 - WAN / LAN connection with the R&S NESTOR host (see [Chapter 3.1.9, "Connecting LAN"](#), on page 25)
 - R&S NESTOR Probe mode requires a primary PC to control the measurement
 - Optional: R&S NESTOR license dongle connected to a USB port

R&S NESTOR mode

To use the R&S TSM6B R&S NESTOR mode, the following steps must be performed.

1. In the web-GUI, set the "Mode of Operation" to "R&S NESTOR".

2. Configure "Autostart".
 - Unselected: R&S NESTOR starts without a workspace parameter and the workspace selector box is inactive.
 - Selected: Select a workspace file for mode activation. The workspace selector box is active.
3. Select a scenario ("Monitoring" or "Cellular Network Analysis").
4. Press "Submit".

The R&S TSM6B is switched into "R&S NESTOR" mode. In the status bar, the entry is "Changing mode of operation in progress...".

The selected mode is active when the status bar displays "No error". The scanner "State" LED starts blinking rapidly.

R&S NESTOR probe mode

1. On the "Mode" tab, select "R&S NESTOR Probe" mode.
2. Press "Submit".

The R&S TSMA6B is switched into "R&S NESTOR Probe" mode. In the status bar, the entry is "Changing mode of operation in progress...".

The selected mode is active when the status bar indicates "No error". The scanner "State" LED starts blinking rapidly.

The R&S NESTOR measurement is started and controlled from the host PC.

For more details about the R&S NESTOR configuration and usage, refer to the user documentation for R&S NESTOR.

6.6.1.5 R&S SmartONE mode



The R&S SmartONE modes are only displayed if R&S SmartONE software is installed (see [Chapter 8.6.3, "R&S SmartONE setup \(R&S SmartBenchmarker, ROMES, QualiPoc\)"](#), on page 107).

To use the R&S TSMA6B with R&S SmartONE, the following steps must be performed.

1. In the web GUI, set the "Mode of Operation" to one of the following R&S SmartONE modes and press "Submit".
 - "SmartONE Standard" (1)
Activating this mode, you can use a web-based UI with the R&S SmartBenchmarker software, designed for efficient data collection and remote control support in combination with SmartMonitor.
 - "SmartONE Expert" (1)
Activating this mode, you can use an expert UI with the ROMES software for complex measurement tasks and detailed data investigation during the measurement.
For the initial settings after installation, see [Chapter 8.6.3.5, "Initial software start / measurement mode selection"](#), on page 110.
 - "Smart Monitor" (2)
Activating this mode, you can use a central, web-based module for controlling and monitoring a fleet of QualiPoc Android probes.

The screenshot shows a configuration page for the R&S TSM6B. It features a 'Mode of Operation' section with several radio button options: NESTOR, NESTOR Probe, SmartONE Standard, SmartONE Expert (selected), QualiPoc, Smart Monitor, rViCom Server, and PC Mode. There are also checkboxes for 'Autostart', 'IP Controlled', and 'Recording'. Two 'Select the Workspace File' dropdown menus are present. A 'Submit' button is at the bottom right. Three numbered callouts (1, 2, 3) point to the SmartONE Expert mode, the Smart Monitor option, and the Submit button respectively. Below the mode selection is a 'Current Measurement' section with 'State' and 'Info' links.

2. Configure the additional settings for "R&S SmartONE Expert" mode only.

- Autostart
R&S SmartONE Expert starts automatically in this mode with a workspace file. Select the workspace file via the drop-down menu.
- Workspace File
In "Autostart" mode, select via the drop-down menu a workspace file (see ["Import of R&S SmartONE Expert workspace file"](#) on page 62).
- Recording
Activating this checkbox, the R&S SmartONE measurement data are written to the R&S TSM6B hard disk.
- IP Controlled
Activating this checkbox, you can control the R&S SmartONE measurement via IP from an external host PC. In this mode, you need no "Autostart", "Workspace File" and "Recording" setting.

3. Click "Submit" (3) to activate the selected measurement configuration.

For more details about the R&S SmartONE configuration and usage, refer to the user documentation for R&S SmartONE.

6.7 Importing workspace files (R&S NESTOR, R&S SmartONE Expert)

Import R&S NESTOR workspace file

1. Start the R&S TSMA6B web GUI from the host PC (see [Chapter 6.1.1, "Using the R&S TSMA6B web GUI"](#), on page 45).
2. Navigate to "Configuration" > "System" > "Mode" and set measurement mode to "NESTOR Probe".
3. Press "Submit".
Wait until the device is in "NESTOR Probe" mode (the status bar displays "No error").
4. Navigate to "File Transfer".
5. Press "Browse..." in the "Upload" section.
6. Search on the host PC for the R&S NESTOR workspace file, which you want to import and confirm the dialog with "Open".
7. Press "Upload".
The file is copied to the R&S NESTOR workspace directory (default: `D:\Users\Instrument\Documents\NESTOR\FavoriteWorkspaces`). You can configure this path in the "File Transfer" menu.
8. Navigate back to "Configuration" > "System" > "Mode".
9. The imported workspace file is selectable from the list box in the "Mode" tab.

Import of R&S SmartONE Expert workspace file

Importing of the R&S SmartONE Expert workspace file is an additional requirement for operating in the "SmartONE Expert" mode.

1. Start the R&S TSMA6B web GUI (see [Chapter 6.1.1, "Using the R&S TSMA6B web GUI"](#), on page 45).
2. Navigate to "File Transfer" menu.
3. Navigate to the section "Upload File to TSMA".
4. Press the "Browse" button.
5. Select the desired ROMES workspace file on the remote PC.
6. Click "Upload File".
7. The file is copied by default in the directory `C:\ProgramData\Rohde&Schwarz\My ROMES\Workspace`.
Note: The target directory for file upload depends on the selected mode. The mentioned directory is only valid in ROMES mode.

6.8 Pairing Bluetooth devices

To pair the R&S TSMA6B with a remote device, the following steps must be performed.



For Bluetooth preparation, the device must be in the "PC Mode". Check it via the web GUI ("Home" > "Overview").

To change the operation mode, navigate to "Configuration" > "System" > "Mode" and select an operation mode.

1. In the web-GUI, verify the Bluetooth settings on R&S TSMA6B.




Figure 6-6: Bluetooth settings

2. Navigate to "Configuration" > "Connectivity" > "Bluetooth".
3. Verify the settings:
 - STATUS = On
 - Visibility = Visible

If necessary, change the settings via the buttons on the right.

4. On the remote device, activate Bluetooth.
5. Enable visibility.

Note: For devices with Android versions ≥ 5.0 , there can be problems with visibility of the device.

Refer to [Chapter 11.14, "Bluetooth device not detected by R&S TSMA6B"](#), on page 145.

6. In the R&S TSMA6B web GUI, click "Refresh Device List".
The status text shows the following: "Refreshing device list in progress".
Wait until you see the message "No Error".

7. Click the arrow next to the "Refresh Device List" button.
8. Open the Bluetooth adapter list box.
9. Select the device, which you want to pair.
10. Click "Connect".
11. On the remote device, confirm the Bluetooth pairing code.

6.9 Changing language and keyboard language


By default, the R&S TSM6B is delivered with the English version of Windows®10 and it supports the English keyboard. With Windows® image version 1.6/1.4 (see "Image" on page 154), following languages are pre-installed:

- Arabic
- French
- German
- Italian
- Russian

To change the language and the keyboard layout, proceed as follows.

To change the language and the keyboard layout

1. Open the "Settings".



2. Select "Time & Language".
3. In the menu on the right, select "Language".
4. In the drop-down list "Windows display language", select the language according to your needs.
5. Reboot the device.

The selected language and keyboard gets active.




With the Windows®image 1.4/1.3 or smaller, you cannot activate any other language. To solve this behavior for the German language, install the language package `TSM6B_LanguagePack_de-de.exe` separately.

To get the language installation package, contact R&S support.


After the installation of the language package, continue with ["To change the language and the keyboard layout"](#) on page 64 to select the German language.

To change the keyboard language in case of image version 1.4. / 1.3 or lower and no separate language package installation, proceed as follows.

1. Open the "Settings".



2. Select "Time & Language".
3. In the menu on the right, select "Language".
4. Select "Add Language".
5. In "Choose a language to install", type the language that you want to install.
6. Click "Next".
NOTE: You can ignore messages regarding missing internet connection.
7. Click "Install".
After successfully adding the language, it is listed as a selectable language.
8. Move your selected language with the arrow upwards on top of the list.




9. Change the keyboard language by clicking the language icon on the Windows® taskbar near the clock.


6.10 Verify virtual memory settings

To enable virtual memory on the R&S TSM6B, perform the following steps:


1. Open "Settings".




2. In the "Settings", select "System".




3. In "Systems", select "About".




4. Select "System info".
5. Select "Advanced System Settings".




6. Select the tab "Advanced".



7. Select "Settings..." in the section "Performance".
8. Select the tab "Advanced".



9. Select "Change..." in the section "Virtual memory".
10. Enable "Automatically manage paging file size for all devices".



11. Click "OK" to close the dialog.
12. Reboot the device.

7 Measurement setup

7.1 Connecting R&S TSMA6/6B with other devices



4 collar screws are part of the standard accessory of the R&S TSMA6B. Additional collar screws are part of the R&S TSME6/TSMExxDC accessory or can be ordered as spare parts (order no. 4900.0804.00).

7.1.1 Cascading R&S TSMA6/6B and R&S TSME6

To connect R&S TSMA6/6B and R&S TSME6

1. Screw the connecting elements (order no. 4900.0804.00) on the top of the R&S TSMA6/6B.
 - Torque: 0.66 Nm \pm 0.05 Nm
 - Secure with liquid plastic




Figure 7-1: Connecting elements

1 = Connecting elements (order no.4900.0804.00)

2. **Notice:** An insufficient airflow can cause the instrument to overheat, which disturbs the operation and even cause damage. Make sure that all fan openings are unobstructed and that the airflow perforations are unimpeded, particularly when you install the instrument in a rack or packed in a backpack. Keep clear the following surrounding spaces to the instrument:
 - Front pane: minimum 2 cm
 - Left/right panes: minimum 1 cm
 Align the connecting elements with the holes on the bottom of an R&S TSME6.




Figure 7-2: Aligning R&S TSMA6/6B and R&S TSME6

- 1 = R&S TSMA6/6B
- 2 = Connecting screws
- 3 = R&S TSME6
- 4 = Holes on the bottom pane of R&S TSME6

3. Press the R&S TSME6 down.

7.1.2 Connecting R&S TSMA6/6B-BP with R&S TSME6 and R&S TSMExxDC/TSMS53DC




The following steps are valid for R&S TSME6 and downconverter R&S TSMExxDC/R&S TSMS53DC.

For the cabling of the devices, the accessory cables R&S TSMA6-BPPT or R&S TSMA6-BP2T are necessary.



Additional cabling can be necessary for proper operation. For complete cabling instructions, refer to the R&S TSME6 user manual and the R&S TSMExxDC/R&S TSMS53DC manual.

1. Screw the collar screws (1) on the top of the R&S TSMA6/6B-BP with a Torx 8 screw driver.
 - Torque: 0.66 Nm \pm 0.05 Nm



- 1 = Collar screws for connecting R&S TSME6
 2 = Aux 1 / Aux 2 (auxiliary power out for connecting R&S TSME6/TSMExxDC/TSMS53DC via power cable R&S TSME-ZYC)

2. Align the collar screws with the snap-in holes on the bottom of an R&S TSME6/TSMExxDC/TSMS53DC.




Figure 7-3: Example: Aligning R&S T SMA6/6B-BP and R&S TSME6

- 1 = R&S T SMA6/6B-BP
 2 = Collar screws
 3 = R&S TSME6/TSMExxDC/TSMS53DC
 4 = Snap-in holes on the bottom pane of R&S TSME6/TSMExxDC/TSMS53DC

3. Press the device down.
 4. Move the R&S TSME6/TSMExxDC/TSMS53DC to the back side, until you hear a click when the collar screws lock into place.




Figure 7-4: Connected R&S TSME6/TSMExxDC/TSMS53DC and R&S TSM6/6B-BP

1 = R&S TSM6/6B-BP

2 = R&S TSME6/TSMExxDC/TSMS53DC

5. Connect the power cable R&S TSM6-BPPT resp. R&S TSM6-BP2T from AUX1 resp. AUX2 to DC IN of R&S TSME6/xxDC/TSMS53DC.

7.1.3 Disconnecting the R&S TSM6B from R&S TSM6/6B-BP and other R&S TSMx devices

To disconnect the R&S TSM6B from R&S TSM6/6B-BP and R&S TSMx devices (R&S TSM6/6B, R&S TSME6, R&S TSMExxDC/TSMS53DC), proceed as follows.

1. Power off all connected R&S TSMx devices.
2. Disconnect the DC power cables of the devices.
3. Disconnect all other cables of the devices.
4. Remove the R&S TSMx devices.
5. **Only for R&S TSM6/6B:** Lift the release button (1) on both sides of the R&S TSM6/6B and slide it in direction (2) until the device is released.



Figure 7-5: Disconnect R&S TSMAX6/6B

7.2 Use cases

In the following, you find several use cases with different combinations of TSMAX devices.

7.2.1 R&S TSMAX6B with R&S TSME6 and R&S TSMAX6B-BP



The usage of the R&S TSME6 at the SCAN port of the R&S TSMAX6B requires the R&S TSME6 base firmware version 05.08.xx.00.

Update the R&S TSME6 to the corresponding firmware version in "Section 0" on a separate PC before connecting it to the R&S TSMAX6B. Use for the update the TSME Device Manager Tool version 1.7.4.0 or higher.




Figure 7-6: R&S TSM6B + R&S TSME6

- 1 = LAN connection: R&S TSM6B (SCAN port) - R&S TSME6
- 2 = Synchronization: R&S TSM6B - R&S TSME6
- 3 = DC power: R&S TSM6B-BP - R&S TSME6
- 4 = RF: R&S TSM6B RF In < 6 GHz
- 5 = RF: R&S TSME6

For the LAN connection between R&S TSM6B and R&S TSME6, you need a LAN cable of type CAT6.

Change the SCAN port of the R&S TSM6B via the web-GUI to DHCP (see "[TCP/IP Mode \(LAN SCAN\)](#)" on page 165). This allows to connect an R&S TSME6 without IP address change.

For the synchronization between R&S TSM6B and R&S TSME6, you need the synchronization cable R&S TSME6-ZC2.

For the DC power between R&S TSM6B-BP and R&S TSME6, you need the power cable R&S TSM6-BPPT.

For the RF input connector, you need an antenna according to your needs.



Additional devices like R&S TSME6 and R&S TSMExxDC can also be mounted to the side.




Figure 7-7: Example: R&S TSM6B with R&S TSME6 mounted to the side

7.2.2 R&S TSM6B with R&S TSMExxDC and R&S TSM6B-BP




Figure 7-8: R&S TSM6B + R&S TSMExxDC

- 1 = Synchronization: R&S TSM6B - R&S TSMExxDC
- 2 = DC power: R&S TSM6B-BP - R&S TSMExxDC
- 3 = RF: R&S TSMExxDC RF In 24 GHz to 27.5 GHz (R&S TSME30DC as example)
- 4 = RF: R&S TSMExxDC IF1 - R&S TSM6B RF In

For the synchronization between R&S TSM6B and R&S TSMExxDC, you need the synchronization cable R&S TSME6-ZC2.

For the DC power between R&S TSM6B-BP and R&S TSME6, you need the power cable R&S TSM6-BPPT.

Using an R&S TSME30DC (see [Figure 7-8](#)), you can connect the RF antenna to two RF connectors with different frequency ranges (24 GHz to 27.5 GHz and 27 GHz to 30 GHz). The R&S TSME44DC offers only one RF connector with a frequency range from 24 GHz to 44 GHz.

7.2.3 R&S TSM6B with R&S TSMExxDC, R&S TSME6 and R&S TSM6B-BP




Figure 7-9: R&S TSM6B + R&S TSMExxDC + R&S TSME6

- 1 = LAN connection: R&S TSM6B - R&S TSME6
- 2 = Synchronization: R&S TSM6B - R&S TSME6 / R&S TSMExxDC
- 3 Aux 1 = DC power: R&S TSM6B-BP - R&S TSMExxDC
- 3 Aux 2 = DC power: R&S TSM6B-BP - R&S TSME6
- 4 = RF: R&S TSM6B RF In < 6 GHz
- 5 = RF: R&S TSMExxDC RF In 27 GHz to 30 GHz
- 6 = RF: R&S TSMExxDC IF1 - R&S TSME6 RF In

For the LAN connection between R&S TSM6B and R&S TSME6, you need a LAN cable of type CAT6.

For the synchronization between R&S TSM6B and R&S TSMExxDC / R&S TSME6, you need the synchronization cable R&S TSME6-ZC4, which is required for 3 and more devices.

For the DC power between R&S TSM6B-BP and R&S TSME6 / R&S TSMExxDC, you need two times the power cable R&S TSM6-BPPT. Alternatively you can use the dual power cable R&S TSM6-B2T. It connects the R&S TSMExxDC and R&S TSME6 via Aux1 of the R&S TSM6B.



If the R&S TSM6B is connected with a R&S TSM6B-BP, DC power must be connected to the R&S TSM6B-BP (1).

Do not connect the DC power to the R&S TSM6B (2).



Figure 7-10: DC IN connectors

1 = DC IN connector R&S TSM6B-BP

2 = DC IN connector R&S TSM6B

8 Installing firmware and software updates


8.1 Downloading setup file

Firmware and R&S TSM A6B Windows operating system update packages for the R&S TSM A6B can be downloaded from the Rohde & Schwarz webpage <https://www.rohde-schwarz.com/us/firmware/tsmx>. The firmware setup file can be found under the title *R&S TSM A_x Firmware V ww.xx.yy.zz*.

The EDGE browser setup package can be downloaded from the Rohde & Schwarz webpage <https://www.rohde-schwarz.com/us/software/tsmx>.



Download the R&S TSME Tools setup package as a **distributor version** from the Rohde & Schwarz webpage <https://www.rohde-schwarz.com/us/software/tsmx>.



For R&S NESTOR, R&S SmartONE and R&S ViCom, contact the appropriate sales channel.

8.2 Prerequisites

To execute the setup on the R&S TSM A6B, the mode of operation has to be "PC Mode".



The PC Mode is not necessary for the following software packages.

- R&S NESTOR
- R&S TSM A6B

1. Open the R&S TSM A6B web GUI (see [Chapter 8.3.4, "Calling R&S TSM A6B web GUI"](#), on page 93).
2. The mode of operation is displayed in the "Overview" page. If the mode is already "PC Mode", you can skip this section.

TSM6B

Home

Configuration

- System
- Connectivity

File Transfer

Options

Update

Backup

Restart

Help

OSA

Overview

Overview IP Settings HW Info

Device Info

Type	TSM6B
Material No.	4900.8005k20
Serial No.	101025
Computer Name	TSM6B-101025
Mode of Operation	PC Mode

Bluetooth/WLAN BT: On / WLAN: On / AP: On

FW/SW Version

HW	1.00
Image	1.2 / 1.1
Firmware	4.2.0.0
ViCom	20.3.0.2138
NESTOR	21.2.0.19518
ROMES	21.2.0.774
EDGE	4.2.0.0
Microsoft Edge	93.0.961.38
TSME Device Manager	1.7.4.1
SmartONE	21.2.42

Battery Info


Battery 1	not used
Battery 2	not used
Battery Life Time	
Mainboard Temperature	39 °C

Status

No error

© 2019 ROHDE&SCHWARZ. All rights reserved.

3. If a different mode is active, navigate to "Configuration" > "System" > "Mode".
4. Select the "PC Mode".
5. Press the "Submit" button.



6. Reload the web GUI after changing the mode.
7. Ensure that the "Mode of Operation" is "PC Mode".

8.3 Updating firmware/software/tools - general instructions

After a firmware update, perform the following steps.


- [Chapter 8.4, "R&S TSME tools update"](#), on page 94)
- [Chapter 8.5, "Microsoft EDGE browser update"](#), on page 97

8.3.1 Local execution of the setup file


The local setup is executed from a remote PC and is useful if you have the device at your own workplace. Mouse, monitor and keyboard must be connected to the device directly. You need a LAN or WLAN connection between the R&S TSMAX and the remote PC.

1. Connect a mouse and a keyboard to USB ports and a monitor to the HDMI port. The setup file must be available on the R&S TSM6B or on a USB flash drive.


2. Switch on the R&S TSM6B via the power button.
3. Copy the setup file for firmware/software/EDGE/TsmeTools (.zip or .exe) into a temporary directory on the R&S TSM6B.
4. Check that R&S TSM6B is in "PC Mode" (see [Chapter 8.2, "Prerequisites"](#), on page 80).
5. Open the Windows Explorer.
6. Execute the setup file TSMAX-Setup-<Version>.exe.
7. The "R&S Software Distributor" window opens. Select "Local Installation" and "Next >".




8. In the License Agreement window, check "I accept the license agreement".



9. Select "Next>".
10. The package dialog lists all the available packages in the setup. In general, you can skip this dialog without any changes. Select "Automatic Reboot".




11. Select "Install >".
The progress bar indicates the installation process.



Note: Do not switch off or unplug from power while running a firmware/software update.

12. The device reboots automatically after the installation is complete. If the automatic reboot does not start, reboot manually.



13. If the firmware package contains a new mainboard firmware, a separate flash routine starts in a post process, see [Chapter 8.3.5, "Subsequent steps after firmware update"](#), on page 94).
14. Reload the web GUI.

15. Verify the displayed firmware/software version in the "Overview" menu. You must see the installed version.
16. The firmware update has finished successfully and the device is ready for operation, when the LEDs display the following state.
Mode LED = green resp. blue (depends on the state of the WLAN access point)
17. To configure the required measurement mode, see [Chapter 6.6, "Selecting measurement mode"](#), on page 53.

The R&S TSMA6B is ready for operation.

8.3.2 Remote installation of the setup file

The remote setup is the preferred way, if the device is not accessible on site or if multiple TSMAX devices are to be updated simultaneously.

1. Copy the setup file (firmware `TSMAX-Setup-<Version>.zip` or software) into a temporary directory on the remote PC.
2. Establish a LAN respectively WLAN connection between the remote PC and the R&S TSMA6B. Make sure that the "Mode of Operation" is "PC Mode" (see [Chapter 8.2, "Prerequisites"](#), on page 80).

a) Using LAN connection


- Connect the LAN port of the R&S TSMA6B with the host PC LAN port.
The LAN symbol marks the LAN port.




The default IP setting of this port is "DHCP client". For details on how to configure the remote PC, contact your network administrator.

b) Using WLAN connection

- The WLAN/Bluetooth switch must be "On".
 - On the remote PC, search for the R&S TSMA6B WLAN and connect to the network. You find the parameters for the TSMAX WLAN access on a label on the bottom of the device.
WLAN SSID *TSMA6B<xxxxxx>* xxxxxx: device serial number (see bottom label)
WLAN key: *instrument* (default)
3. Execute the firmware/software setup file on the connected remote PC. The "R&S Software Distributor" dialog box opens.




4. Select "Remote Installation" and "Next>".
5. In the License Agreement window, check "I accept the license agreement".




6. Select "Next>".

7. The package dialog lists all the available packages to install.



All packages, which you need to install, are already pre-selected.

8. Select "Next>".
9. After a while, a list with all R&S TSM A6B devices in the network appears in the "Device List" dialog. Devices are only available in the list if the device is in "PC Mode" (see [Chapter 8.2, "Prerequisites"](#), on page 80). Tick one or more devices to update. If there is no entry in the column "Serial No.", move the mouse pointer over the listed items to get related device information.



10. Select "Install".

Note: Do not switch off or unplug from power while running a firmware/software update.

11. The state of the installation process is displayed in the "Status" column. The process has finished when the status indicates "Ready, see report for details!".

Note: If you are connected via WLAN, reconnection to the R&S TSMA6B WLAN access point can be necessary as the R&S TSMA6B reboots after the firmware/software update.

12. Select "Exit" to end the setup program on the remote PC.

13. **Only** for firmware update.

If the firmware package contains a new mainboard firmware, a separate flash routine starts in a post process, see [Chapter 8.3.5, "Subsequent steps after firmware update"](#), on page 94.

Note: If you are connected via WLAN, reconnection to the R&S TSMA6B WLAN access point can be necessary as the R&S TSMA6B reboots after the firmware/software update.

14. Reload the R&S TSMA6B web GUI (see [Chapter 8.3.4, "Calling R&S TSMA6B web GUI"](#), on page 93).

15. Verify the installed firmware /software version in the "Overview".

16. The firmware/software update has finished successfully and the device is ready for operation when the firmware / software appears correctly in the "Overview" page of the R&S TSMA6B web-GUI.

17. To configure the required measurement mode, see [Chapter 6.6, "Selecting measurement mode"](#), on page 53.


The R&S TSMA6B is ready for operation.

8.3.3 Installation using a USB flash drive


The setup is initiated via the web GUI of the R&S TSMA6B. In this case, the setup file must be available in the root directory of a USB flash drive, which is connected to the R&S TSMA6B. To initiate the setup, a tablet or handheld device is used usually, which is connected via LAN or WLAN with the R&S TSMA6B.

1. Connect a mouse and a keyboard to the USB ports and a monitor to the HDMI port.
2. Switch on the R&S TSMA6B via the power button.
3. Copy the setup file for firmware/software/EDGE/TsmeTools (.exe) into the root directory of the USB memory stick.
4. Open the R&S TSMAx web GUI (see [Chapter 8.3.4, "Calling R&S TSMA6B web GUI"](#), on page 93).
5. In the R&S TSMAx web GUI, navigate to the menu "Update".
6. Select the appropriate setup file in the combo box.
7. Select "Update Software" next to the select box.

The "Update" button is only active if a valid `TSMAx-Setup-<Version>.exe` setup file is available in the root directory of the connected USB flash drive. For some of the installer packages, the measurement mode of the device needs to be "PC Mode" to be selectable, see [Chapter 8.2, "Prerequisites"](#), on page 80.



8. A confirmation dialog appears. Confirm with "OK" to start the update.



9. The firmware/software installation starts. The status text in the web GUI displays "Installation in progress...".



The Mode LED starts blinking blue.

Note: Do not switch off or unplug from power while running a firmware/software update.

10. Once the installation of all firmware/software packages has finished, the R&S TSMA6B reboots.
After reboot, the firmware is running a self-test (Mode LED is blinking green).
Note: If you are connected via WLAN, reconnection to the R&S TSMA6B WLAN access point can be necessary.
11. Open the web GUI. After a while, the status text in the web GUI changes to `No error`.
The reboot has finished when the Mode LED changes into steady blue (WLAN AP On) or green (WLAN AP Off) color.
12. **Only** for firmware installation.
If the firmware package contains a new mainboard firmware, a separate flash routine starts in a post process, see [Chapter 8.3.5, "Subsequent steps after firmware update"](#), on page 94.
Note: If you are connected via WLAN, reconnection to the R&S TSMA6B WLAN access point can be necessary as the TSMAx reboots after the mainboard flash.
13. Reload the R&S TSMA6B web GUI (see [Chapter 8.3.4, "Calling R&S TSMA6B web GUI"](#), on page 93).
14. Verify the installed firmware /software version in the "Overview".

The screenshot displays the R&S TSM6B web GUI. The left sidebar contains a navigation menu with options: Home, Configuration (System, Connectivity), File Transfer, Options, Update, Backup, Restart, Help, and OSA. The main content area is titled 'Overview' and includes tabs for Overview, IP Settings, and HW Info. The 'Overview' tab is active, showing the following information:

Device Info	
Type	TSM6B
Material No.	4900.8005.02
Serial No.	900020
Computer Name	TSM6B-900020
Mode of Operation	PC Mode
Bluetooth/WLAN	BT: On / WLAN: On / AP: On

FW/SW Version	
HW	5.00
Image	1.2 / 1.2
Firmware	03.00.10.02
ViCom	16.25.0.743
ROMES	18.3.0.347

Battery Info	
Battery 1	96 %
Battery 2	99 %
Battery Life Time	Ext. DC
Mainboard Temperature	41 °C

At the bottom, the 'Status' section indicates 'No error'. A copyright notice at the bottom right reads: © 2019 ROHDE&SCHWARZ. All rights reserved.

15. The device is ready for operation when the firmware/software appears correctly and the TSM6B is in the "Ready" state.

R&S TSM6B: Mode LED = green resp. blue (depends on the state of the WLAN access point)

16. To configure the required measurement mode, see [Chapter 6.6, "Selecting measurement mode"](#), on page 53.

8.3.4 Calling R&S TSM6B web GUI

Load the R&S TSM6B web GUI before executing firmware / software setup.

- Remote from a WLAN connected device
Start the browser and enter the following URL:
`http://192.168.137.1`
- Remote from a LAN connected device
Enter the URL `http://TSM6B-xxxxxx.local` into the browser.
TSM6B-xxxxxx = R&S TSM6B host name

This information can be found on a label at the bottom.

- Local
Open the browser (Microsoft EDGE or Internet Explorer). The web GUI starts automatically. If not, enter the URL `http://localhost` into the browser.


8.3.5 Subsequent steps after firmware update

The following steps are only performed during a firmware update, if the firmware package contains a new mainboard firmware.

1. About one minute after the operating system is up again, the mainboard firmware starts flashing.

The following dialog appears:

NOTE: The dialog is only visible for local installation procedure.



```
"Bootloader_GUI.exe" /file TSMAMainBoardCtr.cyacd /name TSM6B /ini flashtool.ini
Application for flashing PSoC devices

Bootload Device TSM6B.
Flash firmwarefile TSMAMainBoardCtr.cyacd.
Please note that this can take a few minutes!
Started Flashing device at 08:23:51...
....Flashing device TSM6B was successful.
```

The rear panel LEDs and the internal fans indicate the mainboard firmware flash like following:

- Meas LED = red / green
 - Mode LED = blue / green
 - Internal fans are running with full speed
2. After the mainboard firmware flash has finished, the device reboots.
The device enters the selected "Mode of Operation".

8.4 R&S TSME tools update

The R&S TSME Tools are used for diagnostics and maintenance purposes of the R&S TSMAX devices. As a recommendation, always install the latest version on the devices.



For the R&S TSME Tools installation on the R&S TSMAX devices, use only the R&S Distributor version `TSMAX-TsmeTools-<version>.exe`.

Example: `TSMAX-TsmeTools-v1.7.4.1.exe` (current version).


8.4.1 Preparation

1. Download the R&S TSME Tools setup file
TSMAX-TsmeTools-v<x.y.z.z1>.exe from <https://www.rohde-schwarz.com/software/tsmx/>.
2. Choose the way of installation (local, remote, USB flash drive).
3. Follow the instructions on how to update the R&S TSME Tools (see [Chapter 8.3, "Updating firmware/software/tools - general instructions"](#), on page 82).

8.4.2 R&S TSME tools local installation

Follow the general instructions in [Chapter 8.3.1, "Local execution of the setup file"](#), on page 82, [step 1](#) to [step 7](#).

The "R&S Software Distributor" window opens. Select "Local Installation" and "Next".



All subsequent steps are similar to local firmware installation, see [Chapter 8.3.1, "Local execution of the setup file"](#), on page 82, [step 8](#) and following.




Do not switch off or unplug from power while running a firmware/software update.

8.4.3 R&S TSME tools remote installation

Follow the general instructions in [Chapter 8.3.2, "Remote installation of the setup file"](#), on page 86, [step 1](#) to [step 3](#).

The "R&S Software Distributor" opens. Select "Remote Installation" and "Next >".



All subsequent steps are similar to remote firmware installation, see [Chapter 8.3.2, "Remote installation of the setup file"](#), on page 86, [step 5](#) and following.

8.4.4 R&S TSME tools installation using a USB flash drive


Follow the general instructions in [Chapter 8.3.3, "Installation using a USB flash drive"](#), on page 90, [step 1](#) to [step 6](#).

Select the appropriate R&S TSME Tools setup file

TSMAX-TsmeTools-v<x.y.z.z1>.exe and press "Update Software" next to the select box.

The "Update Software" button is only active if a valid

TSMAX-TsmeTools-<Version>.exe setup file is available in the root directory of the connected USB flash drive and the device is in "PC Mode".



The following steps are similar to the installation using a USB flash drive, see [Chapter 8.3.3, "Installation using a USB flash drive"](#), on page 90, [step 8](#) and following.

8.5 Microsoft EDGE browser update

Starting with firmware version 4.1.0.4 there is also a Microsoft EDGE browser installation available for R&S TSM6B/TSM6B.

The Microsoft EDGE browser replaces the formerly used Internet Explorer for the TSM6B web-GUI as the Internet Explorer is no longer supported by Microsoft. It also brings a better compatibility with the web-based tools R&S SmartBenchmarker and R&S SmartAnalytics as the Internet Explorer is incompatible with these products.



For the Microsoft EDGE browser installation on the R&S TSM6B/TSM6B, use the dedicated TSM6B EDGE setup. `TSM6B-EDGE-Setup-<version>.zip`.

Example: `TSM6B-EDGE-Setup-v4.1.0.5.zip` (current version).


8.5.1 Preparation

1. Download the Microsoft EDGE browser setup file TSMAX-EDGE-Setup-<version>.zip from <https://www.rohde-schwarz.com/us/software/tsmx>.
2. Choose the way of installation.
3. Follow the instructions how to update the browser.

8.5.2 Microsoft EDGE browser local installation

Follow the general instructions in [Chapter 8.3.1, "Local execution of the setup file"](#), on page 82, [step 1](#) to [step 7](#).

The "R&S Software Distributor" window opens. Select "Local Installation" and "Next".



All subsequent steps are similar to local firmware installation, see [Chapter 8.3.1, "Local execution of the setup file"](#), on page 82, [step 8](#) and following.




Do not switch off or unplug from power while running a firmware/software update.

8.5.3 Microsoft EDGE browser remote installation

Follow the general instructions in [Chapter 8.3.2, "Remote installation of the setup file"](#), on page 86, [step 1](#) to [step 3](#).

The "R&S Software Distributor" opens. Select "Remote Installation" and "Next >".



All subsequent steps are similar to remote firmware installation, see [Chapter 8.3.2, "Remote installation of the setup file"](#), on page 86, [step 5](#) and following.


8.5.4 Microsoft EDGE browser installation using a USB flash drive

Follow the general instructions in [Chapter 8.3.3, "Installation using a USB flash drive"](#), on page 90, [step 1](#) to [step 6](#).

Select the appropriate Microsoft EDGE setup file

TSMa-EDGE-Setup-<Version>.exe and press "Update Software" next to the select box.

The "Update Software" button is only active if a valid TSMa-EDGE-<Version>.exe setup file is available in the root directory of the connected USB flash drive and the device is in "PC Mode".



The following steps are similar to the installation using a USB flash drive, see [Chapter 8.3.3, "Installation using a USB flash drive"](#), on page 90, [step 8](#) and following.

8.6 Software update - details



Make sure that the latest firmware is installed on the device before you start with the installation of software packages.



For software installations (R&S NESTOR, R&S SmartONE, R&S ViCom), only use the TSM6B-specific setup files (TSM6B-<AppName>-|<version>-setup.exe).

8.6.1 R&S Remote ViCom software

The R&S Remote ViCom server (rViCom) is an additional software package for the R&S TSM6B.



An upgrade of the R&S Remote ViCom package is only recommended when operating the R&S TSM A6B in "rViCom Server" mode.

The update of the R&S Remote ViCom package installation could be neglected for other modes of operation (R&S NESTOR, ROMES, QualiPoc).



The installed version of the R&S Remote ViCom server on the R&S TSM A6B needs to match with the applied version of the R&S Remote ViCom client API on the remote Android device.

In cases of a client / server mismatch, there are the following possibilities:

- Downgrade the R&S Remote ViCom server version on the R&S TSM A6B to match with the applied R&S Remote ViCom client version on the Android device.
- Upgrade the R&S Remote ViCom client version on the connected tablet / smart-phone to comply with the installed R&S Remote ViCom server version on the R&S TSM A6B.


8.6.1.1 Preparation

1. To get the setup file `TSMAX-rViCom-Setup-<Version>.exe`, contact the R&S customer support.
2. Choose the way of installation.
3. Follow the instructions on how to prepare.

8.6.1.2 R&S Remote ViCom server local installation

Follow the general instructions in [Chapter 8.3.1, "Local execution of the setup file"](#), on page 82, [step 1](#) to [step 7](#).

The "R&S Software Distributor" window opens. Select "Local Installation" and "Next".



All subsequent steps are similar to local firmware installation, see [Chapter 8.3.1, "Local execution of the setup file"](#), on page 82, [step 8](#) and following.




Do not switch off or unplug from power while running a firmware/software update.

8.6.1.3 R&S Remote ViCom server remote installation

Follow the general instructions in [Chapter 8.3.2, "Remote installation of the setup file"](#), on page 86, [step 1](#) to [step 3](#).

The "R&S Software Distributor" opens. Select "Remote Installation" and "Next >".




All subsequent steps are similar to remote firmware installation, see [Chapter 8.3.2, "Remote installation of the setup file"](#), on page 86, [step 5](#) and following.

8.6.1.4 R&S Remote ViCom server installation using a USB flash drive

Follow the general instructions in [Chapter 8.3.3, "Installation using a USB flash drive"](#), on page 90, [step 1](#) to [step 6](#).

Select the appropriate setup file `TSM6B-rViCom-Setup-<Version>.exe` and press "Update Software" next to the select box.

The "Update Software" button is only active if a valid `TSM6B-rViCOM-Setup-<Version>.exe` setup file is available in the root directory of the connected USB flash drive and the device is in "PC Mode".



The following steps are similar to the installation using a USB flash drive, see [Chapter 8.3.3, "Installation using a USB flash drive"](#), on page 90, [step 8](#) and following.

8.6.2 R&S NESTOR software



Only execute the dedicated R&S NESTOR setup for R&S TSM6B. The setup file is named `TSM6x_NESTOR_Setup-<Version>.exe`.


8.6.2.1 Preparation

1. Download the software setup file `TSM6x_NESTOR_Setup-<Version>.exe` from the Rohde & Schwarz FTP server.
2. Choose the way of installation.
3. Follow the instructions on how to prepare.

8.6.2.2 R&S NESTOR local installation

Follow the general instructions in [Chapter 8.3.1, "Local execution of the setup file"](#), on page 82, [step 1](#) to [step 7](#).

The "R&S Software Distributor" opens. Select "Local Installation" and "Next".



All subsequent steps are similar to local firmware installation, see [Chapter 8.3.1, "Local execution of the setup file"](#), on page 82, [step 8](#) and following.




Do not switch off or unplug from power while running a firmware/software update.

8.6.2.3 R&S NESTOR remote installation

Follow the general instructions in [Chapter 8.3.2, "Remote installation of the setup file"](#), on page 86, [step 1](#) to [step 3](#).

The "R&S Software Distributor" opens. Select "Remote Installation" and "Next >".




All subsequent steps are similar to remote firmware installation, see [Chapter 8.3.2, "Remote installation of the setup file"](#), on page 86, [step 5](#) and following.

8.6.2.4 R&S NESTOR installation using a USB flash drive

Follow the general instructions in [Chapter 8.3.3, "Installation using a USB flash drive"](#), on page 90, [step 1](#) to [step 6](#).

Select the appropriate R&S NESTOR setup file `TSMax_NESTOR_Setup-<Version>.exe` and press "Update Software" next to the select box.

The "Update Software" button is only active if a valid `TSMax-NESTOR-Setup-<Version>.exe` setup file is available in the root directory of the connected USB flash drive.



The following steps are similar to the installation using a USB flash drive, see [Chapter 8.3.3, "Installation using a USB flash drive"](#), on page 90, [step 8](#) and following.

8.6.3 R&S SmartONE setup (R&S SmartBenchmarker, ROMES, QualiPoc)



As a recommendation, install and use the Microsoft Edge browser with R&S SmartONE.



The setup file is named `TSM6B-SmartONE_x.y.z.exe` (example: `TSM6B-SmartONE_20.3.35.exe`).

The R&S SmartONE installation contains the following applications.

- R&S SmartBenchmarker
- ROMES
- R&S QualiPoc
- R&S SmartMonitor


8.6.3.1 Preparation

1. Download the R&S SmartONE setup file `TSMaX-SmartONE_x.y.z.exe` from the Rohde & Schwarz FTP server respectively R&S SmartONE CD-ROM.
2. Choose the way of installation.
3. Follow the instructions how to prepare.

8.6.3.2 R&S SmartONE local installation

Follow the general instructions in [Chapter 8.3.1, "Local execution of the setup file"](#), on page 82, [step 1](#) to [step 7](#).

The "R&S Software Distributor" opens. Select "Local Installation" and "Next".



All subsequent steps are similar to local firmware installation, see [Chapter 8.3.1, "Local execution of the setup file"](#), on page 82, [step 8](#) and following.

8.6.3.3 R&S SmartONE remote installation

Follow the general instructions in [Chapter 8.3.2, "Remote installation of the setup file"](#), on page 86, [step 1](#) to [step 3](#).

The "R&S Software Distributor" opens. Select "Remote Installation" and "Next >".




All subsequent steps are similar to remote firmware installation, see [Chapter 8.3.2, "Remote installation of the setup file"](#), on page 86, [step 5](#) and following.

8.6.3.4 R&S SmartONE installation using a USB flash drive

Follow the general instructions in [Chapter 8.3.3, "Installation using a USB flash drive"](#), on page 90, [step 1](#) to [step 6](#).

1. Select the appropriate R&S SmartONE setup file `TSMAX-SmartONE_x.y.z.exe`.
2. Press "Update Software" next to the select box.
The "Update Software" button is only active if a valid `TSMAX-SmartONE_x.y.z.exe` setup file is available in the root directory of the connected USB flash drive.



3. The following steps are similar to the installation using a USB flash drive, see [Chapter 8.3.3, "Installation using a USB flash drive"](#), on page 90, [step 8](#) and following.


8.6.3.5 Initial software start / measurement mode selection

After the successful installation of R&S SmartONE, the device is always in "QualiPoc" mode.

Initial starting of R&S SmartONE Expert (ROMES)

1. Start the web GUI.
2. Navigate to "Configuration" > "System" > "Mode".
3. As "Mode of Operation" select "SmartONE Expert".


Make sure that "Autostart" is deselected and no workspace is selected.




4. Select "Submit".

After starting ROMES, configure the following settings.

1. In the "Romes Technology Selector", select the technologies which you want to be supported by your ROMES installation.




2. Select "OK".
3. In the "ROMESTecSelectorGUI" window, select "OK".




The current installation is adapted according to your selection and the ROMES start process continues.

4. In the "User" window, check that the "User Level" is "Normal".
5. Select "Don't Ask again".



- In the "Installation Check", select "Don't Ask again" and "Continue".



Initial starting of R&S SmartONE Standard (R&S SmartBenchmarker)

- Start the web GUI.
- Navigate to "Configuration" > "System" > "Mode".
- As "Mode of Operation", select "R&S SmartONE Standard".

For further details about using R&S SmartBenchmarker, refer to *R&S SmartBenchmarker - Manual*.

9 Installing software options (scanner, R&S NESTOR)

9.1 Installing scanner options

To install scanner options, perform the following steps.

1. Start the web GUI of the R&S TSMA6B.
2. Navigate to "Options" > "Install" Tab (see ["Install Scanner Options"](#) on page 168)
3. Add the license keycode of a specific scanner option in the field "Install Scanner Options" manually.
4. Select "Install".
5. Alternatively, you can install a scanner option by selecting a license .xml file and selecting "Install XML file."

9.2 Installing R&S NESTOR options

A later enhancement of the R&S TSMA6B with options requires a USB license dongle.

To install R&S NESTOR options, perform the following steps.

1. Start the web GUI of the R&S TSMA6B.
2. Navigate to "Options" > "Install" Tab (see ["Install NESTOR Options"](#) on page 168).
3. Add the license keycode of a specific NESTOR option in the field "Install NESTOR Options" manually.
4. Select "Install".

10 User backup and restore

10.1 Creating a user backup

The user backup creates an image copy of partition C : / on a hidden partition on the device SSD.



The backup procedure takes up to 15 minutes.

During the backup, do not interrupt the procedure or disconnect the power supply.

To create a user backup, click the "Backup" button in the web GUI menu "Backup", see "[Backup TSM6B System](#)" on page 169.

If there is already a user backup available a dialog comes up, which alerts that the existing user backup is overwritten. The backup creation proceeds, if you confirm the dialog.

The status of the backup generation process is displayed via the [Mode] LED, see [Table 10-1](#).

After the creation of the backup image has finished, the device reboots and enters again the selected "Mode of Operation".

Table 10-1: LED states (Backup)

[Mode] LED	Status
Red blinking	Backup process running
Green continuous	Backup process finished, WLAN AP off
Blue continuous	Backup process finished, WLAN AP on

10.2 Restoring a backup

The Restore button brings the device back to factory / user default configuration according to [Table 10-2](#).

Use a blunt pen (diameter 1 mm to 2 mm) for pressing the Restore button.

Min. button hold time for restore trigger: 20 s.

The restore process is indicated by the [Mode] LED (see [Table 10-3](#)).



The restore procedure takes up to 15 minutes.

During this time, do not interrupt the procedure or disconnect the power supply.



Loss of user settings after restore

Executing restore brings the R&S TSMA6B irreversible back to the condition of delivery or any other subsequently created user backup state.

On the C:\ drive, all user settings and installed programs since the last backup is deleted.

The D:\ partition is deleted too, if enabled in the backup / restore configuration of the web-GUI, see "[Delete data partition D:](#)" on page 169.

Table 10-2: Restore conditions

Initiate Restore / Available Partitions	Restore button	Restore button	Restore factory backup (see Chapter 10.4, "Restoring the factory backup" , on page 117)
Factory Backup	X	X	X
User Backup (see Chapter 10.1, "Creating a user backup" , on page 115)	No user backup (factory default)	X	X
Condition after restore			
Partition C:\	C:\factory backup	C:\user backup	C:\factory backup
Partition D:\ (default)	Unchanged	Unchanged	Unchanged
Partition D:\ (web-GUI setting " Delete data partition D: " on page 169)	deleted	deleted	deleted

When the restore procedure has been completed, the R&S TSMA6B reboots. The color of the [Mode] LED depends on the state of the WLAN AP (see [Table 10-3](#)).

Table 10-3: LED states (Restore)

[Mode] LED	Status
Blue blinking	Restore process running
Green	Restore process finished, WLAN AP off
Blue	Restore process finished, WLAN AP on

10.3 Restoring with Debian installation

Follow the procedure as described in [Chapter 10.2, "Restoring a backup"](#), on page 115.



After restoring an R&S TSMA6B with an existing Debian backup, the Debian installation is recovered automatically at the initial power-up sequence.

If you have a system with an existing Debian backup, an additional entry "Restore Debian" is available in the web-GUI.



If you press "Start", the current Debian installation is overwritten with your Debian backup.

10.4 Restoring the factory backup

The system recovery via the "Restore" button recovers always to the latest user backup if available on the device (see [Table 10-2](#)). Only if no user backup exists the recovery via the restore button recovers the factory backup.

To restore the factory backup at the presence of a user backup, perform the following steps.

1. Connect mouse, keyboard and monitor to the R&S TSM6B.
2. Press the [Shift] key and reboot the operating system.
3. The R&S TSM6B reboots in the R&S recovery environment.
4. Select "Factory Default Restore".
5. Select "Start Recovery".
The R&S TSM6B recovery starts and the "Mode" LED blinks green.
NOTE: Do not interrupt the recovery process.
6. When the recovery has finished, press Exit/Reboot.

After a few minutes, a mainboard firmware flash can start, indicated by the full speed of the internal fans (recognizable by the loud fan noise, see [Chapter 8.3.5, "Subsequent steps after firmware update"](#), on page 94).

- After the mainboard firmware flash has finished, the device enters the selected "Mode of Operation".

10.5 Capturing and applying R&S TSM6B images

Use the R&S TSM6B image stick to capture and apply Windows images.

- [Preparing a backup for R&S TSM6B image stick](#)..... 118
- [Creating an R&S TSM6B image stick](#)..... 119
- [Booting from the R&S TSM6B image stick](#)..... 120
- [Capturing an image from R&S TSM6B](#)..... 120
- [Applying an image to R&S TSM6B](#)..... 122

10.5.1 Preparing a backup for R&S TSM6B image stick

For a R&S TSM6B system with an active Debian installation, an intermediate step (backup Debian) is necessary to prepare the system image for the application of the R&S TSM6B image stick.




Only applicable to capture a R&S TSM6B image with the R&S TSM6B image stick (see <https://www.rohde-schwarz.com/de/software/tsma6b/>). For details about using the R&S TSM6B image stick, see [R&S TSM6B Image Stick Supplement](#).


The "Backup Debian" entry in the web-GUI is only visible if an active Debian installation is available on the device.

To install a Debian system, see ["Install Debian"](#) on page 169.


To create the Debian backup, press "Start" beside the entry "Backup Debian" and confirm the upcoming dialog with "OK".



The status of the backup creation process is displayed in the bottom status line of the web-GUI.

-  After restoring an R&S TSMA6B with an existing Debian backup, the Debian installation is recovered automatically at the initial power-up sequence.

10.5.2 Creating an R&S TSMA6B image stick


-  You need administrator rights on the PC, where you create the image stick.

To create an R&S TSMA6B image stick, proceed as follows.

Prerequisites:

- A bootable USB flash drive (USB 3.1 Gen1) with a capacity of at least 64 GB. Make sure that the data on the USB flash drive is no longer needed as it will be formatted during the process of R&S TSMA6B image stick creation.
- Download the "R&S TSMA6B Image Stick" (TSMA6B_ImageStick-v<x.y>.zip) tool (<https://www.rohde-schwarz.com/us/software/tsmx>).
- On a PC, unzip the file TSMA6B_ImageStick-v<x.y>.zip to a directory of your own choice. The extracted directory contains the PrepareWinPEStick.exe file.

1. Insert the USB flash drive into a free USB 3.1 port of a PC.
2. Execute the PrepareWinPEStick.exe file in the directory where you have saved the file.
3. Select the USB flash drive via the "Removable Device Selection" drop-down box.



4. Press "Create RecoveryStick".

In the main directory of the image stick, the following directories and files are created automatically:

- /Boot
- /Device
- /EFI
- /sources
- bootmgr
- bootmgr.efi

When the creation of the image stick has finished, you can boot the R&S TSMA6B from this stick.

10.5.3 Booting from the R&S TSMA6B image stick

To boot from the R&S TSMA6B image stick, proceed as follows.

1. Connect mouse, keyboard and monitor to the R&S TSMA6B.
2. Insert the created R&S TSMA6B image stick (see [Chapter 10.5.2, "Creating an R&S TSMA6B image stick"](#), on page 119) into a free USB 3.0 port ([Figure 3-11](#)) on the R&S TSMA6B.
3. Power on the R&S TSMA6B.
4. During boot up, press [F10] to enter the boot menu.
5. Select the R&S TSMA6B image stick from the list of boot devices and press <Enter>.

The Windows PE environment starts.

10.5.4 Capturing an image from R&S TSMA6B




For a system with an existing Debian installation, you must create a Debian backup first. See [Chapter 10.5.1, "Preparing a backup for R&S TSMA6B image stick"](#), on page 118 for details.

To capture an image from an R&S TSMA6B device, proceed as follows:


NOTE: No image files may be present on the R&S TSMA6B image stick in the directory `Device/Images`. Otherwise, capturing the image from an R&S TSMA6B primary device is not possible.

1. Boot from the R&S TSMA6B primary device via image stick (see [Chapter 10.5.3, "Booting from the R&S TSMA6B image stick"](#), on page 120).
2. In the main menu, press "Capture Image".

The capture process starts automatically and the image files of the R&S TSMA6B primary device are saved on the R&S TSMA6B image stick.



3. After the capture process has finished, the message "Operation successfully done." appears.



4. Press "OK".
5. Remove the R&S TSMA6B image stick.
The R&S TSMA6B image stick now contains the image files (`/Device/Images`).
6. Press "Reboot".
The R&S TSMA6B reboots normally in the previously selected mode of operation.



The image files, which are available on the R&S TSMA6B image stick in the directory `/Device/Images` can be saved manually on a PC. So, the image files can be used to be applied on more than one device.

10.5.5 Applying an image to R&S TSMA6B



Images which are captured from R&S TSMA6B devices with an external SSD (R&S TSMA6B-BEP) can only be applied to devices that also have an external SSD.

To apply an image to an R&S TSMA6B device, the following files must be available in the directory `Device/Images` on the R&S TSMA6B image stick.


- `BACKUP.wim`
- `Data.wim`
- `RECOVERY.wim`
- `SYSTEM.wim`




These files can be copied manually from a PC to the image stick or are the result of capturing an image (see [Chapter 10.5.4, "Capturing an image from R&S TSMA6B"](#), on page 120).

To apply an image to an R&S TSMA6B, proceed as follows:

1. Boot the R&S TSMA6B image stick from the target device (see [Chapter 10.5.3, "Booting from the R&S TSMA6B image stick"](#), on page 120).
2. In the main menu, press "Apply Image".
The applying process starts automatically. The image files from the R&S TSMA6B primary device are transferred to the R&S TSMA6B target device.



3. After the apply process has finished, the message "Operation successfully done." appears.



4. Press "OK".

5. Remove the R&S TSMA6B image stick.
6. Press "Reboot".
The R&S TSMA6B reboots from the deployed image.

11 Troubleshooting



For all troubleshooting procedures, connect a keyboard, a mouse and a monitor to the R&S TSMA6B.

• LED indicated errors	125
• Evaluate self-test file	126
• Access the firmware log file	126
• Write battery info into the firmware log file	126
• Verify scanner link / recall device info using the R&S TSME device manager	127
• R&S TSMA6B automatically switches off after power on	131
• Scanner is not found from software (ROMES, R&S NESTOR)	132
• Verify LAN settings (internal scanner connection)	135
• No remote access via LAN port	136
• WLAN access point not detected by an external PC, mobile or tablet	140
• Web GUI not accessible via WLAN connection	142
• Web GUI not locally accessible	143
• Slow/Instable WLAN connection	145
• Bluetooth device not detected by R&S TSMA6B	145
• No RF / GPS data	147
• Contacting customer support	148

11.1 LED indicated errors

- "Mode" LED blue blinking fast – self-test error
 - Check the scanner connection (see [Chapter 11.8, "Verify LAN settings \(internal scanner connection\)"](#), on page 135).
 - Evaluate the `Selftestresult.txt` (see [Chapter 11.2, "Evaluate self-test file"](#), on page 126).
- "State" LED red blinking (2 Hz) – temperature warning
 - Check the ventilation openings and the operating temperature.
 - Switch off the device and let it cool down.
- "State" LED red continuous – overheated unit
 - Switch off the device and let it cool down.
 - Check the ventilation openings and switch on the device. If the problem occurs again, analyze the `Selftestresult.txt` (see [Chapter 11.2, "Evaluate self-test file"](#), on page 126).
- "Meas" LED red blinking (2 Hz) –application error
 - Refer to the application note of the software used.
- "Pwr" LED off after startup –power error
 - Contact R&S support.

11.2 Evaluate self-test file

- Path: C:\ProgramData\Rohde-Schwarz\TSMA\Selftestresults
- Filename: Selftestresult.txt

Entries in the `Selftestresult.txt` are created during the boot process of the device and every 5 minutes.

To open the `Selftestresult.txt`, proceed as follows.

1. Open a file explorer.
2. Enter the path to the directory where you find the self-test file.
3. Open the self-test file.

The following device parameters and values are stored.

- Internal voltages (nominal values / actual values)
- Temperatures (scanner / mainboard)
- Battery status info
- Status of fans
- Status of scanner interface

11.3 Access the firmware log file

The firmware log file is created once per day. A maximum of 15 files are available for download (see ["App Log"](#) on page 167).

To check the log file entries

1. Navigate to "File Transfer" > "App Log".
2. Under "Firmware Log Trace", you see the content of the current log file.

To download a log file

1. Navigate to "File Transfer" > "App Log".
2. Under "Firmware Log File", select the log file according to your needs.
The log files have the following format: `Log_YYYY-mm-dd.txt`.

11.4 Write battery info into the firmware log file

As an option, you can write the battery info also into the firmware log file (see ["Battery"](#) on page 160).

Verify scanner link / recall device info using the R&S TSME device manager

To write battery info into the firmware log file

1. Navigate to "Configuration" > "System" > "Power".
2. Under "Battery", press "Start".

The battery info is written to the firmware log file (see [Chapter 11.3, "Access the firmware log file"](#), on page 126).

11.5 Verify scanner link / recall device info using the R&S TSME device manager

1. To start the R&S TSME Device Manager, choose one of the following options.
 - a) Double-click the desktop icon.
 - b) Select in Windows:
"Start" > "R&S TSME Tools" > "TSME Device Manager"
2. The following error messages can occur.
 - **TSME Device Manager Application has stopped**
In the web GUI, check "Mode of Operation". If necessary, change to "PC Mode" and try again.
 - **No TSME connected**
In the web GUI, verify "Scanner LAN Port Settings".
3. If the "Device Info" tab (see [Figure 11-1](#)) contains scanner data, the scanner connection exists.
4. Check the "Device Analysis Output" (see [Chapter 11.5.2, "Device analysis output"](#), on page 129) and the "Options" (see [Chapter 11.5.3, "Verify installed license keys"](#), on page 130).



If the connection to an R&S TSMA6B is not established correctly, for example due to a mismatch of the scanner link IP configuration, only limited information is displayed. In this case, no information about installed options is available.

11.5.1 Obtaining device information - "Device Info"

The most important configuration settings for each available R&S TSMA6B are displayed in the "Device Info" tab of the "R&S TSME Device Manager".

Verify scanner link / recall device info using the R&S TSME device manager




Figure 11-1: Tab "Device Info"

The table includes the following information:

Table 11-1: R&S TSMA6B device information

Label	Description
Device	
Device Type	Type of device (TSME family, TSMA family)
Material Number	Order number of the R&S TSMA6B
Variant Number	Precise device type (variant)
Serial Number	Unique ID of the R&S TSMA6B

Verify scanner link / recall device info using the R&S TSME device manager

Label	Description
Product Change Index	Version of the device
MAC Address	Network address of the R&S TSMA6B
FPGA	
Available FPGA Bit File Versions	Previous firmware version backups stored on the device)
Current FPGA Bit File Version	Currently used firmware version
Power Board	
Serial Number	Unique ID of the power board
Product Change Index	Version of the power board
Controller Board	
Serial Number	Unique ID of the controller board
Product Change Index	Version of the controller board
Temperature	Current temperature of the hardware in [°]C
RF Board	
Serial Number	Unique ID of the RF board
Product Change Index	Version of the RF board
Temperature	Current temperature of the hardware in [°]C
Correction Data	
Version	Current version of the calibration data saved on the device
Type	<ul style="list-style-type: none"> • Factory The original factory calibration data are saved on the device. • Update An improved set of calibration data is available and saved on the device.
Date	Timestamp of creating and saving the calibration data on the device
TCXO Date	Date of correction data for the internal reference

11.5.2 Device analysis output

Furthermore, you can see any warnings, errors or information concerning the device status that can occur in the "Device Analysis Output" table. This table is available on all tabs at the bottom of the "R&S TSME Device Manager" window (see [Figure 11-1](#)).

Depending on their relevance, the messages are assigned to the following categories:

- **Info:** information for the user, no action required
- **Warning:** warning on behalf of the instrument - recommended being solved
- **Error:** error on behalf of the instrument - must be solved before further operation

Verify scanner link / recall device info using the R&S TSME device manager



In case measurement problems occur with the R&S TSM6B, check the "Device Analysis Output" table for any detected errors. If available, a repair function is provided.

11.5.3 Verify installed license keys

Figure 11-2: Tab "Options"

Table 11-2: Software license key information

Label	Description
Option Type	Band or technology option name
Option Material No.	Order number of the option
Option key	Software license key number
Privilege	Usage type (customer, services, demo)
Time Stamp	Time the software license key was installed
License Count	Number of times the (band upgrade) option is installed


R&S TSMA6B automatically switches off after power on

Label	Description
Activation Type	Activation can be permanent or temporary
Valid From	Start of validity for temporary license
Valid To	End of validity for temporary license
Time to Expiration	Time left until license expires
Option Index	For internal use only
Format ID	For internal use only

11.6 R&S TSMA6B automatically switches off after power on

1. Check if there is a battery pack unit connected.
 - If yes, continue with [step 2](#).
 - If no, contact R&S support.
2. Check the state of charge of the batteries.
 - If the charging state is > 20% (charging indicator displays one loading bar), continue with [step 4](#).
 - If the charging state is < 20%, an auto power off of the device starts due to insufficient remaining battery charge. Continue with [step 3](#)
3. Perform one of the following actions.
 - a) Replace the batteries with fully charged ones and try again.
 - b) Charge the batteries in an external charger and retry later.
 - c) Connect the DC power supply to the R&S TSMA6B battery pack unit and charge the batteries inside the bay. Keep the R&S TSMA6B switched off.
4. Connect the DC power supply to the R&S TSMA6B battery pack unit.
5. Navigate to "Configuration" > "System" > "Power".
6. Check the state of "Auto Power Off".
 - If enabled, check the shutdown delay.
 - If not enabled, contact R&S support.


Scanner is not found from software (ROMES, R&S NESTOR)



11.7 Scanner is not found from software (ROMES, R&S NESTOR)

To check if the scanner unit is working properly, perform the following steps.


Scanner is not found from software (ROMES, R&S NESTOR)



1. Check the LEDs of the device (see [Chapter 11.1, "LED indicated errors"](#), on page 125).
 - If the LEDs indicate an error, follow the instructions according to the indicated error.
 - If the LEDs indicate no error, continue with [step 2](#).
2. Evaluate the results of the self-test (see [Chapter 11.2, "Evaluate self-test file"](#), on page 126).
 - If there is an error in the list, check the error type.
 - If there is no error in the list, continue with [step 3](#).
3. Start the web GUI (see [Chapter 6.1.1, "Using the R&S TSMA6B web GUI"](#), on page 45).
Check "Mode of Operation" and "IP Settings".

Scanner is not found from software (ROMES, R&S NESTOR)

- If the "Mode of Operation" = "PC Mode", continue with [step 4](#).
 - If the "Mode of Operation" != "PC Mode", switch mode to "PC Mode". Restart the R&S TSMA6B via web GUI and check the LEDs, see [step 1](#).
 - If the IP address of the "SCAN Port (int)" = "192.168.0.1", continue with [step 4](#).
 - If the IP address of the "SCAN Port (int)" != "192.168.0.1", contact R&S support.
4. Check the scanner [State] LED.
 - If it is off, continue with [step 6](#).
 - If it is on, continue with [step 5](#).
 5. A program in Windows "Startup" can block the scanner module.
To open the "Startup" folder, press *Windows + R* to open the "Run" dialog box, type in `shell:startup` and then press "OK".



An explorer window right to the "Startup" folder opens.

- Remove any program entry which could interface the scanner module, restart the R&S TSMA6B via the web GUI and repeat with [step 3](#).
 - If there is no entry, contact R&S support.
6. Start the "TSME Device Manager" via the Windows "Start" menu.
"Start" > "R&S TSME Tools" > "TSME Device Manager"

Verify LAN settings (internal scanner connection)

Available Devices

Device (Serial Number): R&S TSMA6 900020 Refresh Device List Refresh Device Data

Device Info | Network Configuration | Options | Band Configuration | Updates | Self Alignment

Details

Device ID: 4900.8005K02-900020-eQ Identify

Device				
Device Type	R&S® TSMA6			
Material Number	4900.8005			
Variant Number	2			
Serial Number	900020			
Product Change Index	05.00			
MAC Address	00:90:b8:20:67:cd			
FPGA	Section 0	Section 1	Section 2	Section 3
Available FPGA Bit File Versions	04.08.10.00	04.08.10.00	unused	unused
Current FPGA Bit File Version	04.08.10.00			
Power Board				

7. Check in the "Info" tab if any device is available.
 - If the R&S TSMA6B device is available, check the "Device Analysis Output".
 - If the R&S TSMA6B device is not available, contact the R&S support.
8. Check the "Device Analysis Output".
 - If there is an error, check if autofix is possible.
If autofix is possible, then continue with [step 9](#).
If autofix is not possible, then contact R&S support.
 - If there is no error, continue with [step 9](#)
9. Check the "Options" tab (see [Figure 11-2](#)).
 - If all the required options are active, the scanner works correctly.
 - If necessary options are missing, contact R&S support.

11.8 Verify LAN settings (internal scanner connection)

1. Check the IP setting of the TSMA6B scanner connection.
Navigate to "Windows" > "Settings" > "Network & Internet" > "Network & Sharing Center" > "Change Adapter Options".
The entry "TSMA6B Scanner Connection Int" must be available.

No remote access via LAN port






Figure 11-3: TSM6B scanner connection

2. Double-click the "TSM6B Scanner Connection Int" entry.
3. Verify the following settings.
 - IP address: 192.168.0.1 (static IP address)



- "Jumbo Packet": 9014 Bytes



11.9 No remote access via LAN port

If the R&S TSM6B could not be accessed for remote control or remote desktop session via the LAN port, check the following issues:

Optical check

1. Check on the rear panel the connection of the LAN cable to the remote control LAN port (see connector (14) in [Figure 3-11](#)).
The LAN symbol indicates the LAN port.



The default setting for this port is "DHCP client". The R&S TSMA6B obtains the IP address automatically.

2. If you connect the LAN cable not to the correct LAN port, correct the cabling and try the remote access again. Otherwise, continue with [Verify LAN Settings in the web GUI](#).
3. Check the LEDs at the LAN port.
 - LED on the left (Link)
Orange permanent
 - LED on the right (Activity)
Yellow blinking

Verify LAN settings in the web GUI

1. Open the web GUI (see [Local access from the TSMA6B and Windows Explorer](#)).
The predefined start page is `http://localhost`.
Note: If the web GUI cannot be started locally, contact the R&S support.
2. Check if you see an IP address in the web GUI. This IP address match must match with the IP settings of the remote PC (IP subnet range).
See [Figure 11-4](#).
If you see no LAN port address, continue with [Check R&S TSMA6 Network Connections](#).




Figure 11-4: Web GUI - Overview > IP Settings

3. Check the setting of the R&S TSM6B LAN port (see Figure 11-5). The default setting is "DHCP".




Figure 11-5: Web GUI - LAN Connection

Ping command

Execute the `ping` command from the Windows CMD on the host PC.

1. Use the IP address displayed in the R&S TSM6B web GUI (see Figure 11-4).
2. Start the ping command.

Type in the command-line window `ping <IP address of the remote port of the R&S TSMA6B (LAN)>` and wait for the answer.

If the R&S TSMA6B does not answer, contact the system administrator or the R&S support.

Example:

```
C:\>ping 192.167.0.10
Pinging 192.167.0.10 with 32 bytes of data:
Reply from 192.167.0.10: bytes=32 time<1ms TTL=128
Reply from 192.167.0.10: bytes=32 time<1ms TTL=128
Reply from 192.167.0.10: bytes=32 time<1ms TTL=128
Reply from 192.167.0.10: bytes=32 time<1ms TTL=128
Ping statistics for 192.167.0.10:
    Packets: Sent = 4, Received = 4, Lost = 0 (0% loss),
    Approximate round trip times in milli-seconds:
        Minimum = 0ms, Maximum = 0ms, Average = 0ms
```

Check R&S TSMA6B Network Connections

Check if the "TSMA6B LAN Connection" is available in the Windows network connections.

1. Connect a keyboard, a mouse and a monitor to the R&S TSMA6B.
2. Navigate to "Windows" > "Settings" > "Network & Internet" > "Network & Sharing Center" > "Change Adapter Settings".
3. The entry "TSMA6B LAN Connection" must be available.




Figure 11-6: TSMA6B LAN Connection


4. If the "TSMA6B LAN Connection" is not available in the "Network Connections" list, we recommend a recovery of the R&S TSMA6B (see [Chapter 10, "User backup and restore"](#), on page 115).
If the "TSMA6B LAN Connection" is available in the "Network Connections" list and the IP address of the LAN port is still not displayed in the web GUI, contact R&S support.

11.10 WLAN access point not detected by an external PC, mobile or tablet

With the first R&S TSMA6B devices shipped, the WLAN module is configured to use the 2.4 GHz and 5 GHz band.

In environments with high traffic on the 2.4 GHz band, the R&S TSMA6B access point sometimes switches into the 5 GHz band after power-up. The effect is that notebooks / PCs / handheld devices with a 2.4 GHz limited WLAN module could no longer detect the TSMA6 WLAN access point. To overcome this error, the driver settings of the WLAN module of the TSMA6 need to be adapted.


1. Check the "Mode" LED.
 - "Mode" LED is permanently green => continue with [step 2](#)
 - "Mode" LED is permanently blue => continue with [step 3](#)
 - Other color => check error states (see [Chapter 11.1, "LED indicated errors"](#), on page 125)
2. Check the WLAN switch on the rear panel of the device. It must be "On".




1 = WLAN Switch (1 = "On", 0 = "Off")

3. Verify the WLAN AP settings via the web GUI.
Navigate to "Configuration" > "Connectivity" > "WLAN AP".
The "Status" must be "On".

WLAN access point not detected by an external PC, mobile or tablet



- Verify the IP settings via the web GUI.
Navigate to "Home" > "IP Settings".
IP address of WLAN AP = 192.168.137.1




- Verify WLAN adapter settings.
Many of the connection troubles are based on misconfigured WLAN adapter settings or the settings does not match the WLAN adapter settings on the host device. To check and set the WLAN adapter settings back to default, see [Chapter 6.5, "Changing WLAN settings"](#), on page 52.
Try again after settings are back to default.
- Verify the availability of the WLAN adapters in the Windows control panel.
Navigate to "Settings" > "Network & Internet" > "Ethernet" > "Change adapter options"

Web GUI not accessible via WLAN connection

Check for the following entries:

- "TSMA6B WLAN AP"
- "TSMA6B WLAN Connection"


If the adapters are not available in the list, we recommend a recovery of the factory backup (see [Chapter 10, "User backup and restore"](#), on page 115) or contact R&S support.



11.11 Web GUI not accessible via WLAN connection

If the R&S TSMA6B web GUI is not accessible, perform the following steps to solve the problem.

1. Check if the WLAN access point is active.
 - If "Mode" LED = blue, continue with [step 2](#).
 - If Mode LED != blue, continue with [Chapter 11.10, "WLAN access point not detected by an external PC, mobile or tablet"](#), on page 140.
2. For remote connection via WLAN, check if the TSMA6 WLAN is visible via your smartphone/tablet.
 - If it is visible, continue with [step 3](#).
 - If it is not visible, continue with [Chapter 11.10, "WLAN access point not detected by an external PC, mobile or tablet"](#), on page 140.
3. Check the connection between your smartphone/tablet and the TSMA6B WLAN AP.
 - If the connection exists, continue with [step 5](#).
 - If the connection does not exist, try to reconnect. If it fails again, contact R&S support.
4. Open the browser on the handheld device.
5. Enter the following URL:
http://192.168.137.1.
If the browser cannot load the webpage, continue with [step 6](#).



6. Check the IP address of the WLAN connection on your handheld device. It must be in the subnet *192.168.137.xxx*.
 - If the subnet is correct, continue with [Chapter 11.12, "Web GUI not locally accessible"](#), on page 143.
 - If the subnet is not correct, try to reconnect. If it fails again, contact R&S support.
7. Check the WLAN settings (see [Chapter 6.5, "Changing WLAN settings"](#), on page 52).

11.12 Web GUI not locally accessible


Open the web GUI locally. Start the Internet Explorer and enter the following URL to open the R&S TSMA6B web GUI.

http://localhost

1. Check for the following URL in the browser dialog.

http://localhost/TSMA/Html/overview.php

 - If the URL is not correct, enter the correct URL and reload the URL. If it fails again, reinstall the firmware [Chapter 8.3, "Updating firmware/software/tools - general instructions"](#), on page 82.
 - If the URL is correct and the following error status appears, continue with [step 3](#).



2. In the Windows "Start" menu, enter "Services".
3. Check the state of the following services.
 - R&S TSM6B Monitoring Application running?
 - R&S WebServer running?




Figure 11-7: R&S TSM6B Services

If both services are running, continue with [step 5](#).

4. Start the services that are not running.
 - a) Select the service that you want to start.
 - b) Open the context menu with a right-mouse click.
 - c) Start the service.

If the services could not be started, reinstall the firmware (see [Chapter 8.3, "Updating firmware/software/tools - general instructions"](#), on page 82).

5. Try again to start the web GUI locally on the R&S TSMA6B via Internet Explorer. If you cannot start the web GUI, perform a complete restore (see [Chapter 10, "User backup and restore"](#), on page 115).

11.13 Slow/Instable WLAN connection

If the WLAN connection is slow or sometimes interrupted, check the WLAN settings, see [Chapter 6.5, "Changing WLAN settings"](#), on page 52.

11.14 Bluetooth device not detected by R&S TSMA6B

To detect/connect a Bluetooth device with R&S TSMA6B, click "Refresh Device List" in the web GUI.


If a mobile or tablet is not detected by the R&S TSMA6B as Bluetooth device, the problem is probably the bluetooth visibility of the mobile (or tablet). This problem occurs when a new device is connected to the R&S TSMA6B for the first time.

The visibility of an Android device with firmware version ≥ 5.0 cannot be changed. The mobile (tablet) is only visible to other devices when the "Bluetooth Properties" window is open.


If you are controlling the R&S TSMA6B web GUI with the mobile and also want to couple the devices via Bluetooth, then you have to perform following steps.

1. On the R&S TSMA6B, enable Bluetooth.
2. Make Bluetooth visible (see [step 1](#)).
3. On the mobile device (mobile or tablet), open the Bluetooth properties. The R&S TSMA6B should be listed. Choose the entry for your R&S TSMA6B.


Bluetooth device not detected by R&S TSM6B



4. After choosing the R&S TSM6B, you receive a "Bluetooth pairing request". Click "OK".



5. Open the R&S TSM6B web GUI.
6. Navigate to "Configuration" > "Connectivity" > "Bluetooth".
7. Execute "Refresh Device List".
8. Wait until your mobile device and the following message "Unable to pair with TSM6B-xxxxxx. Incorrect PIN or password" appear.



9. Select the mobile device.
10. Press "Connect" for coupling the devices.

If you need to transport or ship the product, see [Chapter 12, "Transporting"](#), on page 150.

11.15 No RF / GPS data

1. Check the connection between the RF antenna and the RF port.




Figure 11-8: RF antenna connector

1 = RF port

2. Check the connection between the GPS antenna and the GPS antenna input.




Figure 11-9: GPS antenna connector

1 = GPS antenna connector

Note: Only use the GPS antenna included in the scope of delivery.

3. Check if the LEDs indicate an error (see [Chapter 11.1, "LED indicated errors"](#), on page 125).
4. Open the web GUI (Internet Explorer, URL: <http://localhost>) and change the "Mode of Operation" to "PC Mode".
5. Start the "TSME Device Manager" via the Windows "Start" menu.
"Start > R&S TSME Tools > TSME Device Manager"
 Check if there are any error messages in the "TSME Device Manager".
 - If you find errors in the "Device Analysis Output" window, follow the instructions.
 - If you do not find errors or if the repair actions via the "Device Analysis Output" window fail, contact the R&S support.

11.16 Contacting customer support

Technical support – where and when you need it

For quick, expert help with any Rohde & Schwarz product, contact our customer support center. A team of highly qualified engineers provides support and works with you to find a solution to your query on any aspect of the operation, programming or applications of Rohde & Schwarz products.

Contact information

Contact our customer support center at www.rohde-schwarz.com/support, or follow this QR code:



Figure 11-10: QR code to the Rohde & Schwarz support page

12 Transporting

Packing

Use the original packaging material. It consists of antistatic wrap for electrostatic protection and packing material designed for the product.

If you do not have the original packaging, use similar materials that provide the same level of protection. You can also contact your local Rohde & Schwarz service center for advice.

Securing

When moving the product in a vehicle or using transporting equipment, make sure that the product is properly secured. Only use items intended for securing objects.

Transport altitude

The maximum transport altitude without pressure compensation is 4500 m above sea level.

13 Maintenance, storage and disposal

The product does not require regular maintenance. It only requires occasional cleaning. It is however advisable to check the nominal data from time to time.

13.1 Cleaning

Do not use any liquids for cleaning. Cleaning agents, solvents (thinners, acetone), acids and bases can damage the front panel labeling, plastic parts and display.

13.2 Storage

Protect the product against dust. Ensure that the environmental conditions, e.g. temperature range and climatic load, meet the values specified in the specifications document.

13.3 Disposal

Rohde & Schwarz is committed to making careful, ecologically sound use of natural resources and minimizing the environmental footprint of our products. Help us by disposing of waste in a way that causes minimum environmental impact.

Disposing of electrical and electronic equipment

A product that is labeled as follows cannot be disposed of in normal household waste after it has come to the end of its life. Even disposal via the municipal collection points for waste electrical and electronic equipment is not permitted.



Figure 13-1: Labeling in line with EU directive WEEE

Rohde & Schwarz has developed a disposal concept for the eco-friendly disposal or recycling of waste material. As a manufacturer, Rohde & Schwarz completely fulfills its obligation to take back and dispose of electrical and electronic waste. Contact your local service representative to dispose of the product.

Disposing of batteries

A product that contains a battery cannot be disposed of in the normal household waste after it has come to the end of its service life. It is labeled as follows:



Figure 13-2: Disposal information in line with EU battery directive

Dispose of batteries as specified by the local waste disposal agency. Alternatively, you can contact the Rohde & Schwarz local service representative.

For information on returning batteries to Rohde & Schwarz subsidiaries, see "[Handling batteries safely](#)" on page 13.

Annex

A Web GUI reference

To start the web GUI for configuration tasks, open a browser on your PC, tablet or smartphone and enter the following URL:

http://192.168.137.1/

The web GUI offers the following pages for configuration tasks:

- "Home"
- "Configuration"
- "File Transfer"
- "Options"
- "Update"
- "Backup"
- "Restart"
- "Help"
- "OSA"

A.1 Home

The "System" window consists of the following tabs.

• Overview	153
• IP settings	155
• HW info	156

A.1.1 Overview

The "Overview" tab displays the following basic settings of the R&S TSMA6B.

Device Info	154
L Type	154
L Material No.	154
L Serial No.	154
L Computer Name	154
L Mode of Operation (Overview)	154
L Bluetooth/WLAN	154
FW/SW Version	154
L HW	154
L Image	154
L Firmware	155
L NESTOR	155

L ROMES.....	155
L EDGE.....	155
L Windows Update Installer.....	155
L Microsoft Edge.....	155
L TSME Device Manager.....	155
L SmartONE.....	155
Battery Info.....	155
L Battery 1.....	155
L Battery 2.....	155
L Battery Life Time.....	155
L Mainboard Temperature.....	155
Status.....	155

Device Info

General device info

Type ← Device Info

Type of instrument

Material No. ← Device Info

R&S order number of the device

Serial No. ← Device Info

Serial number of the device

Computer Name ← Device Info

Computer name of the R&S TSMA6B (read-only). The name consists of a fixed part (TSMA6B) and a variable part (serial number).

Example: R&S TSMA6B-<Serial Number>

NOTE: The serial number can be found on the bottom side of the device.

Mode of Operation (Overview) ← Device Info

Selected mode of operation

Bluetooth/WLAN ← Device Info

Activity status of Bluetooth and WLAN

BT Bluetooth activity status ON/OFF

WLAN WLAN activity status ON/OFF

AP WLAN access point activity status ON/OFF

FW/SW Version

Version information of installed firmware / software / Windows image components

HW ← FW/SW Version

Hardware revision

Image ← FW/SW Version

Windows image version

- 1st number is the version of the basic image
- 2nd number is the version of the device installation

Firmware ← FW/SW Version

Firmware version

NESTOR ← FW/SW Version

Installed R&S NESTOR version (optional)

ROMES ← FW/SW Version

Installed R&S ROMES version (optional)

EDGE ← FW/SW Version

Version of TSM A x EDGE setup file

Windows Update Installer ← FW/SW Version

Version of Windows update installer

Microsoft Edge ← FW/SW Version

Installed Microsoft Edge browser version

TSME Device Manager ← FW/SW Version

Installed R&S TSME Device Manager version (optional)

SmartONE ← FW/SW Version

Installed R&S SmartONE version (optional)

Battery Info

Battery status if a battery pack unit is connected to the device.

Battery 1 ← Battery Info

Charging state of battery 1.

Battery 2 ← Battery Info

Charging state of battery 2.

Battery Life Time ← Battery Info

Estimated remaining battery lifetime.

Mainboard Temperature ← Battery Info

Current temperature of the mainboard.

Status

Current status of the measurement

A.1.2 IP settings

This tab lists the IP addresses of all available LAN / WLAN adapters.

LAN	156
SCAN (Int.)	156
LAN SCAN	156
LAN EXT2 / EXT3 / EXT 5 / EXT6	156
WLAN AP (Overview)	156

LAN

IP address of the remote LAN port

SCAN (Int.)

IP address of the internal scanner link

LAN SCAN

IP address of the "SCAN" port

LAN EXT2 / EXT3 / EXT 5 / EXT6

IP addresses of the external LAN adapter ports.

- R&S TSPC-U2L4: LAN EXT2, 3, 5, 6
- R&S TSPC-USL2: LAN EXT 5, 6

WLAN AP (Overview)

IP address of the WLAN access point.

A.1.3 HW info

The "HW Info" tab lists hardware-related information for the assembled modules.

- Internal scanner component
- Battery pack unit (if connected)
- RF downconverter (if connected)

Scanner Info	157
L MAC Address	157
L IP Address (Scanner)	157
L Available Config	157
L Used Config	157
Correction Data	157
L Version	157
L Date	157
L TCXO Date	157
Module Info	157
L Controller Board	157
L RF Board	157
L Mainboard	157
L Batterypack	157
CPU Info	158
Down Converter Info	158
L Available Config	158
L Used Config	158

L Used CLPD Version.....	158
Correction Data (Downconverter).....	158
L Version.....	158
L Date.....	158
Module Info (Downconverter).....	158
L Controller Board.....	158
L RF Board.....	158

Scanner Info

Displays IP and configuration settings of the internal scanner device.

MAC Address ← Scanner Info

MAC address of the internal scanner device.

IP Address (Scanner) ← Scanner Info

IP address of the internal scanner device.

Available Config. ← Scanner Info

All firmware versions which are stored on the internal scanner device.

Used Config. ← Scanner Info

Currently used firmware version on the internal scanner device.

Correction Data

Information about the calibration status of the scanner device.

Version ← Correction Data

Version of the scanner correction data.

Date ← Correction Data

Date of the scanner correction data.

TCXO Date ← Correction Data

Date of the TCXO correction data.

Module Info

Version info of the various scanner modules.

Controller Board ← Module Info

Serial number and product change index of the controller board.

RF Board ← Module Info

Serial number and product change index of the RF board.

Mainboard ← Module Info

Serial number and product change index of the mainboard.

Batterypack ← Module Info

Serial number and product change index of the battery pack module (TSMA6-BP).

CPU Info

CPU system information

Down Converter Info

System information of the connected downconverter device.

Available Config. ← Down Converter Info

All stored firmware versions on the downconverter device.

Used Config. ← Down Converter Info

Currently used firmware version on the downconverter device.

Used CLPD Version ← Down Converter Info

Active CPLD version on the downconverter device.

Correction Data (Downconverter)

Information about the calibration status of the downconverter device.

Version ← Correction Data (Downconverter)

Version of the downconverter correction data.

Date ← Correction Data (Downconverter)

Date of the downconverter correction data.

Module Info (Downconverter)

Displays version info of the various downconverter modules.

Controller Board ← Module Info (Downconverter)

Serial number and product change index of the controller board.

RF Board ← Module Info (Downconverter)

Serial number and product change index of the RF board.

A.2 Configuration

A.2.1 System

The "System" window consists of the following tabs.

- [Mode](#)..... 159
- [Power](#)..... 159
- [RF band](#)..... 160
- [Password](#)..... 160
- [Watchdog](#)..... 161

A.2.1.1 Mode

The "Mode" tab is used to configure and read back the selected mode of operation.

Mode of Operation	159
Current Measurement	159

Mode of Operation

Set of radio buttons for all supported modes of operation. The desired measurement mode is selected and activated by pressing "Submit". The selected mode is automatically started after each power-up as long as not reconfigured by the user.

In "PC Mode", no active measurement is selected in autostart.

Current Measurement

Status information and action buttons for the selected mode of operation.

A.2.1.2 Power

The "Power" tab displays all settings related to the power on/power off scenarios.

Startup Settings	159
L Auto Power ON	159
L Remember Last State	159
Delayed System Start	159
Sleep Mode Settings	159
Battery	160
Shutdown Settings	160
L Auto Power Off	160

Startup Settings

Configures different startup sequences.

Auto Power ON ← Startup Settings

The device is starting automatically when DC power is available at the DC IN connector or at the docking connector for the battery pack unit.

Remember Last State ← Startup Settings

When the device was powered down in the previous measurement session, then the device keeps this state when DC power is applied again.

Delayed System Start

Note: To support this mode, connect a R&S TSM6B battery pack.

The delay time is configured at the R&S TSM6x. After pressing "Activate" and "Shutdown", the device enters sleep mode and starts after the configured delay. The sleep mode is indicated with a green blinking "Mode" LED.

Sleep Mode Settings

Note: To support this mode, connect a R&S TSM6B battery pack.

If activated, the device enters sleep mode after powering down. The CPU LAN port remains powered to access the device via Intel ATM.

Battery

Press "Start" to write the battery info into the firmware log file.

Shutdown Settings

Configures the auto-power off behavior of the R&S TSMA6x.

Note: To support this mode, connect a R&S TSMA6B battery pack.

Auto Power Off ← Shutdown Settings

To enable auto power off, select "Auto Power Off" and enter the desired delay in seconds. Press "Submit Timeout" to enable this feature.

The R&S TSMA6x with a connected battery pack unit will automatically power down after the configured time delay when the DC power is removed from the R&S TSMA6B battery pack.

A.2.1.3 RF band

With the "RF Band" tab, you can configure and recall the desired RF band for the scanner if a limited band option is installed for the scanner.

Current Configuration	160
New Configuration	160

Current Configuration

Current valid band configuration

New Configuration

Selects a specific band.

A.2.1.4 Password

With the "Password" tab, you can change the Windows password.

Change Instrument Password	160
L Current Password	160
L New Password	160
L Confirm New Password	160

Change Instrument Password

Changes and confirms a new password for the R&S TSMA6B.

Current Password ← Change Instrument Password

Enter the current valid password.

New Password ← Change Instrument Password

Enter a new password.

Confirm New Password ← Change Instrument Password

To confirm the new password, enter it again.

A.2.1.5 Watchdog

In the "Watchdog" tab, you can define the behavior of the watchdog.

[Watchdog Settings](#)..... 161

Watchdog Settings

By default, the internal watchdog is disabled and does not trigger a restart if the given watchdog time interval is asserted.

A.2.2 Connectivity

The "Connectivity" window consists of the following tabs.

- [Bluetooth](#)..... 161
- [WLAN](#)..... 162
- [WLAN AP](#)..... 163
- [LAN](#)..... 164
- [LAN SCAN](#)..... 165
- [LAN EXT2 / EXT3 / EXT5 / EXT6](#)..... 165

A.2.2.1 Bluetooth

The "Bluetooth" tab is used for configuration and pairing with external Bluetooth devices.

[Bluetooth Connection](#)..... 161

- L [Status \(Bluetooth\)](#)..... 161
- L [Visibility](#)..... 161
- L [Bluetooth Device\(s\)](#)..... 161

Bluetooth Connection

Specifies the configuration details of a Bluetooth adapter.

Status (Bluetooth) ← Bluetooth Connection

Switch The Bluetooth adapter on or off.

Note: The Bluetooth buttons are disabled when the WLAN/Bluetooth switch in position "Off" (right position) "[WLAN/Bluetooth on/off](#)" on page 36. Move the switch to position (left position) to make the Bluetooth settings configurable via web-GUI.

Visibility ← Bluetooth Connection

The Bluetooth adapter can be set to visible or hidden for external devices.

Bluetooth Device(s) ← Bluetooth Connection

Press "Refresh" to update visible Bluetooth devices. For pairing a device, select it in the file box and press "Connect".

A.2.2.2 WLAN

The "WLAN" tab is used to recall and configure settings of the embedded WLAN module.



The "WLAN" tab is only available if the switch WLAN/Bluetooth is in position "On".

WLAN Adapter.....	162
L Status (WLAN Adapter).....	162
L Permanent.....	162
L SSID.....	162
L Network Key.....	162
L TCP/IP Mode (WLAN Client).....	162
WLAN Settings.....	163
L Wireless Mode.....	163
L Preferred Band.....	163
L Wireless Mode Ext.....	163

WLAN Adapter

Specifies the configuration details for the WLAN adapter.

Status (WLAN Adapter) ← WLAN Adapter

Switch the WLAN adapter on and off.

Status = On	The WLAN is on.
Status = Off and Permanent = Off	The WLAN is switched off for the current session. After the next power cycle, the WLAN is switched on again.
Status = Off and Permanent = On	The WLAN is permanently switched off even after a power cycle.

Note: The WLAN buttons are disabled when the WLAN/Bluetooth switch in position "Off" (right position) "[WLAN/Bluetooth on/off](#)" on page 36. Move the switch to position (left position) to make the WLAN settings configurable via web-GUI.

Permanent ← WLAN Adapter

If enabled, the WLAN is permanently on.

SSID ← WLAN Adapter

Click "Refresh" to scan for available WLAN access networks. Available networks are listed in the file select box.

Network Key ← WLAN Adapter

Enter the network key to connect with the selected WLAN network as a client.

TCP/IP Mode (WLAN Client) ← WLAN Adapter

The IP address configuration in a client connection can be switched between "DHCP" (receive IP address from host) and static IP ("Static").

Enter the static IP configuration in the dialog below.

- IP address
- Subnet Mask
- Default Gateway
- DNS Server

It is possible to specify a primary and a secondary DNS server.

WLAN Settings

Specify the WLAN standard and the preferred band. If you change the default settings, the new settings are marked orange. To reset the default settings, these settings are marked green.

Wireless Mode ← WLAN Settings

Recall and change the settings of the WLAN adapter in this section. The following modes are supported:

- 5 GHz 802.11a
- 2.4 GHz 802.11b
- 2.4 GHz 802.11g
- 2.4 GHz 802.11b/g (default)
- Dual Band 802.11a/g
- Dual Band 802.11a/b/g

To change the mode, select "Change".

To reset the default settings, select "Default".

Preferred Band ← WLAN Settings

Select the following preferred band settings.

- No Preference
- Prefer 2.4 GHz band (default)
- Prefer 5 GHz band

To change the preferred band, select "Change".

To reset the default setting, select "Default".

Wireless Mode Ext ← WLAN Settings

Select one of the following wireless mode settings.

- Disabled
- 802.11n
- 802.11ac
- 802.11ax

To change the mode, select "Change".

To reset the default settings, select "Default".

A.2.2.3 WLAN AP

The "WLAN AP" tab is used to recall and configure settings of the WLAN access point.

[WLAN Access Point](#)..... 164

L Status (WLAN AP)	164
L SSID	164
L Current Network Key	164
L New Network Key	164
L Confirm Network Key	164

WLAN Access Point

Specify the configuration details for the WLAN access point.

Status (WLAN AP) ← WLAN Access Point

Status = On	The WLAN access point is on.
Status = Off and Permanent = Off	The WLAN access point is switched off for the current session. After the next power cycle, the WLAN access point is switched on again.
Status = Off and Permanent = On	The WLAN access point is permanently switched off even after a power cycle.

Note: The WLAN buttons are disabled when the WLAN switch in position "Off" (right position) "[WLAN/Bluetooth on/off](#)" on page 36. Move the switch to position (left position) to make the WLAN settings configurable via web-GUI.

SSID ← WLAN Access Point

Enter SSID and network key and press "Submit" to change the default settings.

- Default SSID: *TSMA6B-<DeviceSerialNumber>*
- Default Key: *instrument*

Current Network Key ← WLAN Access Point

Enter the current valid network key for the specified SSID.

New Network Key ← WLAN Access Point

Enter a new network key for the specified SSID.

Confirm Network Key ← WLAN Access Point

To confirm the new network key, enter it again.

A.2.2.4 LAN

Configure the "LAN" port IP of the R&S TSMA6B. The port is marked with the LAN symbol.



LAN Connection	164
L State (LAN)	165
L R&S TSMA6BTCP/IP Mode (LAN)	165

LAN Connection

Specify the configuration details for the LAN connection.

State (LAN) ← LAN Connection

Displays the state of the LAN connection.

- Connected
- Disconnected

R&S TSMA6BTCP/IP Mode (LAN) ← LAN Connection

The IP address configuration can be switched between "DHCP" (receive IP address from host) and static IP ("Static").

Enter the static IP configuration in the dialog below.

- IP address
- Subnet Mask
- Default Gateway
- DNS Server

It is possible to specify a primary and a secondary DNS server.

A.2.2.5 LAN SCAN

Configure the "LAN SCAN" port of the R&S TSMA6B. This is the port marked with "SCAN".

LAN Connection (LAN SCAN).....	165
L State (LAN SCAN).....	165
L TCP/IP Mode (LAN SCAN).....	165

LAN Connection (LAN SCAN)

Specify the configuration details for the additional Gbit LAN connection.

It is used to connect the R&S TSMA6B to a separate R&S TSME6 as a second scanner, which is used for MIMO scenarios and increase bandwidth and measurement rate.

State (LAN SCAN) ← LAN Connection (LAN SCAN)

Displays the state of the LAN SCAN connection.

- Connected
- Disconnected

TCP/IP Mode (LAN SCAN) ← LAN Connection (LAN SCAN)

The IP address configuration in a client connection can be switched between "DHCP" (receive IP address from host) and static IP ("Static").

Enter the static IP configuration in the dialog below.

- IP address
- Subnet Mask
- Default Gateway
- DNS Server

It is possible to specify a primary and a secondary DNS server.

A.2.2.6 LAN EXT2 / EXT3 / EXT5 / EXT6

Configure the external LAN adapter ports.



The tabs for the additional LAN ports are only visible if you connect a USB to LAN adapter to the R&S TSM6B.

LAN Connection (EXT2 / EXT3 / EXT5 / EXT6).....	166
L State (EXT2 / EXT3 / EXT5 / EXT6).....	166
L TCP/IP Mode (EXT2 / EXT3 / EXT5 / EXT6).....	166

LAN Connection (EXT2 / EXT3 / EXT5 / EXT6)

Specify the configuration details for the external LAN adapter ports.

- R&S TSPC-U2L4: LAN EXT2, 3, 5, 6
- R&S TSPC-USL2: LAN EXT5, 6

State (EXT2 / EXT3 / EXT5 / EXT6) ← LAN Connection (EXT2 / EXT3 / EXT5 / EXT6)

Displays the state of the external LAN adapter ports.

- Connected
- Disconnected

TCP/IP Mode (EXT2 / EXT3 / EXT5 / EXT6) ← LAN Connection (EXT2 / EXT3 / EXT5 / EXT6)

The IP address configuration can be switched between "DHCP" (receive IP address from host) and static IP ("Static").

Enter the static IP configuration in the dialog below.

- IP address
- Subnet Mask
- Default Gateway
- DNS Server

It is possible to specify a primary and a secondary DNS server.

A.3 File transfer

The "File Transfer" window offers the following functions:

- Uploads and downloads of files to/from the R&S TSM6B.
- Download of the Vicom sample application to an Android device.

File Transfer.....	166
L Upload.....	167
L Download.....	167
Sample App.....	167
L Download rViCom SampleApp.....	167
App Log.....	167
L Firmware Log File.....	167
L Firmware Log Trace.....	167

File Transfer

Specifies the properties for uploading and downloading files.

Upload ← File Transfer

Specifies the file (e.g. workspace file) to be transferred from a connected device to the R&S TSM6B. The default path is `D:\Upload`.

Note: The maximum file size for the upload is 2048 MB.

With "Apply Path", you can specify a user-specific path for uploading files.

With "Restore Default", the default path `D:\Upload` is selected.

Download ← File Transfer

Specifies the measurement data file to be transferred from the R&S TSM6B (`D:\Download`) to a connected device.

With "Apply Path", you can specify a user-specific path for uploading files.

With "Restore Default", the default path `D:\Upload` is selected.

Sample App

Specifies the download of the sample app.

Download rViCom SampleApp ← Sample App

Specifies the sample app file (`*.apk`) to be downloaded to the connected Android device.

App Log

The "App Log" tab offers access to firmware log files.

Firmware Log File ← App Log

Select a log file and download it to a local directory.

Firmware Log Trace ← App Log

View into the current firmware log file.

A.4 Options

The "Options" window consists of the following tabs.

- [Available](#).....167
- [Install](#).....168

A.4.1 Available

The "Available" tab gives an overview of available active and inactive scanner and NESTOR (if installed) licenses.

Option Type	168
Option Material No	168
Activation Type	168
Valid From / Valid To	168
Option Index	168

Option Type

Type name of installed license key

Option Material No.

R&S order number of the SW license

Activation Type

Activation type of license key (temporary or permanent)

Valid From / Valid To

Start and expiration date of the license key

Option Index

Index number of the license key

A.4.2 Install

The "Install" tab is used to install various license key files on the R&S TSM6B.

Install NESTOR Options	168
Install Scanner Options	168

Install NESTOR Options

Enter the NESTOR license key and press "Install" to activate a new license.

Install Scanner Options

Install a scanner option. Two different methods are supported.

- License keycode: enter the license number and press "Install"
- License key file: select the license key file (*.xml) with the "Browse" button and press "Install XML File"

A.5 Update

Via the "Update" page, you can install all the related software and firmware packages for the R&S TSM6x.

**Prerequisites**

- The setup file must be located in the root directory of a USB data stick.

Select <FW/SW> Setup File	168
---	-----

Select <FW/SW> Setup File

Select the setup file and press the "Update Software" button.

Categories

- "Firmware Setup File"
- "NESTOR Setup File"

- "Windows Setup File"
- "SmartONE Setup File"
- "ViCom Setup File"
- "EDGE and TSME Tools Setup File"

The progress can be monitored in the status line of the web GUI.

A.6 Backup

Via the "Backup" window, you can create a backup of the R&S TSMA6B system.

Available Backup	169
Delete data partition D:	169
Backup TSMA6B System	169
Install Debian	169
Backup Debian	169
Restore Debian	169

Available Backup

Displays the date of the factory backup.

Delete data partition D:

When switched to "On", the data partition D: \ is deleted during a system recovery.

Backup TSMA6B System

Click "Backup" to create a user backup of the system partition C: \ and data partition D: / if "Delete data partition" is not enabled .

- At first, it is checked if there is enough memory available for the backup.
- You can store only one user backup. An existing user backup is overwritten when running backup again.

Install Debian

Click "Install" to install the Debian system on your R&S TSMA6B. After the successful installation of Debian, the option "Backup Debian" appears.

Backup Debian

Only available if Debian is installed on a R&S TSMA6B.

Click "Backup" to create a user backup of the Debian system.

You must execute this step to prepare the device before capturing a R&S TSMA6B image via an R&S TSMA6B image stick (see [Chapter 10.5.4, "Capturing an image from R&S TSMA6B"](#), on page 120).

Restore Debian

Click "Restore" to restore the last backup of the Debian system.

The Debian installation is recovered after an R&S TSMA6B image recovery from an R&S TSMA6B image stick (see [Chapter 10.5.5, "Applying an image to R&S TSMA6B"](#), on page 122).

A.7 Restart


Via the "Restart" window, you can restart the complete R&S TSMA6B and the scanner unit separately.

System restart	170
PowerCycle	170

System restart

To restart the R&S TSMA6B, click "Restart".

The following message appears.




Click "OK" to reboot the R&S TSMA6B.

PowerCycle

To restart the scanner unit of the R&S TSMA6B, click "PowerCycle".

The following message appears.



Click "OK" to reboot the scanner unit of the R&S TSMA6B.

A.8 Help

The "Help" window displays the online help system of the R&S TSMA6B.

B Introduction to remote ViCom sample app

B.1 Overview

The R&S TSMA6B provides an open remote R&S ViCom interface that allows the integration into Windows and Android-based software tools. Via the R&S Remote ViCom API, it is possible to configure and control TSMA6B scanner measurements from a remote PC / tablet.

The installation of R&S Remote ViCom on the R&S TSMAx is accompanied with an R&S Remote ViCom sample application. The source code for this Android-based App is also available as a subcomponent of the R&S ViCom scanner interface. This ready-to-use application gives the user a quick and easy impression about the capabilities of this API interface.

B.2 Requirements

B.2.1 General requirements

To use this app successfully, check the following requirements.

- An Android device with at least Android 4.4.2 (Android 4.4.4 is recommended)
- A WLAN respectively Bluetooth connection between the Android device and the R&S TSMA6B
- R&S Remote ViCom server on the R&S TSMA6B (default)
- An installed Sample App on the Android device
The version of the R&S Remote ViCom server on the R&S TSMA6B must match the version of the sample App on the Android device.

B.2.2 Preparation

Before starting a scan or test, it is necessary to make sure that a connection can be established.

Download and installation of R&S Remote ViCom sample app

To install the R&S Remote ViCom sample app on an Android device, the following steps must be performed.

1. Navigate to "File Transfer" > "Sample App" > "Download TsmasampleApp".
2. Select the Sample App.

3. Click "Download".
4. Install the Sample App on the Android device.

B.3 Usage

B.3.1 Connection establishment

Start the sample app on the Android device.

B.3.1.1 Connection type selection

To connect to the R&S Remote ViCom server, it is either possible to use a WLAN connection or a Bluetooth connection.

The selection of the connection type depends on the measurement task (see [Chapter B.3.1, "Connection establishment"](#), on page 172).




Figure B-1: Connection Type Selection

B.3.1.2 Server discovery

1. Choose a connection type, as described in [Chapter B.3.1.1, "Connection type selection"](#), on page 172.
2. The server discovery starts and the following dialog appears.




Figure B-2: Active Server Discovery

3. If a server is found, the server will be connected and the name of the server is displayed.




Figure B-3: Successful Server Discovery

4. Choose the server.

If a R&S Remote ViCom server connection could be established, the "Choose scan type" window appears. See [Figure B-4](#).



Figure B-4: Choose scan type

If no server is found, it is possible to start a new scan by selecting "Rescan" in the menu inflater in the top-right corner.



To stop the server discovery, the app has to be closed.

The following scan types are available:

- **GSM RSSI Scan**
It provides a GSM scan by selecting a band and radio channels
- **WCDMA Top-N Pilot Scan**
It provides an UMTS scan by selecting a frequency band and the UARFCN
- **LTE Top Signal Scan**
It provides an LTE scan by selecting the frequency band and the EARFCN
- **Throughput Test**
It provides a throughput test for the connection using a configurable buffer size
- **RF Powerscan**
It provides a spectrum analysis by selecting the frequency range

The RAN technology for which a scan should be performed has to be selected. The selection of the technologies is described in the following chapters.

B.3.2 GSM RSSI scan

B.3.2.1 GSM preferences

To start a GSM RSSI scan, the following steps must be performed.

1. Choose a frequency band.

The channels are set automatically to the maximum range available for the selected band.




Figure B-5: Setting the GSM Preferences

2. If necessary, change the channels manually according to your needs. The input in the "Channels" field can be done like the following.
 - a) Add a single number for one specific channel.
Example: 7
 - b) Add a range of channels.
Example: 1-124
 - c) Add more than one single number separated by semicolon.
Example: 2;4;7;76

- Click "Start scan" to start the scan.

B.3.2.2 GSM scan results

The GSM scan result graph displays one column for each channel selected. The height of a column represents the RSSI value (in dBm).




Figure B-6: GSM Scan Result View

Below the graph the measurement preferences and the status are displayed.

Parameters

Displays the configured preferences for the GSM RSSI scan.

Status

Displays the measurement duration and the measurement rate. The status button displays the following colored states.

- *Green*
The measurement is running and measurement data are received.
 - *Yellow*
The measurement is running but no measurement data are received.
 - *Red*
The measurement was stopped
- To stop the scan, use "Stop scan" in the menu inflator in the top-right corner.

B.3.3 WCDMA Top-N pilot scan

B.3.3.1 WCDMA Top-N pilot preferences

To start a WCDMA scan, the following steps must be performed.

1. Choose a frequency band.

The minimum UARFCN of this band is set automatically.




Figure B-7: Setting the WCDMA Preferences

2. If necessary, change the UARFCN according to your needs.

Note: Due to processing issues, it is not possible to select more than one UARFCN.

3. Click "Start scan" to start the scan.



In the menu inflator on top of the right corner, templates for existing preferences (Munich and surrounding areas) can be selected.

B.3.3.2 WCDMA Top-N pilot scan results

The WCDMA scan result graph displays one column for each SC found by the measurement. The height of a column represents the RSCP value (in dBm).




Figure B-8: WCDMA Scan Result View

Below the graph the measurement preferences and the status are displayed.

Parameters

Displays the configured preferences for the WCDMA scan.

Status

Displays the measurement duration and the measurement rate. The status button displays the following colored states.

- *Green*
The measurement is running and measurement data are received.
- *Yellow*
The measurement is running but no measurement data are received.
- *Red*
The measurement was stopped.

► To stop the scan, use "Stop scan" in the menu inflator in the top-right corner.

B.3.4 LTE top signal scan

B.3.4.1 LTE top signal preferences

To start an LTE scan, the following steps must be performed.

1. Choose a frequency band.
The minimum EARFCN of this band is set automatically.




Figure B-9: Setting the LTE Preferences

2. If necessary, change the EARFCN according to your needs.

Note: Due to processing issues, it is not possible to select more than one EARFCN.

3. Click "Start scan" to start the scan.



In the menu inflator on top of the right corner, templates for existing preferences (Munich and surrounding areas) can be selected.

B.3.4.2 LTE top signal scan results

The LTE scan result graph displays one column for each PCI found by the measurement. The height of a column represents the PBCH RSRP value (in dBm).




Figure B-10: LTE Scan Result View

Below the graph the measurement preferences and the status are displayed.

Parameters

Displays the configured preferences for the LTE scan.

Status

Displays the measurement duration and the measurement rate. The status button displays the following colored states.

- *Green*
The measurement is running and measurement data are received.
- *Yellow*
The measurement is running but no measurement data are received.
- *Red*
The measurement was stopped.

► To stop the scan, use "Stop scan" in the menu inflator in the top-right corner.

B.3.5 Throughput test case

The throughput test case is useful to find out the throughput speed of your connection. This allows to decide, which connection type (WLAN or Bluetooth) should be used.

B.3.5.1 Throughput preferences

To start the throughput test, the following steps must be performed.

1. Specify the parameter "Buffer size (in Byte)".
The default buffer size is 20480 bytes.




Figure B-11: Throughput Preferences

2. Click "Start Test" to start the throughput test.



For WLAN, the optimal buffer size varies between 950.000 byte and 1.000.000 byte.
For Bluetooth, the optimal buffer size varies between 81.000 byte and 165.000 byte.

B.3.5.2 Throughput results

The result of the throughput test case is a line chart with the following axes:

- X-axis
The x-axis displays the number of measurements

- Y-axis
The y-axis displays the corresponding throughput value (kB/s)

The blue line shows the measured values. The orange line represents the visualized average of all values.




Figure B-12: Throughput Result View

Below the graph the following throughput results are displayed.

Results

- Max. Through
Displays the maximum throughput
 - Ave. Through
Displays the average throughput
 - Last Through
Displays the current throughput
- To stop the scan, use "Stop scan" in the menu inflator in the top-right corner.

B.3.6 RF power scan

B.3.6.1 RF power scan references

To start an RF power scan, the following steps must be performed.

1. Specify the parameters "Start Frequency (in Mhz)" and "End Frequency (in Mhz)" to define the frequency range of the RF power scan.
The maximum range is from 350 MHz to 4.400 MHz.




Figure B-13: RF Power Scan References

- Click "Start Test" to start the scan.

B.3.6.2 RF power scan results

The result of the RF power scan is a spectrum of the frequency range set before with the following axes:

- X-axis
The x-axis displays the frequency
- Y-axis
The y-axis displays the power level for each frequency (dBm)




Figure B-14: RF Power Scan Results

Below the graph the measurement preferences and the status are displayed.

Parameters

- Start
Displays the start frequency
- End
Displays the end frequency

Status

Displays the measurement duration and the measurement rate. The status button displays the following colored states.

- *Green*
The measurement is running and measurement data are received.
 - *Yellow*
The measurement is running but no measurement data are received.
 - *Red*
The measurement was stopped
- ▶ To stop the scan, use "Stop scan" in the menu inflator in the top-right corner.

C Managing scanner device with R&S TSME Device Manager

The "R&S TSME Device Manager" is a configuration software tool for scanners of the R&S TSME and R&S TSMA family. This utility is part of the R&S®TSME installation package. It can also be installed together with R&S ROMES, R&S NESTOR and R&S ViCom, and is available for download from the Rohde & Schwarz product website <http://www.rohde-schwarz.com/product/TSMx.html>.

C.1 Installing and managing software license keys - "Options"

All new devices are preconfigured and specified technology and band options are already installed. Only if you obtain additional software options later, you have to enable the options with the corresponding software license keys.

License keys are shipped as a printed "License Keys List". Advance deliveries can consist of a PDF file. Unregistered software licenses can be downloaded from the Rohde & Schwarz website (<https://extranet.rohde-schwarz.com/service>). For details see the "Installation Instructions for Options".

(Note: previously, license keys were shipped as XML files.)

Prerequisites to install software license keys

To install a software license key, the following conditions must apply:

- PC/notebook is connected via Gbit LAN adapter, with Jumbo Frames (9 kB) enabled
- The (registered) software license key must be available

Software license keys are installed using the "R&S TSME Device Manager" ("Options" tab).




Figure C-1: Tab "Options"

For each option, the following information is displayed:



Information for options that are no longer valid because their expiry date has passed is listed as "Inactive Options".

To replace temporary by permanent software license keys, contact your Rohde & Schwarz sales representative.

Table C-1: Software license key information

Label	Description
Option Type	Band or technology option name
Option Material No.	Order number of the option
Option key	Software license key number
Privilege	Usage type (customer, services, demo)
Time Stamp	Time the software license key was installed
License Count	Number of times the (band upgrade) option is installed

Label	Description
Activation Type	Activation can be permanent or temporary
Valid From	Start of validity for temporary license
Valid To	End of validity for temporary license
Time to Expiration	Time left until license expires
Option Index	for internal use only
Format ID	for internal use only

Finding the software license key files

Previously, license keys were shipped as XML files. This function is only available for compatibility reasons.

If you do not know the precise path and filename of the required software license key, you can browse through the host PC's file system directly from the "R&S TSME Device Manager", by selecting the "Browse" button in the "Options" tab.

Entering key codes

Enter the 30-digit keycode from the "License Keys List" in the "Key" field.

Alternatively, if available, copy the keycode from the supplied PDF license key file and paste it in the "Key" field.

To install the software license key on the currently selected R&S TSMA6B, select the "Install" button (see [Figure C-1](#)).

Installing a software license key

The software license key for which you have entered the keycode in the R&S TSME Device Manager is installed on the currently selected R&S TSMA6B when you select the "Install" button. It then appears in the "Active Options" list with its validity dates and other information (see [Figure C-1](#)).

C.2 Configuring measurement bands - "Band Configuration"

Depending on which options are installed, various different bands and technologies can be scanned by the R&S TSMA6B.



Before you can configure the measurement bands you must install all required software license keys, see [Chapter C.1, "Installing and managing software license keys - "Options""](#), on page 183).

The band configuration is stored permanently on the R&S TSMA6B.



When using a R&S TSMA6B with a limited number of measurement bands, you must consider the band configuration of the scanner when planning a measurement task.

The scanner only provides measurement results for those bands that are currently configured on the scanner.

The band configuration is defined in the "Band Configuration" tab of the "R&S TSME Device Manager".

Select the bands that are to be scanned by the R&S TSMA6B in the "Band Table". Which bands are available is independent of the installed *technology* options; all installed technologies can be scanned in all configured bands at the same time.

The *number* of bands available for selection depends on the installed band options.

The screenshot shows the 'R&S TSME Device Manager' application window. The 'Available Devices' section at the top shows the selected device 'R&S® TSME6 100844'. Below this, the 'Band Configuration' tab is active, displaying the following information:

Bands
Changes to the band configuration can not be made randomly; within any 48 hour period, the band configuration may only be changed up to 5 times, where one "configuration change" may consist of several band changes at the same time.

Band Table:	
Current Configuration	New Configuration
1 TETRA	TETRA
2 3500	3500
3 480	480
4 900	900
5 2100	2100

Next 5 Possible Band Changes:

Valid From
1 1970-01-01 01:00
2 1970-01-01 01:00
3 2019-02-08 11:02
4 2023-03-15 16:09
5 2024-03-15 10:13

At the bottom of the 'Band Configuration' section, there is an 'Accept Band Changes' button. Below this, the 'Device Analysis Output' and 'Message Output' sections are visible, showing 0 Errors, 0 Warnings, and 0 Infos.

Figure C-2: Tab "Band Configuration"

The current band configuration for the selected R&S TSMA6B is displayed for reference. It remains active until you select the "Accept Band Changes" button.



Band configuration changes

Changes to the band configuration cannot be made randomly. Within any 48-hour period, you can change the band configuration only up to 5 times (where one "configuration change" can consist of several band changes at the same time, see ["Applying band configuration changes"](#) on page 187).

A counter is decremented after each (applied) change. How many changes have already been performed and how many are still possible within the current timeframe is displayed at the bottom of the "Band Configuration" tab of the "R&S TSME Device Manager".

Red dates indicate the changes recently made, while green dates indicate possible changes left.

Applying band configuration changes

Changes to the band configuration are only applied to the R&S TSMA6B when you select the "Accept Band Changes" button in the "Band Configuration" tab of the "R&S TSME Device Manager".

Only then the counter for possible band changes (within 48 hours) is decremented.

C.3 Obtaining firmware and correction data updates - "Updates"

The "R&S TSME Device Manager" is always provided with the most recent basic FPGA (section 0). If a newer one becomes available due to security or functional issues, a message is indicated in the "Device Analysis Output" at the bottom of the "R&S TSME Device Manager" window. In this case, and only in this case, it is recommended that you install this update on your R&S TSMA6B.

Keep the correction data on your R&S TSMA6B always up to date. Available updates are also indicated in the "Device Analysis Output" and it is recommended that you install them.



If the downconverter is correctly connected, the basic FPGA and correction data for the downconverter are also displayed in a second line.

NOTICE

Risk of inoperability of device due to FPGA update

Before performing an update, make sure you have a stable power supply and a stable LAN connection. Both updates take a few minutes.

If the LAN connection is interrupted during an FPGA update, the device can become inoperable. Thus, only install such an update if it is explicitly recommended by a message in the "Device Analysis Output" of the "R&S TSME Device Manager" or by the Rohde & Schwarz support center.

You can update the basic FPGA or the correction data on your R&S TSMA6B directly from the "R&S TSME Device Manager", in the "Update" tab. The currently installed versions and the newest supported version (of the FPGA) or the minimum recommended version (of the correction data) are indicated.




Figure C-3: Tab "Updates"

To perform an update

1. In the "R&S TSME Device Manager", select the serial number of the R&S TSMA6B you want to update.
2. In the "Updates" tab, select the "Update" button for either the "Basic FPGA" or the "Correction Data".

When updating the correction data, you are asked to select a directory to store a backup of your current correction data.

C.4 Aligning R&S TSMA6B manually - "Self Alignment"

During self-alignment, the R&S TSMA6B determines alignment values for the I/Q filter, ADC offset and the I/Q imbalance.

Configuring downconverter R&S TSME30DC/TSME44DC - "Downconverter Configuration"




Figure C-4: Tab "Self Alignment"

Start Self Alignment

To start the self-alignment manually, select the "Start Self Alignment" button in the "Self Alignment" tab of the "R&S TSME Device Manager".

C.5 Configuring downconverter R&S TSME30DC/TSME44DC - "Downconverter Configuration"

Within this tab, you can configure the IF output receiver and the RF input antenna of the R&S TSME30DC downconverter. For details, refer to the *R&S TSME30DC / R&S TSME44DC Getting Started*.

Configuring downconverter R&S TSME30DC/TSME44DC - "Downconverter Configuration"




Figure C-5: Tab "Downconverter Configuration"

IF Output Receiver Configuration

Specify the configuration of the IF output connectors of the R&S TSME30DC/TSME44DC.

RF Input Antenna Configuration

- Specify the configuration of the RF input antenna connectors of the R&S TSME30DC.
 - Bypass Antenna (< 6 GHz)
 - mmWave Antenna 1 (24 GHz to 27.5 GHz)
 - mmWave Antenna 2 (27 GHz to 30 GHz)

For R&S ViCom and R&S ROMES, the API only allows the configuration of frequencies of activated antenna ports. For the overlapping frequency range 27 GHz to 27.5 GHz, the "mmWave Antenna 1" is used by default.

- Specify the configuration of the RF input antenna connectors of the R&S TSME44DC.
 - Bypass Antenna (< 6 GHz)
 - mmWave Antenna 1 (24-44 GHz)

For R&S ViCom and R&S ROMES, the API only allows the configuration of frequencies of activated antenna ports.

Accept Configuration

To confirm the current configuration settings, select the "Accept Configuration" button.

Index

A

Application cards	18
Application notes	18

B

Band Options	
Available	41
Brochures	18

C

Casing	
Labels	14
Customer support	148

D

Data sheets	18
Dead reckoning	38
Device data	
Self Alignment	189
Updating	187
Device Manager	
Downconverter Configuration	190
Finding software license keys	185
Installing software license keys	185
Self Alignment	189
Software license keys	185
Updating device data	187

G

Getting started	17
GSM Scan	174
Preferences	174
Results	175

H

HDMI connector	37
Help	17

L

Labels on casing	14
LAN	
Environment	48
LED	
LAN Connector	37
LTE Scan	177
Preferences	177
Results	178

M

Multi-GNSS	38
------------------	----

N

Network	
Environment	48

O

Open source acknowledgment (OSA)	18
Option Concept	
Band Options	40
R&S NESTOR	41
Technology Options	40

R

R&S TSMA6B Option concept	39
Release notes	18
Remote rViCom	
Requirements	171
Usage	172
Remote ViCom	171
Removable disk option	24
RF Power Scan	180
References	180
Results	181

S

Safety instructions	11, 17
Warning messages	16
Software license keys	185
Finding	185
Information	130, 184
Prerequisites	183
Updating	185
Specification	18

T

Technology Options	
Available	40
Throughput Test Case	179
Preferences	179
Results	179

U

User manual	17
-------------------	----

V

Videos	17
--------------	----

W

Warning messages	16
WCDMA Scan	176
Preferences	176
Results	176
White papers	18