# MHL (Mobile high-definition link)

# Technical overview


#### Mobile high-definition link

MHL is the new leading mobile device interface for transmitting video and audio. This interface can connect smartphones, tablet PCs and video cameras with display equipment such as TV sets, projectors and monitors. MHL uses the micro USB port which is already available on many mobile devices. The USB interface can be used for data connections to a PC as usual. When the built-in MHL transmitter chip recognizes an MHL-capable receiver at the other end, it switches into the MHL transmit mode. The MHL transmitter then sends the AV data over two of the five pins on the micro USB port. The control signals are transmitted via one of the other pins. The 5 V line is used to charge the mobile device while

#### **Key features of MHL:**

- I HD video and digital audio: 1080p/60 video and up to 192 kHz 7.1 surround audio
- Utilization of existing connectors
- Low pin-count interface: HD video and digital audio over a 5-pin interface which includes control and power Provision of power to the mobile device: 5 V and 900 mA
- I Content protection: full support of high-bandwidth digital content protection (HDCP)

#### Interfaces and pin assignment



#### MHL link control bus (CBUS)

- The point-to-point single-wire CBUS provides the following functionality:
- A mechanism allowing source and sink devices to detect connectivity to an MHL-compliant sink and source device, respectively A communications channel for DDC commands that is used by an MHL source device to determine the capabilities and characteristics


An MHL sideband channel (MSC) is provided for higher-level user functions such as automatic setup tasks or tasks typically associated with

- of the sink device by reading the EDID data structure
- A communications channel for DDC commands that is used by an MHL source device to initiate all register reads and writes required for content protection
- infrared remote control usage: remote control protocol (RCP), UTS-8 character protocol (UCP), request action protocol (RAP) The CBUS has sufficient headroom to be used for other protocols in the future.

#### MHL voltage bus (VBUS)

The VBUS provides a minimum of 5 V/900 mA power between sink (e.g. TV) and source (e.g. mobile phone).





### TMDS protocol video and audio formats

Supported video formats			3D video modes				Pixel encoding	Supported color spaces
Index	Mode	Refresh	Index	Mode	Refresh	3D mode	YCbCr 4:2:2	SD: ITU-R Rec. BT.601
1	640×480 (VGA)	59.94/60	4	1280×720p		top-bottom	YCbCr 4:4:4	HD: ITU-R BT.709-5
2,3	720×480p	59.94/60				frame	RGB 4:4:4	Additional: xvYCC, sYCC601,
17,18	720×576p	50				sequential		AdobeYCC601, AdobeRGB
4	1280×720p	59.94/60	19 5	1280×720p	50	top-bottom		
19	1280×720p	50				frame	Audio formats	
5	1920×1080i	59.94/60		1920×1080i		sequential left-right	L-PCM 8 channel aud	dio
20	1920×1080i	50	20	1920×1080i		left-right	Channel assignment in line with CEA-861E	
16	1920×1080p	59.94/60		1920×1080p		top-bottom	Supported audio sample rates	
31	1920×1080p	50				frame	32 kHz	48 kHz
34	1920×1080p	30				sequential	44.1 kHz	96 kHz
6,7	720 (1440)×480i	59.94/60					88.2 kHz	192 kHz
21,22	720 (1440)×576i	50					176.4 kHz	

TMDS is used to carry all audio and video data as well as auxiliary data (such as InfoFrame packets) that describes the active audio and video streams. The bit stream is modulated by a clock signal. In 24-bit mode, MHL uses a single differential channel to transmit TMDS data that, for example, is carried over three different channels in DVI. The incoming three-channel data needs to be packed into one TMDS channel at the TX end and unpacked into three channels at the RX end. There is one TMDS encoder at the TX end and one TMDS decoder at the RX end. TX data is multiplexed into a single lane prior to being encoded. RX data is decoded prior to being demultiplexed into three lanes. In PackedPixel mode, only two channels are multiplexed: channel 0 and channel 1. One clock period of the MHL clock equals two periods of the pixel clock. Each period of the MHL clock transmits four TMDS characters.

CBUS = MHL link control bus, DVI = digital visual interface, E-EDID = enhanced extended display identification data, GND = ground, HD = high definition, HDCP = high-bandwidth digital content protection, HDMI = high definition multimedia interface, MHL = mobile highdefinition link, MSC = MHL sideband channel, RAP = request action protocol, RCP = remote control protocol, SD = standard definition, TMDS = transition-minimized differential signaling, UCP = UTS-8 character protocol, USB = universal serial bus, VBUS = MHL voltage bus

Rohde & Schwarz as a valued partner of consumer electronics manufacturers offers test and measurement solutions for MHL.

## Rohde & Schwarz solutions for MHL












R&S®VTC video test center

www.the-av-experts.com









## high-definition link) Technical overview MHL (Mobile

About Rohde & Schwarz

Rohde & Schwarz is an independent group of companies specializing in electronics. It is a leading supplier of solutions in the fields of test and measurement, broadcasting, radiomonitoring and radiolocation, as well as secure communications. Established more than 75 years ago, Rohde & Schwarz has a global presence and a dedicated service network in over 70 countries. Company headquarters are in Munich, Germany.

Environmental commitment

1 Energy-efficient products
1 Continuous improvement in environmental sustainability
1 ISO 14001-certified environmental management system

Certified Quality System ISO 9001



# Rohde & Schwarz GmbH & Co. KG www.rohde-schwarz.com

Regional contact

| Europe, Africa, Middle East | +49 89 4129 12345 |
| Customersupport@rohde-schwarz.com |
| North America | 1 888 TEST RSA (1 888 837 87 72) |
| customer.support@rsa.rohde-schwarz.com |
| Latin America | +1 410 910 79 88 |
| customersupport.la@rohde-schwarz.com |
| Asia/Pacific | +65 65 13 04 88 |
| customersupport.asia@rohde-schwarz.com |
| China | +86 800 810 8228/+86 400 650 5896 |
| customersupport.china@rohde-schwarz.com |

ademark of Rohde & Schwarz GmbH & Co. KG
ranarks of the owners | Printed in Germany (as)
rsion 04.00 | July 2013 |
finition Link) Technical Overview
a limits is not binding | Subject to change
& Schwarz GmbH & Co. KG | 81671 München, Germa



